Universidade de São Paulo
Instituto de Física

Diagnóstico de Plasma em Tokamak Utilizando Ondas de Alfvén

Marcos Antonio Albarracin Manrique

Orientador: Prof. Dr. Ricardo Magnus Osório Galvão

Tese de doutorado apresentada ao Instituto de Física
para a obtenção do título de Doutor em Ciências.

Banca Examinadora:

Prof. Dr. Ricardo Magnus Osório Galvão Orientador (IFUSP)
Prof. Dr. Artour Elfimov (IFUSP)
Prof. Dr. Zwinglio de Oliveira Filho (IFUSP)
Prof. Dr. Homero Santiago Maciel (UNIVAP)
Prof. Dr. Antonio de Pádua Brito Serbeto (UFF)

São Paulo
2015

FICHA CATALOGRÁFICA
Preparada pelo Serviço de Biblioteca e Informação
do Instituto de Física da Universidade de São Paulo

Manrique, Marcos Antonio Albarracin

Diagnóstico de plasma em Tokamak utilizando ondas de Alfvén. São Paulo, 2015.

Tese (Doutorado) – Universidade de São Paulo.
Instituto de Física. Depto. Física Aplicada.

Orientador: Profº. Drº. Ricardo Magnus Osório Galvão

Área de Concentração: Física de Plasmas.

Unitermos: 1. Física; 2. Eletromagnetismo; 3. Física computacional; 4. Física experimental; 5. Fusão nuclear.

USP/IF/SBI-073/2015

University of Sao Paulo
Institute of Physics

Plasma Diagnostic in Tokamaks Using Alfvén Waves

Marcos Antonio Albarracin Manrique

Supervisor: Prof. Dr. Ricardo Magnus Osório Galvão

Doctoral thesis presented to the
Institute of Physics to obtain the title
of Doctor in Science.

Thesis Defence Committee:

Prof. Dr. Ricardo Magnus Osório Galvão Orientador (IFUSP)
Prof. Dr. Artour Elfimov (IFUSP)
Prof. Dr. Zwinglio de Oliveira Filho (IFUSP)
Prof. Dr. Homero Santiago Maciel (UNIVAP)
Prof. Dr. Antonio de Pádua Brito Serbeto (UFF)

Sao Paulo
2015

To God, my Mother and my big love, my wife Maria Izabel with gratitude.

Acknowledgements

I would like to thank my mother Rosa and my wife Maria Izabel for their love and support.

For my wife's family, my mother-in-law Terezinha, my sister-in-law Marília her husband Joni and her son Miguel and father-in-law Silva for their support and affection.

I am very grateful to my supervisor Dr. Ricardo M. Osório Galvão for his patiente and dedication in this work.

The author wishes to express his special thanks to Dr. Leonid Ruchko, whose thoughtful supervision provided continuing guidance for this work.

I would like to thank the entire group of the Plasma Physics Laboratory of University of Sao Paulo, MSc. Alexandre Machado de Oliveira, Dr. António M. Marques Fonseca, Dr. Artour Elfimov, Dr. Carlos J. Amado Pires, Dr. Cássio H. dos Santos Amador, MSC. Diego Sales de Oliveira, Eleonora V. Domingos Lo Duca, MSc. Gilson Ronchi, Dr. Iberê Luiz Caldas, Dr. Ivan Cunha Nascimento, Dr. José Helder F. Severo, Dr. Juan Iraburu Elizondo, MSc. Leonardo Cunha Jerônimo, MSc. Paulo G. P. Pereira Puglia, Dr. René J. Franco Sgalla, Dr. Ruy Pepe da Silva, BSc. Tiago Fernandes, MSc. Victor Cominato Theodoro, MSc. Vinicius Njaim Duarte, Dr. Wanderley Pires de Sá, MSc. Wilson Andres Hernandez Baquero, Dr. Yuri Kuznetsov and Dr. Zwinglio de Oliveira Guimarães Filho. I am very grateful to all my friends inside the IFUSP who were in good and bad times with me during my PhD, Andres, Carlos G., Carlos M., Daniel, David, Dennis, Javier, Hans, Hector, Leonardo, Marlon, Pablo and a special thanks to my friend Wilmer thanks for your friendship and time.

A special thanks from the bottom of my heart for all the staff of post-graduate center (CPG) of the Physical Institute of the University of Sao Paulo, Adriana Noçais Scatolin,

Andrea Wirkus, Cláudia Conde Barioni, Cristiano Araujo Chaves, Éber De Patto Lima, Paula Cristina Rodrigues Mondini, Renata Matsumoto, thanks for the friendship and dedication in their work.

I am grateful to the Dr. Tito Bonagamba and my friends of the Resonance Group LEAR Arthur Gustavo Ferreira de Araújo, Camila Cardoso, Charlie Oncebay Segura, Christian Rivera Ascona, Elton Montrazi, Everton Oliveira, Mariane Barsi Andreeta, Reinaldo Cesar, Roberson Polli, and Rodrigo de Oliveira Silva, for very interesting discussions and collaborations.

I wish to acknowledge the contributions of the numerous people who have contributed to this work, Dr. D. Borba, Dr. J. P. Goedbloed, Dr. G. T. A. Huysmans, Dr. S. Poedts and Dr. S. D. Pinches.

*"The most terrible sin is boredom! ... Here comes the
Day of Judgement, God will call and ask: "Why not
enjoy all the benefits of life? Why so boring?"*

Lev Davidovich Landau, (1908-1968) - Nobel Prize in Physics
in 1962.

"Imagination is more important than knowledge."

Albert Einstein, (1879-1955) - Nobel Prize in Physics in 1921.

Resumo

Neste trabalho é investigada a excitação de modos próprios de Alfvén em tokamaks, utilizando antenas externas à coluna de plasma.

A teoria básica das ondas de Alfvén é revista, incluindo efeitos não ideais, como resistividade. A seguir, o modelo teórico para excitação de ondas de Alfvén numa coluna cilíndrica de plasma, desenvolvido por Kurt Appert, é apresentado em detalhe, como introdução ao problema mais complexo de ondas de Alfvén em plasmas toroidais.

O modelo cilíndrico é implementado em um código numérico, que é utilizado para estudar a excitação de modos globais de Alfvén (GAWs - Global Alfvén Waves), abaixo do chamado Continuo de Alfvén, nos tokamaks TCABR e JET, utilizando uma descrição realista de seus sistemas de antenas.

A seguir é feita uma breve descrição dos auto modos toroidais de Alfvén (TAEs - Toroidal Alfvén Eigenmodes) que são excitados nas brechas do Continuo de Alfvén criadas pela condição de periodicidade em configurações toroidais. A excitação desses modos no tokamak JET é estudada utilizando os códigos HELENA, para reconstrução do equilíbrio magneto-hidrodinâmico, e CASTOR, que calcula os campos perturbados nesse equilíbrio, associados a instabilidades ou modos excitados, dentro do modelo magneto-hidrodinâmico resistivo.

Esse estudo foi feito com o objetivo de determinar, de forma consistente, a qualidade do espectro e as auto-funções associadas a TAEs, com diferentes números toroidais n , excitados pelo atual sistema de antenas do JET.

Em particular, foi investigado em detalhe o efeito das fases das correntes de alimentação dos diferentes módulos (oito) do sistema de antenas na qualidade do espectro excitado, utilizando um método original, implementado neste trabalho, de utilizar o código

CASTOR.

Os resultados indicam que embora a excitação de um determinado modo possa ser privilegiado por uma escolha ótima das fases, modos satélites também podem ser excitados com maior amplitude, de modo que a pureza do espectro não é substancialmente melhorada. Este é o principal resultado obtido neste trabalho.

Abstract

In this work we investigated the excitation of Alfvén eigenmodes in tokamaks using external antennas to the plasma column.

The basic theory of Alfvén waves is revised, including non-ideal effects such as resistivity. Then the theoretical model for excitation Alfvén waves in a cylindrical plasma column, developed by Kurt Appert, is shown in detail, as an introduction to the more complex problem of Alfvén waves in toroidal plasmas.

The cylindrical model is implemented in a numerical code, which is used to study the excitation of Global Alfvén Waves (GAWs), below to the so-called Continuum of Alfvén, in TCABR and JET tokamaks, using a realistic description of their antenna systems.

In the sequel, it is given a brief description of Toroidal Alfvén eigenmodes (TAEs) that are excited in the gaps of the Continuum of Alfvén created by the periodicity condition of the toroidal configuration. The excitement of these modes in JET tokamak is studied using the codes HELENA, for reconstruction of magneto-hydrodynamic equilibrium, and CASTOR, which calculates the perturbed fields in this equilibrium, coupled with instability or modes excited within the magneto-resistive hydrodynamic model.

This study was carried out in order to determine, consistently, the spectrum quality and the eigenmodes associated with TAEs, with different toroidal numbers n , excited by the new JET antenna system.

In particular, it was investigated in detail the effect of the phases of the supply currents of the different modules (eight) of the antenna system in the quality of the excited spectrum, using an original method, implemented in this work, based on the CASTOR code.

The results indicate that, although the excitation of a certain mode may be a privi-

leged by an optimized choice of phases, satellite modes can also be excited with higher amplitude, so that the purity of the spectrum is not substantially improved. This is the main result obtained in this work.

Contents

1	Introduction	1
1.1	Controlled thermonuclear fusion	1
1.2	Tokamaks	4
1.3	Alfvén waves in controlled thermonuclear fusion	5
1.4	Motivation for this thesis	8
1.5	Outline of the thesis	9
2	Alfvén waves review	11
2.1	Alfvén waves in the MHD model	12
2.1.1	Alfvén waves in the ideal MHD model	14
2.1.2	Alfvén waves in the Hall-MHD model	20
2.1.3	Alfvén waves in the resistive MHD model	25
3	Cylindrical model of Alfvén waves	29
3.1	Theory of waves in a cold magnetized cylindrical plasma column	30
3.2	Wave equation	34
3.3	Boundary conditions and power emitted by the antenna	38
3.4	Continuum and global Alfvén waves	39
4	Excitation of Alfvén waves by an external antenna system	42
4.0.1	TCABR tokamak	43
4.0.2	JET tokamak	47
5	Global Alfvén waves results	51

5.1	Computational model	51
5.2	Global Alfvén waves results in the TCABR	54
5.2.1	Numerical procedure to analyze the results for GAWs	57
5.2.1.1	Global Alfvén waves results in the JET	67
6	Toroidal model of Alfvén eigenmodes	74
6.1	TAEs analysis of resistive MHD equations in toroidal geometry using CAS- TOR	75
6.1.1	Linear resistive MHD eigenvalue problem and CASTOR code . . .	76
6.2	The equilibrium in CASTOR code	83
6.2.1	The Grad-Shafranov equation	84
7	Excitation of Toroidal Alfvén Eigenmodes in JET	88
7.1	Introduction	88
7.1.1	Results of the simulation of TAEs in JET	93
7.1.1.1	Analysis of $n = 3$ TAEs	95
7.1.1.2	Analysis of high- n TAEs	100
7.1.2	Results of the simulation of TAEs in JET considering different an- tenna distribution	109
8	Conclusions and outlook	113
8.1	Summary	113
8.2	Conclusions	114
8.3	Outlook	115
	Bibliography	116
A	Vectorial identities	126
B	Magnetic coordinates and the (s, θ, ϕ) coordinate system	127
B.1	The magnetic coordinates	127
B.2	The (s, θ, ϕ) coordinate system	129
C	New JET antenna spectrum	131

D	Figures of TAEs results	134
D.0.1	Resonant mode $n_0 = 3$	134
D.0.2	Resonant mode $n_0 = 9$	135
D.0.3	Resonant mode $n_0 = 10$	138
D.0.4	Resonant mode $n_0 = 11$	140

List of Figures

1.1	Schematic representation of a tokamak like JET. From the JET site [14]. . .	4
1.2	D-T fusion reaction.	6
1.3	Resonant interaction with waves and self-heating (A. Fasoli).	8
2.1	Orthogonal system of vectors [53].	18
2.2	(a) Directions of the perturbed variables for V_A in the direction of $\vec{B}_0$. (b) Directions of the perturbed variables for V_A in the opposite direction of $\vec{B}_0$. . .	19
2.3	Distortion of lines of force by an Alfvén wave, for the case that V_A is in the direction of $\vec{B}_0$ [54].	20
3.1	Plasma-antenna-wall configuration in cylindrical geometry	35
3.2	(a) Helical antenna and (b) Poloidal antenna with radial feeders [67]. . . .	36
4.1	Medium-sized tokamak TCABR, for confinement of high temperature plas- mas.	44
4.2	(a) Scheme of the one poloidal quarter turn of the TCABR antenna. (b) Photography of one antenna module in the test bench.	45
4.3	Poloidal cross-section showing the location of the two poloidal quarter turns. . .	45
4.4	Schematic drawing of on antenna poloidal sector; top view.	46
4.5	(a) Module formed by 4 antennas,each consisting of 18 coils [86]. (b) Real image of one assembly of 4 antennas system as installed on the wall of the JET vessel [39].	48
4.6	Rectangular conductor with current flow.	48
4.7	Position of the antenna modules in the cylindrical model.	49

5.1	Scheme of one strap antenna current Fourier decomposition.	52
5.2	Scheme of system for excitation and detection of Alfvén waves in TCABR [94].	55
5.3	Safety factor profiles. The coefficient multiplying x^2 and x^4 ensures the concavity the safety factor profile.	56
5.4	$\Delta f \times n$ for fixed $m = 1$, for multiple values of the effective mass, referring to discharge # 28038 with $I_p = 83$ kA.	59
5.5	$\Delta f \times n$ for fixed $m = 2$, for multiple values of the effective mass, referring to discharge # 28038 with $I_p = 83$ kA.	59
5.6	$\Delta f \times n$ for fixed $m = 3$, for multiple values of the effective mass, referring to discharge # 28038 with $I_p = 83$ kA.	60
5.7	$\Delta f \times$ effective mass for fixed modes numbers, and for discharge # 28038 with $I_p = 83$ kA.	61
5.8	Possible GAWs represented by impedance peaks for three pairs of mode numbers, for discharge # 28038 with $I_p = 83$ kA. The ranges of variation of the effective mass correspond to the ones of figure 5.7	62
5.9	Radial profiles of magnetic field component $ B_r $ for GAWs, discharge # 28038 with $I_p = 83$ kA, for three pairs of mode numbers.	62
5.10	Profile of magnetic field component $ B_z $ for GAWs through the total radius, discharge # 28038 with $I_p = 83$ kA.	63
5.11	Radial profiles of magnetic field component $ B_r $ for GAWs for, discharge # 28038 with $I_p = 86$ kA, and three pairs of mode numbers.	64
5.12	Profile of magnetic field component $ B_z $ for GAWs through the total radius, discharge # 28038 with $I_p = 86$ kA.	64
5.13	Radial field profiles of global modes for $m = 1$ and $n = 2$, for discharge # 28289, with $I_p = 88$ kA and $Mi \approx 1.36$	65
5.14	Radial field profiles of global modes for $m = 2$ and $n = 1$, for discharge # 28289, with $I_p = 88$ kA and $Mi \approx 1.21$	66
5.15	Possible global modes, for $m = 1$ and $n = 1$, represented by impedance peaks, for certain frequency and effective mass values, for JET.	68

5.16	Possible global modes, for $m = 1$ and $n = 2$, represented by impedance peaks, for certain frequency and effective mass values, for JET.	68
5.17	Possible global modes, for $m = 1$ and $n = 3$, represented by impedance peaks, for certain frequency and effective mass values, for JET.	69
5.18	Possible global modes, for $m = 2$ and $n = 1$, represented by impedance peaks, for certain frequency and effective mass values, for JET.	69
5.19	$ B_r $ field structure of possible global mode in JET for $m = 2$ and $n = 1$. . .	70
5.20	$ B_z $ field structure of possible global mode in JET for $m = 2$ and $n = 1$. . .	70
5.21	$ B_r $ field structure of possible global mode in JET for $m = 1$ and $n = 2$. . .	71
5.22	$ B_z $ field structure of possible global mode in JET for $m = 1$ and $n = 2$. . .	71
5.23	$ B_r $ field structure of possible global mode in JET for $m = 1$ and $n = 3$. . .	72
5.24	$ B_z $ field structure of possible global mode in JET for $m = 1$ and $n = 3$. . .	72
6.1	Schematic representation of the tokamak geometry.	84
7.1	Position of the antennas on the toroidal model. Here R_0 is the major radius.	90
7.2	Example of resonance frequencies indicated by peaks in the absorbed power. The power absorbed, in arbitrary units, by the plasma as a function of the normalized antenna frequency.	91
7.3	The scheme of the positioning of the JET antennas.	92
7.4	Equilibrium solution provided by HELENA for JET discharge #77788 at $t = 10$ s, R, ϕ, Z denote cylindrical coordinates. Flux line contours shown in straight-field-line coordinates (a) and flux coordinates (ψ, χ) (b).	94
7.5	The safety factor profile reconstructed by HELENA for JET discharge #77788 at $t = 10$ s. Plasma current $I_p = 2$ MA; toroidal magnetic field $B_T = 2.7$ T.	94
7.6	Density profile used in CASTOR to simulate JET discharge #77788 at $t = 10$ s. Here $n_{e0} \approx 2.3 \times 10^{19} \text{ m}^{-3}$	95
7.7	The frequency spectrum of the $n = 3$ modes as function of the the variable s that labels the flux surfaces. The the red lines represent the TAE region and the green line represent the normalized frequency of resonance.	96

7.8	The power absorbed by the plasma as a function of the antenna frequency.	97
7.9	Values of the radial velocity field excited by all eight antennas for unoptimized phases. For $n = 3$ (blue asterisk), and for all modes (red solid). . . .	97
7.10	Real (blue asterisk), imaginary (green dotted) and absolute (red solid) values of the radial velocity field for $n = 3$ mode, which is excited by all eight antennas. (a) unoptimized phases, (b) phases optimized using the factor $e^{-i\frac{n_0}{R}z_i}$ for $n_0 = 3$	98
7.11	Real (blue asterisk), imaginary (green dotted) and absolute (red solid) values of the total radial velocity field for the $n = 4$ component of the spectrum, which is excited by all eight antennas.(a) unoptimized phases, (b) phases optimized for $n_0 = 3$	99
7.12	Real (blue asterisk), imaginary (green dotted) and absolute (red solid) values of the radial velocity field for the $n = 5$ component, excited by all eight antennas. (a) unoptimized phases, (b) phases optimized for $n_0 = 3$. .	100
7.13	Values of the radial velocity field excited by all eight antennas for unoptimized phases. For $n = 9$ (blue asterisk), and for all modes (red solid). . . .	101
7.14	Values of the radial velocity field excited by all eight antennas for unoptimized phases. For $n = 10$ (blue asterisk), and for all modes (red solid). . .	102
7.15	Values of the radial velocity field excited by all eight antennas for unoptimized phases. For $n = 11$ (blue asterisk), and for all modes (red solid). . .	102
7.16	Real (blue asterisk), imaginary (green dotted) and absolute (red solid) values of the radial velocity field for resonant mode $n = 9$, which is excited by all eight antennas. (a) unoptimized phases, (b) phases optimized for $n_0 = 9$	103
7.17	Real (blue asterisk), imaginary (green dotted) and absolute (red solid) values of the radial velocity field for resonant mode $n = 10$, which is excited by all eight antennas.(a) unoptimized phases, (b) phases optimized for $n_0 = 10$	104

7.18	Real (blue asterisk), imaginary (green dotted) and absolute (red solid) values of the radial velocity field for resonant mode $n = 11$, which is excited by all eight antennas. (a) unoptimized phases, (b) phases optimized for $n_0 = 11$	104
7.19	Values of the radial velocity field excited by all eight antennas for optimized phases. For $n = 9$ (blue asterisk), and for all modes (red solid).	106
7.20	Values of the radial velocity field excited by all eight antennas for optimized phases. For $n = 10$ (blue asterisk), and for all modes (red solid).	106
7.21	Values of the radial velocity field excited by all eight antennas for optimized phases. For $n = 11$ (blue asterisk), and for all modes (red solid).	107
7.22	Module of the perturbed radial velocity in a toroidal section for resonant mode $n = 9$, which is excited by all eight antennas.(a) unoptimized phases, (b) phases optimized for $n_0 = 9$	108
7.23	Module of the perturbed radial velocity in a toroidal section for resonant mode $n = 10$, which is excited by all eight antennas.(a) unoptimized phases, (b) phases optimized for $n_0 = 10$	108
7.24	Module of the perturbed radial velocity in a toroidal section for mode resonant $n = 11$, which is excited by all eight antennas.(a) unoptimized phases, (b) phases optimized for $n_0 = 11$	109
7.25	Proposal for the position of the antennas on the toroidal model.	110
7.26	Spectrum created by eight modules of the new JET antenna (a) with unoptimized phases exciting odd toroidal modes with phases 0° to 4 coils of each module and 180° for the other 4 coils of each module. (b) optimizing $n_0 = 9$	111
7.27	Values of the radial velocity field excited by all 32 antennas. For $n = 9$ (blue asterisk), and for all modes (red solid). (a) with unoptimized phases exciting odd toroidal modes with phases 0° to 4 coils of each module and 180° for the other 4 coils of each module. (b) optimizing $n_0 = 9$	112
C.1	Spectrum created by eight modules of the new JET antenna (a) with phases $[0^\circ, 0^\circ, 0^\circ, 0^\circ, 0^\circ, 0^\circ, 0^\circ, 0^\circ]$ (b) with phases $[180^\circ, 180^\circ, 180^\circ, 180^\circ, 180^\circ, 180^\circ, 180^\circ, 180^\circ]$	131

- C.2 Spectrum created by eight modules of the new JET antenna (a) with phases $[0^\circ, 0^\circ, 0^\circ, 0^\circ, 180^\circ, 180^\circ, 180^\circ, 180^\circ]$ (b) with phases $[180^\circ, 0^\circ, 180^\circ, 0^\circ, 180^\circ, 0^\circ, 180^\circ, 0^\circ]$.132
- C.3 Spectrum created by eight modules of the new JET antenna (a) with phases $[180^\circ, 180^\circ, 0^\circ, 0^\circ, 0^\circ, 0^\circ, 180^\circ, 180^\circ]$ (b) with phases $[0^\circ, 180^\circ, 180^\circ, 0^\circ, 0^\circ, 180^\circ, 180^\circ, 0^\circ]$.132
- C.4 Spectrum with $e^{-i\frac{n_0}{R}z_i}$ phasing (a) optimizing $n_0 = 3$ (b) optimizing $n_0 = 8$. 133
- C.5 Spectrum with $e^{-i\frac{n_0}{R}z_i}$ phasing (a) optimizing $n_0 = 10$ (b) optimizing $n_0 = 15$.133
- D.1 Radial profile created by eight modules of the new JET antenna for mode $n = 1$. (a) unoptimized phases, (b) phases optimized for $n_0 = 3$. We see that the intensity decreases slightly by a factor 0.98. 134
- D.2 Radial profile created by eight modules of the new JET antenna for mode $n = 7$. (a) unoptimized phases, (b) phases optimized for $n_0 = 3$. We see that the intensity increases by a factor 1.27. 135
- D.3 Radial profile created by eight modules of the new JET antenna for mode $n = 5$. (a) unoptimized phases, (b) phases optimized for $n_0 = 9$. We see that the intensity increases slightly by a factor 1.06. 135
- D.4 Radial profile created by eight modules of the new JET antenna for mode $n = 7$. (a) unoptimized phases, (b) phases optimized for $n_0 = 9$. We see that the intensity increases by a factor 1.38. 136
- D.5 Radial profile created by eight modules of the new JET antenna for mode $n = 11$. (a) unoptimized phases, (b) phases optimized for $n_0 = 9$. We see that the intensity increases by a factor 2.65. 136
- D.6 Radial profile created by eight modules of the new JET antenna for mode $n = 13$. (a) unoptimized phases, (b) phases optimized for $n_0 = 9$. We see that the intensity increases by a factor 4.71. 137
- D.7 Radial profile created by eight modules of the new JET antenna for mode $n = 6$. (a) unoptimized phases, (b) phases optimized for $n_0 = 10$. We see that the intensity increases by a factor 1.15. 138
- D.8 Radial profile created by eight modules of the new JET antenna for mode $n = 8$. (a) unoptimized phases, (b) phases optimized for $n_0 = 10$. We see that the intensity increases by a factor 1.55. 138

D.9	Radial profile created by eight modules of the new JET antenna for mode $n = 12$. (a) unoptimized phases, (b) phases optimized for $n_0 = 10$. We see that the intensity increases by a factor 3.5.	139
D.10	Radial profile created by eight modules of the new JET antenna for mode $n = 14$. (a) unoptimized phases, (b) phases optimized for $n_0 = 10$. We see that the intensity increases by a factor 8.38.	139
D.11	Radial profile created by eight modules of the new JET antenna for mode $n = 7$. (a) unoptimized phases, (b) phases optimized for $n_0 = 11$. We see that the intensity increases by a factor 1.27.	140
D.12	Radial profile created by eight modules of the new JET antenna for mode $n = 9$. (a) unoptimized phases, (b) phases optimized for $n_0 = 11$. We see that the intensity increases by a factor 1.79.	141
D.13	Radial profile created by eight modules of the new JET antenna for mode $n = 13$. (a) unoptimized phases, (b) phases optimized for $n_0 = 11$. We see that the intensity increases by a factor 5.1.	141
D.14	Radial profile created by eight modules of the new JET antenna for mode $n = 15$. (a) unoptimized phases, (b) phases optimized for $n_0 = 11$. We see that the intensity increases by a factor 30.9.	142

Chapter 1

Introduction

1.1 Controlled thermonuclear fusion

Controlled thermonuclear fusion is a promising solution to the current energy crisis, since it has important advantages as no carbon emissions, no air pollution (no chemical combustion products released), almost unlimited fuel, and it is intrinsically safe since it does not have the possibility of nuclear runaway. We can say that the thermonuclear fusion will be an energy source environmentally and economically viable in the future, together with other types of energy sources alternative to fossil fuels and hydroelectric, i.e. wind power, solar energy and nuclear fission. Unlike nuclear fission that involves the splitting of heavy elements, like uranium or plutonium, by neutrons, creating lighter elements with the release of energy, the thermonuclear fusion involves the fusion of lighter elements, i.e. isotopes of hydrogen, such as deuterium and tritium (D-T fusion reaction), to form a heavier element, again with the release of energy, ≈ 17.6 MeV reaction (2.8×10^{-12} joule, compared to 200 MeV for U-235 fission).

Deuterium occurs naturally in seawater, ≈ 30 grams per cubic meter, while tritium occurs naturally only in trace quantities, produced by cosmic rays, and it is radioactive, with a half-life of around 12 years. Usable quantities of tritium can be bred in the fusion reactor itself, from the irradiation of lithium with neutrons from the D-T reaction. Therefore lithium is then transformed into tritium, which is used to fuel the reactor, and helium. The lithium, which is less abundant than deuterium, is found in large quantities,

≈ 30 parts per million by weight, in the Earth's crust and in weaker concentrations in the sea.

In a fusion reactor, the neutrons generated in the D-T fusion reaction will be absorbed in a blanket containing lithium, which surrounds the core. The most promising fusion reactions are those in which the nuclei of deuterium and tritium fuse to produce an alpha particle with the release of a neutron. Nuclear reactions of interest, i.e. primary and secondary reactions, for fusion reactors are the following [1]:

$$D_1^2 + D_1^2 \rightarrow T_1^3(1.01MeV) + H_1^1(3.03MeV), \quad (1.1)$$

$$D_1^2 + D_1^2 \rightarrow He_2^3(0.82MeV) + n_0^1(2.45MeV), \quad (1.2)$$

$$D_1^2 + T_1^3 \rightarrow He_2^4(3.52MeV) + n_0^1(14.06MeV), \quad (1.3)$$

$$D_1^2 + He_2^3 \rightarrow He_2^4(3.67MeV) + H_1^1(14.67MeV), \quad (1.4)$$

$$Li_3^6 + n_0^1 \rightarrow T_1^3 + He_2^4 + (4.8MeV), \quad (1.5)$$

$$Li_3^7 + n_0^1 \rightarrow He_2^4 + n_0^1 - 2.5MeV \quad (1.6)$$

The development of plasma physics applied for magnetic fusion research has been strongly influenced by the requirements to achieve ignition. They are mainly two: first, the creation of a stable magnetic configuration to confine the fuel plasma, and, second, doing so at a critical size large enough for the energy delivered by the fusion reactions to heat the fuel faster than they leak away [2]. Therefore, the main goal of magnetic confinement fusion is developing a method to contain a hot plasma in a magnetic bottle for a sufficient time and at sufficiently high density and temperature to achieve a net energy output.

At present, two main experimental approaches are being studied: magnetic confinement and inertial confinement. The first method uses strong magnetic fields to contain the hot plasma. The second involves compressing a small pellet containing fusion fuel to extremely high densities, using strong lasers or particle beams. We will focus on magnetic confinement, where the magnetic fields are ideal for confining a plasma because the electrical charges (ions and electrons) follow the magnetic field lines. However, motion along the lines is not restricted, so the particles can come in contact with the reactor

walls, dissipating their heat and slowing down. To prevent this, studies concluded that the most effective magnetic configuration is toroidal, shaped like a doughnut, in which the magnetic field is curved around to form a closed loop [3]. For proper confinement, this toroidal field must have superimposed upon it a poloidal field component. The result is a magnetic field with force lines following spiral (helical) paths that confine and control the plasma.

A special role in magnetic fusion is played by the ideal magnetohydrodynamics theory or ideal MHD theory. For the development of a viable fusion reactor there are basic physics requirements that must be satisfied. A sufficient density of plasma must be confined for a sufficiently long time at a sufficiently high temperature to produce net thermonuclear power [4, 5]. The net power balance condition for a magnetic fusion system is given by the "*Lawson criterion*" [6]

$$n\tau_E \gtrsim f(T), \quad (1.7)$$

where $n\tau_E$ is the Lawson parameter, with n the plasma number density and τ_E the energy confinement time. Typically $f(T) \approx 10^{14} \text{ cm}^{-3} \text{ sec}$ for the optimized temperature $T \approx 20 \text{ keV}$.

The maximum energy confinement time is determined by the microscopic behavior of the plasma, i.e. the individual particle dynamics on short length and time scales, treated by kinetic models including the proper geometry [7,8]. The maximum density is commonly determined by macroscopic equilibrium and stability limits set by the magnetic geometry. Because of the relatively slow time and large length scales involved, these phenomena are described by fluid models. The ideal MHD is the most basic single-fluid model for determining the macroscopic equilibrium and stability properties of a plasma [9, 10].

There is general consensus that any magnetic geometry meriting consideration as a fusion reactor must satisfy the equilibrium and stability limits set by ideal MHD, since, if not satisfied, violent termination of the plasma on very short time scale, approximately less than $100 \mu\text{sec}$, is often the consequence. Therefore, we can say that the role of ideal MHD in magnetic fusion is the discovery and analysis of different magnetic geometries with the aim of distinguishing those that are particularly attractive for use in fusion reactors. As already mentioned, the most effective magnetic geometry is the toroidal

one. There are several types of toroidal confinement systems, the most important being tokamak, stellarators, and reversed field pinch (RFP) devices. In this work, we will focus on tokamak systems, where the best results to achieve nuclear fusion were obtained.

1.2 Tokamaks

The tokamak (*toroidalnya kamera ee magnetnaya katushka* â torus-shaped magnetic chamber), was invented in the 1950s by Soviet physicists Igor Tamm and Andrei Sakharov in the Soviet Union, inspired by an original idea of Oleg Lavrentiev [11–13]. Since early linear pinch experiments at Los Alamos and elsewhere proved to be unstable and heat leaked out of the ends, the tokamak arose as a solution remedying the defects by bending the cylinder into a closed ring or torus, stabilized by a strong field generated by a solenoid wrapped around the toroidally shaped vacuum vessel. Bending the current channel into a circle requires an additional vertical field perpendicular to the plane of the torus, for maintaining the equilibrium of the plasma column. Therefore, the requirements of stable confinement are reached in the tokamak using three sources of magnetic field: external sources for the vertical field to confine the current, the current to confine the plasma, and the solenoid to stabilize the current channel, see figure 1.1.

Figure 1.1: Schematic representation of a tokamak like JET. From the JET site [14].

Tokamaks operate within limited parameters, outside which sudden losses of energy confinement, so-called disruptions, can occur, causing major thermal and mechanical stresses to the structure and walls. Nevertheless, it is considered the most promising design, and research is continuing on various tokamaks around the world. However, the stability of the tokamak follows from its magnetic geometry, in which the field lines produced by the toroidal solenoid are given a helical twist by the current and trace out symmetric closed toroidal surfaces called flux surfaces.

The plasma created in the tokamak is highly unstable, and even today is not entirely understood. Inside the tokamak, i.e. in the plasma column, the emergence of plasma instabilities inherent is the cause whereby the plasma is not confined for a long time. This fact shows that the plasma is a complex and chaotic system and the plasma confinement is not a trivial problem. For instance, it is quite desirable to operate a tokamak in a high beta regime, where beta is the ratio of the plasma thermal pressure to the magnetic stress pressure, since then the fusion energy output can be maximized. However, the magnetohydrodynamics (MHD) instabilities tend to limit the plasma beta to a low value [15, 16].

Nowadays, there are a number of major projects under development that may bring research to the point where fusion power can be commercialized and several tokamaks have been built. In this work, specifically we focus our attention on the analysis, of two tokamaks. The first one is TCABR, located at the Institute of Physics of the University of São Paulo, in Brazil, and the second is the Joint European Torus (JET), located in Oxfordshire, in the United Kingdom, which is currently the largest tokamak operating in the world. Both tokamaks will be described in detail in chapter three of the present thesis.

1.3 Alfvén waves in controlled thermonuclear fusion

As will be seen in Chapter two, the Alfvén waves are transverse low frequency electromagnetic waves that propagate along the magnetic field $\vec{B}$. These waves are common in both natural and laboratory plasmas. The problem of the stability of Alfvén waves in an ignited tokamak plasma is related to the confinement in the bulk plasma as well as to

the fusion born alpha particles, and they are of fundamental importance to the operation of ignited tokamak plasmas.

As it was described in the previous section, to reach the ignition conditions the tokamak plasma is heated by the ohmic dissipation of the induced current and by additional heating schemes, such as injection of high energy neutral beams, or by launching electromagnetic waves into the plasma [1]. Once ignited, the plasma can become entirely self-heating by the energy deposited by the fusion-born alpha particles, through collisions with the electrons, compensating the heat losses, as indicated in figure 1.2 for the D-T reaction (eq. 6.37).

Figure 1.2: D-T fusion reaction.

The alpha particles, i.e. He_2^4 , born with energy of 3.52 MeV and with a density profile that is sharply peaked at the center of the plasma due to the sensitive dependence of the fusion reaction rate on the plasma temperature, have a corresponding velocity

$V_{\alpha} = 1.3 \times 10^7$ m/s, which is usually greater than the typical Alfvén speed in the plasma. The Alfvén wave describes a basic oscillation between the perpendicular plasma kinetic energy and the perpendicular “line bending” magnetic energy and is analogous to the familiar case of waves traveling along a taut string. These waves propagate along the magnetic field lines at the Alfvén speed. As the alpha particles are slowed down by thermalization on the background particles, the untrapped ones interact resonantly with the Alfvén waves and amplify them via inverse Landau damping. This leads to destabilization of the Alfvén waves and to a loss of energy of the alpha particles, decreasing the amount of energy that they can transfer to the electrons and other ions.

In earlier studies [17], it was found that the global Alfvén waves (GAWs) in cylindrical geometry can be destabilized when interacting with the alpha particles. However, it has been found that the GAW modes can be readily stabilized when toroidicity effects are taken into account [18–20]. However, the alpha particles can destabilize another type of low mode number GAWs called the toroidicity induced Alfvén eigenmode or toroidal Alfvén eigenmode (TAE) [21].

Unstable TAE modes may produce a high level of magnetic field fluctuation, enough to make the characteristic time for alpha particle loss much smaller than the alpha particle slowing down time. In this circumstance, TAE modes effectively increase transport of the alpha particles created by fusion reactions and eject them from the plasma before the complete thermalization on background species occurs. This situation is deleterious to fusion reactor operation since incomplete thermalization lowers the fusion gain, especially in the center of plasma where the energetic particles are concentrated, the temperature is high, and could possibly lead to quenching of the fusion burn altogether [22], as indicated in figure 1.3.

In this thesis, we will investigate an scheme where the natural excitation of GAWs and TAEs by interaction with alpha particles in the fusion process is replaced by the external excitation of Alfvén waves through a proper antenna system. The antenna can excite resonant modes in the Alfvén continuum, which are strongly damped, gap modes that are located near the extremum of the continuum (GAWs), and finally excite gap modes near the extremum or inside of the continuum created by mode coupling (TAEs) [23].

Figure 1.3: Resonant interaction with waves and self-heating (A. Fasoli).

1.4 Motivation for this thesis

Because of their relevance, the characteristics of GAWs and TAEs are intensively investigated experimentally using the scheme of external excitation. In particular, GAWs are investigated in TCABR and PRETEXT [24–34] and TAEs in JET [35–39]. However, in the scheme of external excitation of these waves, the external antenna system normally excites a broad spectrum of modes, making it difficult to analyze the results.

The main objective of this thesis is to study numerical modeling techniques that can properly describe the spectrum of excited modes of TAEs in JET, taking into account the actual geometry of the antenna system and the new RF amplifier designed by the Plasma Physics Laboratory of the University of São Paulo. For this purpose, we used the normal-mode MHD code CASTOR [41], which was slightly modified, together with the HELENA code [42,43], for the study of TAEs in JET.

The GAWs are previously studied, as a workout for understanding the phenomenon of TAEs. We analyze experimental results of TCABR and JET. For this purpose, an old numerical program, for the study of GAWs in TCABR [25, 40] and JET, has been extended.

Finally, there exists a large number of numerical codes for the study of phenomena linked to the plasma confinement inside a tokamak, e.g instabilities waves. Therefore, it is very important for our group to possess a stable and tested numerical code, with acceptable results, as are the CASTOR and HELENA codes. Understanding how they work is crucial for the developed modifications, which allow to create new codes that can meet our needs.

1.5 Outline of the thesis

The contents of this thesis are organized as follows:

Chapter 2: In this chapter, we will introduce the basic topics of Alfvén waves in the MHD model. For this purpose we studied the MHD model, i.e. ideal, hall, and resistive MHD models, for an homogeneous plasma in cartesian geometry.

Chapter 3: We outline the cold-plasma equations that are derived in detail using cylindrical geometry, with the aim of studying GAWs. It includes the discussion of the vacuum and the boundary conditions, i.e. model plasma-vacuum, vacuum-antenna-vacuum, and vacuum-wall. Subsequently, we describe briefly the continuum and global Alfvén waves.

Chapter 4: We discuss the excitement of GAWs and TAEs by an external antenna system. We present a brief description the TCABR and JET tokamaks (story, geometry antenna and main parameters).

Chapter 5: We describe the computational model, as well as present and analyze the numerical results obtained for the global Alfvén waves (GAWs) for both tokamaks. Therefore, the main target this chapter is to compare numerical and experimental results, obtained in various discharges of TCABR, providing information that is hard to get from the experiments and, on the other hand, to confirm the accuracy of the results obtained numerically. Similarly it is analyzed the JET tokamak using imposition parameters, i.e. data not available experimentally.

Chapter 6: In this chapter, we discuss the toroidal model of Alfvén eigenmode in tokamaks. For this we introduce the basic properties of the numerical codes CASTOR

and HELENA, which study the resistive MHD model in toroidal geometry.

Chapter 7: We present the result obtained by the new JET module antenna on the MHD spectrum, using the plasma equilibrium code HELENA and the extended CASTOR code version, considering the new external JET antenna. Finally, a summary of the work in this thesis is presented together with the main conclusions and an outlook for future works.

Chapter 2

Alfvén waves review

The Alfvén waves, discovered by Hannes Alfvén in 1942 [44], are a fundamental physical phenomenon in all kinds of magnetized plasmas. Alfvén waves are electromagnetic waves with low-frequency, less than the ion cyclotron frequency, $\omega < \omega_{ci}$ where $\omega_{ci} = qB/m_i$, $\omega = 2\pi f$ and $f < 10$ MHz, and are called of torsional or shear Alfvén waves. In the case that the frequency is comparable to the ion cyclotron frequency, these waves are called ion cyclotron waves, as will be seen later. Also we can find the compressional Alfvén waves, with frequencies well above the ion cyclotron frequency (helicon or whistler waves), and the electron cyclotron waves, with frequencies near the electron cyclotron frequency. On the other hand, the Alfvén waves are considered the most important magnetohydrodynamics waves (MHD waves), because they are a direct result of flux conservation and frozen magnetic field lines in the fluid (in the absence of collisional processes, e.g. the resistivity), and also for the important role in the heating and transport of energy in the plasma.

The study of the Alfvén waves is not only treated within the MHD model. From the point of view of kinetic theory, the Alfvén waves or the kinetic Alfvén waves (KAW) [46–48], as they are usually called, are very important, since some effects, such as Landau and cyclotron damping, caused by wave-particle resonance, cannot be modelled by the MHD model [45].

In regard to nuclear fusion, the Alfvén waves have been considered and applied for many uses in tokamaks. The study of plasma heating and current drive using Alfvén

waves is perhaps the most important application, due to the Alfvén waves carrying the information about the overall magnetic geometry and because it is generally conceded that some form of auxiliary heating will be needed to bring a tokamak fusion reactor to the ignition temperature.

In this chapter, we will discuss in detail the basic model used to describe the plasma and subsequently analyze the Alfvén wave properties. We focus on the MHD model for an homogeneous plasma. The fundamentals of the kinetic theory model for an homogeneous plasma will not be presented in this work. We will present the case of inhomogeneous plasma together with a description of the effects of geometry (cylindrical and toroidal) on the properties of the plasma and of the Alfvén waves, within the MHD model, in the following two chapters.

2.1 Alfvén waves in the MHD model

The magnetohydrodynamics model, or MHD model, is the mathematical single-fluid model which describes the interaction between the plasma and the magnetic fields, through the fluid equations, including the Lorentz force effects and the Maxwell equations. As described in the previous chapter, the importance of the MHD model in the study of nuclear fusion is its capacity for determining the macroscopic equilibrium and stability properties of a plasma, as also the discovery and analysis of different magnetic geometries attractive for use in fusion reactors.

The model essentially describes how magnetic, inertial, and pressure forces interact within an ideal, i.e. a perfectly conducting, plasma in an arbitrary magnetic geometry. The set of MHD equations are derived from the Klimontovich equation by neglecting all collision effects (the Vlasov equation), see [49] for more details. Then, a set of two-fluid macroscopic equations is obtained for an electron fluid and an ion fluid, this set is called the two-fluid model. We combine both equations to obtain a single- fluid model (MHD model) [50]. The set of equations describing the MHD model are:

The mass conservation law:

$$\frac{\partial \rho_m}{\partial t} + \nabla \cdot (\rho_m \vec{v}) = 0. \quad (2.1)$$

The charge conservation law:

$$\frac{\partial \rho_e}{\partial t} + \nabla \cdot \vec{J} = 0. \quad (2.2)$$

The equation of motion:

$$\rho_m \frac{d\vec{v}}{dt} = -\nabla p + \rho_e \vec{E} + \vec{J} \times \vec{B} - \rho_m \nabla \phi_g. \quad (2.3)$$

The generalized Ohm's law:

$$\vec{E} + \vec{v} \times \vec{B} = \eta \vec{J} + \left(\frac{m_e}{n_i e^2} \right) \frac{\partial \vec{J}}{\partial t} + \left(\frac{1}{n_i e} \right) \vec{J} \times \vec{B} - \left(\frac{1}{n_i e} \right) \nabla p_e. \quad (2.4)$$

The adiabatic equation of state (energy conservation):

$$\frac{\partial p}{\partial t} + \vec{v} \cdot \nabla p + \gamma p \nabla \cdot \vec{v} = (\gamma - 1) \eta \vec{J}^2. \quad (2.5)$$

$$\frac{d(p \rho_m^{-\gamma})}{dt} = (\gamma - 1) \rho_m \eta \vec{J}^2. \quad (2.6)$$

Furthermore, we can add Maxwell's equations to the system:

$$\nabla \times \vec{E} = -\frac{\partial \vec{B}}{\partial t}, \quad (2.7)$$

$$\nabla \times \vec{B} = \mu_0 \vec{J} + \frac{1}{c^2} \frac{\partial \vec{E}}{\partial t}, \quad (2.8)$$

$$\nabla \cdot \vec{E} = \frac{\rho_e}{\varepsilon_0}, \quad (2.9)$$

$$\nabla \cdot \vec{B} = 0. \quad (2.10)$$

These equations constitute a closed set of evolution equations for the variables $\rho_m(\vec{r}, t)$, $\rho_e(\vec{r}, t)$, $\vec{v}(\vec{r}, t)$, $\vec{J}(\vec{r}, t)$, $p(\vec{r}, t)$, $\vec{E}(\vec{r}, t)$ and $\vec{B}(\vec{r}, t)$ (total mass density, charge density, center of mass velocity, current density, pressure, electric field and magnetic field, respectively). Other physical quantities found in the above system of equations are ϕ_g , m_e , n_i , e , p_e , γ , η , c , ε_0 and μ_0 (gravitational potential, electron mass, ion number density, fundamental unit of electric charge, electron gas pressure, adiabatic index, electrical resistivity, speed of light in vacuum, permittivity in vacuum and permeability in vacuum respectively). We note that the Maxwell equations 2.9 and 2.10 may then be considered as initial conditions on $\vec{E}$ and $\vec{B}$ since they remain satisfied if they are initially satisfied. We have 14 equations

in the 14 unknowns; this assumes that the pressure can be expressed in terms of the mass density. SI units are used throughout.

In this section we present an analysis of the theory of wave propagation, predominantly electromagnetic, in a plasma in the Cartesian coordinate system. We discuss the waves first within the ideal MHD model, suitable for a uniform plasma where the waves will be assumed to be low-frequency waves, i.e. frequencies below of the ion cyclotron frequency, and will continue to the Hall-MHD model, where the frequency range is extended to encompass to ion cyclotron frequency. Finally, we will discuss, in basic form, the resistive MHD model, which is of practical interest.

2.1.1 Alfvén waves in the ideal MHD model

We now consider asymptotic approximations to MHD model that lead to the ideal MHD equations [51, 52]. In this model we assume the plasma as a single fluid and consider only low-wavelength and low-frequency waves. We neglected the resistivity (infinite conductivity), displacement current, ∇p_e for low-temperatures, gravity effects, the $\vec{J} \times \vec{B}$ term (Hall term), compared to the $\vec{v} \times \vec{B}$ term, and electron inertia. On the other hand, no net charge (macroscopic electrical neutrality) is considered. The resulting equations read:

$$\frac{\partial \rho_m}{\partial t} + \nabla \cdot (\rho_m \vec{v}) = 0, \quad (2.11)$$

$$\nabla \cdot \vec{J} = 0, \quad (2.12)$$

$$\rho_m \frac{d\vec{v}}{dt} = -\nabla p + \vec{J} \times \vec{B}, \quad (2.13)$$

$$\vec{E} + \vec{v} \times \vec{B} = 0, \quad (2.14)$$

$$\frac{\partial p}{\partial t} + \vec{v} \cdot \nabla p + \gamma p \nabla \cdot \vec{v} = 0, \quad (2.15)$$

$$\frac{d(p\rho_m^{-\gamma})}{dt} = 0. \quad (2.16)$$

The low-frequency Maxwell's equations:

$$\nabla \times \vec{E} = -\frac{\partial \vec{B}}{\partial t}, \quad (2.17)$$

$$\nabla \times \vec{B} = \mu_0 \vec{J}, \quad (2.18)$$

$$\nabla \cdot \vec{E} = 0, \quad (2.19)$$

$$\nabla \cdot \vec{B} = 0. \quad (2.20)$$

Using the equations 2.14, 2.17, 2.18 and the vector identities (A.8) and (A.13), we have

$$\rho_m \frac{d\vec{v}}{dt} = -\nabla p + \frac{1}{\mu_0} [(\nabla \vec{B}) \cdot \vec{B} - \vec{B} \cdot \nabla \vec{B}], \quad (2.21)$$

$$-\frac{\partial \vec{B}}{\partial t} = \vec{v} \cdot \nabla \vec{B} + \vec{B} \nabla \cdot \vec{v} - \vec{B} \cdot \nabla \vec{v}. \quad (2.22)$$

Let us assume an infinite homogeneous plasma in rest and equilibrium, i.e. $\vec{v}_0 = 0$. The force-balance equation in the equilibrium satisfy:

$$\begin{aligned} 0 &= -\nabla p_0 + \vec{J}_0 \times \vec{B}_0, \\ \nabla p_0 &= \vec{J}_0 \times \vec{B}_0. \end{aligned} \quad (2.23)$$

We now linearize the MHD equations; the subscripts "0" denote the equilibrium state χ_0 , and the subscripts "1" denote the first order perturbations associated with the wave motion $\chi_1(\vec{r}, t)$, which may be written as:

$$\chi(\vec{r}, t) = \chi_0 + \chi_1(\vec{r}, t), \quad (2.24)$$

where, if wavelengths are much shorter than the scale-length over which the equilibrium quantities change (uniform plasma), then $|\chi_1| \ll \chi_0 = cte$. Therefore, we have the following set of linearized MHD equations:

$$\frac{\partial \rho_{m1}}{\partial t} + \rho_{m0} \nabla \cdot \vec{v}_1 = 0, \quad (2.25)$$

$$\rho_{m0} \frac{\partial \vec{v}_1}{\partial t} = -\nabla p_1 - \frac{1}{\mu_0} [(\nabla \vec{B}_1) \cdot \vec{B}_0 - (\vec{B}_0 \cdot \nabla) \vec{B}_1], \quad (2.26)$$

$$\frac{\partial p_1}{\partial t} + \gamma p_0 \nabla \cdot \vec{v}_1 = 0, \quad (2.27)$$

$$-\frac{\partial \vec{B}_1}{\partial t} = \vec{B}_0 \nabla \cdot \vec{v}_1 - \vec{B}_0 \cdot \nabla \vec{v}_1, \quad (2.28)$$

$$\nabla \cdot \vec{B}_1 = 0. \quad (2.29)$$

Moreover, let us consider harmonic plane wave solutions in the form $\chi(\vec{r}, t) = \hat{\chi} e^{i(\vec{k} \cdot \vec{r} - \omega t)}$. We can replace the operator ∇ by $i\vec{k}$ and the partial time derivative by $-i\omega$, so that we obtain an algebraic system of eigenvalue equations, using (A.10) in equation 2.26,

$$-i\omega \hat{\rho}_{m1} + \rho_{m0} i\vec{k} \cdot \hat{v}_1 = 0, \quad (2.30)$$

$$-i\omega \rho_{m0} \hat{v}_1 = -i\vec{k} \hat{p}_1 - \frac{1}{\mu_0} [(i\vec{k} \vec{B}_0 \cdot -i\vec{k}_0 \cdot \vec{B}_0) \hat{B}_1], \quad (2.31)$$

$$-i\omega \hat{p}_1 + \gamma p_0 i\vec{k} \cdot \hat{v}_1 = 0, \quad (2.32)$$

$$i\omega \hat{B}_1 = (\vec{B}_0 i\vec{k} \cdot -\vec{B}_0 \cdot i\vec{k}) \hat{v}_1, \quad (2.33)$$

$$i\vec{k} \cdot \hat{B}_1 = 0. \quad (2.34)$$

There is no loss of generality if we choose $\vec{B}_0 = (0, 0, B_0)$ and $\vec{k} = (k \cos \theta, 0, k \sin \theta) = (k_\perp, 0, k_\parallel)$. Hence, can express the set of equations through matrix representation and obtain the following system:

$$\begin{pmatrix} 0 & \rho_{m0} k_\perp & 0 & \rho_{m0} k_\parallel & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & k_\perp & -\frac{1}{\mu_0} k_\parallel B_0 & 0 & \frac{1}{\mu_0} k_\perp B_0 \\ 0 & 0 & 0 & 0 & 0 & 0 & -\frac{1}{\mu_0} k_\parallel B_0 & 0 \\ 0 & 0 & 0 & 0 & k_\parallel & 0 & 0 & 0 \\ 0 & \gamma p_0 k_\perp & 0 & \gamma p_0 k_\parallel & 0 & 0 & 0 & 0 \\ 0 & -B_0 k_\parallel & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & -B_0 k_\parallel & 0 & 0 & 0 & 0 & 0 \\ 0 & B_0 k_\perp & 0 & 0 & 0 & 0 & 0 & 0 \end{pmatrix} \begin{pmatrix} \hat{\rho}_{m1} \\ \hat{v}_{1x} \\ \hat{v}_{1y} \\ \hat{v}_{1z} \\ \hat{p}_1 \\ \hat{B}_{1x} \\ \hat{B}_{1y} \\ \hat{B}_{1z} \end{pmatrix} = \omega \begin{pmatrix} \hat{\rho}_{m1} \\ \rho_{m0} \hat{v}_{1x} \\ \rho_{m0} \hat{v}_{1y} \\ \rho_{m0} \hat{v}_{1z} \\ \hat{p}_1 \\ \hat{B}_{1x} \\ \hat{B}_{1y} \\ \hat{B}_{1z} \end{pmatrix} \quad (2.35)$$

Now that we have obtained the dispersion equation, we will switch to the velocity representation, which is very useful and powerful. For this purpose, firstly differentiate the equation 2.26 with respect to time, obtaining:

$$\rho_m \frac{\partial^2 \vec{v}_1}{\partial t^2} = -\nabla \left(\frac{\partial p_1}{\partial t} \right) - \frac{1}{\mu_0} \left[\left(\nabla \frac{\partial \vec{B}_1}{\partial t} \right) \cdot \vec{B}_0 - (\vec{B}_0 \cdot \nabla) \frac{\partial \vec{B}_1}{\partial t} \right]. \quad (2.36)$$

Next, using 2.27 and 2.28, we can write 2.36 as:

$$\rho_m \frac{\partial^2 \vec{v}_1}{\partial t^2} - \left[\left(\frac{(\vec{B}_0 \cdot \nabla)^2}{\mu_0} \right) \vec{I} + \left(\gamma p_0 + \frac{\vec{B}_0^2}{\mu_0} \right) \nabla \nabla - \frac{\vec{B}_0 \cdot \nabla}{\mu_0} (\nabla \vec{B}_0 + \vec{B}_0 \nabla) \right] \cdot \vec{v}_1 = 0, \quad (2.37)$$

where $\vec{I}$ is the unit matrix. Inserting the plane wave solutions ($\nabla \longrightarrow i\vec{k}$ and $\frac{\partial}{\partial t} \longrightarrow -i\omega$), and using the matrix representation, we obtain

$$\begin{pmatrix} -(\frac{\gamma p_0}{\rho_{m0}} + \frac{B_0^2}{\mu_0 \rho_{m0}})k_\perp^2 - \frac{B_0^2 k_\parallel^2}{\mu_0 \rho_{m0}} & 0 & -\frac{\gamma p_0}{\rho_{m0}} k_\perp k_\parallel \\ 0 & -\frac{B_0^2 k_\parallel^2}{\mu_0 \rho_{m0}} & 0 \\ -\frac{\gamma p_0}{\rho_{m0}} k_\perp k_\parallel & 0 & -\frac{\gamma p_0}{\rho_{m0}} k_\parallel^2 \end{pmatrix} \begin{pmatrix} \hat{v}_{1x} \\ \hat{v}_{1y} \\ \hat{v}_{1z} \end{pmatrix} = -\omega^2 \begin{pmatrix} \hat{v}_{1x} \\ \hat{v}_{1y} \\ \hat{v}_{1z} \end{pmatrix} \quad (2.38)$$

In order to have a nontrivial solution ($\hat{v}_1 \neq 0$), the determinant of the 3×3 matrix of the set of equations 2.38 must vanish. After some calculations and taking into account that, $k^2 = k_\perp^2 + k_\parallel^2$, we obtain the following expression:

$$Det = \left[\omega^2 - \frac{B_0^2 k_\parallel^2}{\mu_0 \rho_{m0}} \right] \left[\omega^4 - \left(\frac{\gamma p_0}{\rho_{m0}} + \frac{B_0^2}{\mu_0 \rho_{m0}} \right) k^2 \omega^2 + \left(\frac{\gamma p_0}{\rho_{m0}} \frac{B_0^2}{\mu_0 \rho_{m0}} \right) k_\parallel^2 k^2 \right] = 0. \quad (2.39)$$

From the expression 2.39, we can identify two dispersion relations:

$$\omega^2 - V_A^2 k_\parallel^2 = 0, \quad (2.40)$$

$$\omega^4 - (C_s^2 + V_A^2) k^2 \omega^2 + (C_s^2 V_A^2) k_\parallel^2 k^2 = 0, \quad (2.41)$$

where $C_s = (\frac{\gamma p_0}{\rho_{m0}})^{1/2}$ and $V_A = (\frac{B_0^2}{\mu_0 \rho_{m0}})^{1/2}$ are the speed of sound and the Alfvén speed, respectively.

Equation 2.40 is the dispersion relation for low-frequency "*shear Alfvén waves*", where V_A is the characteristic speed and ω_A is the Alfvén frequency, $\omega_A = \pm V_A k_\parallel$, with phase velocity $\pm V_A$, where the positive sign corresponds to waves propagating in the direction of $\vec{B}_0$ and the negative sign corresponds to waves propagating in the opposite direction. Equation 2.41 is the dispersion relation for low-frequency "*magnetosonic*" or "*magnetoacoustic wave*",

$$\omega_F^2 = \frac{k^2}{2} \left[V_A^2 + C_s^2 + \left[(V_A^2 + C_s^2)^2 - \frac{4V_A^2 C_s^2 k_\parallel^2}{k^2} \right]^{\frac{1}{2}} \right], \quad (2.42)$$

$$\omega_S^2 = \frac{k^2}{2} \left[V_A^2 + C_s^2 - \left[(V_A^2 + C_s^2)^2 - \frac{4V_A^2 C_s^2 k_\parallel^2}{k^2} \right]^{\frac{1}{2}} \right], \quad (2.43)$$

where ω_F and ω_S are the fast magnetoacoustic frequency and the slow magnetoacoustic frequency, respectively.

Our main objective is the analysis of the Alfvén mode in the ideal MHD model. For this purpose we will use an orthogonal system of vectors, as show the figure 2.1, to discuss the polarization properties of the Alfvén mode [53].

Figure 2.1: Orthogonal system of vectors [53].

We can see that the phase velocity V_A is independent of $|k|$ for the Alfvén mode, so that this mode is non-dispersive. We define the unit vectors $\hat{b} = (0, 0, 1)$, $\hat{a} = (0, 1, 0)$ and $\hat{t} = \hat{a} \times \hat{k}$, where $\hat{a} = -\frac{\vec{k} \times \vec{B}_0}{|\vec{k} \times \vec{B}_0|}$, $\hat{k} = (\sin\theta, 0, \cos\theta)$ and $\hat{t} = (\cos\theta, 0, -\sin\theta)$. In this system, the dispersion relation for the shear Alfvén wave becomes;

$$\frac{\omega_A}{k \cos\theta} = \frac{\omega_A}{k_{\parallel}} = \pm V_A. \quad (2.44)$$

We can see that phase velocity ω_A/k is anisotropic because it depends on the angle of propagation θ . The eigenfunction of the Alfvén mode, system 2.38, is in the y-direction only, it is parallel to vector $\hat{a}$, perpendicular to $\vec{B}_0$ and $\vec{k}$. Thereby, we can conclude that $\hat{v}_{1x} = \hat{v}_{1z} = 0$. Using the previous fact and the system 2.35, we see that $\hat{v}_{1x} = \hat{v}_{1z} = \hat{B}_{1x} = \hat{B}_{1z} = \hat{p}_1 = \hat{\rho}_{m1} = 0$ and $\hat{B}_{1y} = -(\frac{B_0}{\pm V_A})\hat{v}_{1y}$. Using the Ohm's law, equation 2.14, to calculate the direction of the perturbed electric field, we find that $\hat{E}_{1x} = -\pm V_A \hat{B}_{1y}$.

Through these results, we note that there is no density and particle pressure perturbation for this mode, that the magnetic field perturbation is in the y-direction, and that the wave electric field perturbation, which is perpendicular to the magnetic field direction, is not purely transverse to the direction of propagation, being in the x-direction. In the figure 2.2, we show a scheme with the directions of the perturbed variables.

Figure 2.2: (a) Directions of the perturbed variables for V_A in the direction of $\vec{B}_0$. (b) Directions of the perturbed variables for V_A in the opposite direction of $\vec{B}_0$.

Because $\hat{B}_1$ is perpendicular to $\vec{B}_0$, we can say that the magnetic field strength is constant to first order:

$$\vec{B}_{total} = \vec{B}_1 + \vec{B}_0 \Rightarrow \vec{B}_{total}^2 \simeq \vec{B}_0^2 + 2\vec{B}_1 \cdot \vec{B}_0 \simeq \vec{B}_0^2. \quad (2.45)$$

Since in the Alfvén mode the strengths of the magnetic field and particle pressures are conserved variables, there is no compressive stress due to this "*non-compressional shear wave*". We can add that the Alfvén frequency is between the frequencies of the slow and fast magnetoacoustic wave, "*intermediate waves*" [50],

$$0 \lesssim \omega_S^2 \lesssim \omega_A^2 \lesssim \omega_F^2 < \infty. \quad (2.46)$$

An important feature of the Alfvén mode is the fact that it acts to reduce the additional

curvature of the field line, because of the plasma flow across the magnetic field increases the bending of the field.

Finally from the equations 2.40 and 2.45, we conclude that the Alfvén wave dispersion relation is independent of the wave vector component perpendicular to the equilibrium magnetic field. Therefore, as the wave cannot propagate perpendicular to the field, it only propagates parallel to the field, maintaining a constant value of the magnetic field strength to first order, as shown in figure 2.3.

Figure 2.3: Distortion of lines of force by an Alfvén wave, for the case that V_A is in the direction of $\vec{B}_0$ [54].

From the calculation of the Poynting vector, $\vec{S} = \pm V_A \frac{B_{1y}^2}{\mu_0} \hat{e}_z$, and the group velocity vector, $\vec{V}_g = \pm V_A \hat{b}$, we can conclude that the wave energy is always carried along the direction of $\vec{B}_0$, independently of the direction of the wave vector. For the particular case of a cold plasma, which considers $C_S = 0$ and parallel propagation, i.e. $\theta = 0$, the Alfvén frequency and the fast magnetoacoustic frequency are equal ($\omega_A^2 = \omega_F^2$), while the slow magnetoacoustic frequency is null ($\omega_S^2 = 0$) [55].

2.1.2 Alfvén waves in the Hall-MHD model

In this section, we analyze the Hall-MHD model that describes a two-fluid plasma with massless electrons ($m_e \lll m_i$), which maintains charge neutrality at all times and

are considered to be magnetized (electron cyclotron period much shorter than time-scale of interest). The plasma consists of an electron fluid and a single ion species fluid. The ion cyclotron effects are taken into account in the model, where the wave frequency is comparable or up to and beyond the ion cyclotron frequency, but well below the electron cyclotron frequency $\Omega_i \lesssim \omega < \Omega_e$ [56–58].

The equations governing the Hall-MHD model are the same equations used in the ideal MHD model, except that in the Ohm's law 2.14, the Hall term $\frac{\vec{J} \times \vec{B}}{en_i}$ is retained, where n_i is the ion number density, and we continue assuming resistivity to be negligible, so that we have the following expression for the Ohm's law:

$$\vec{E} + \vec{V} \times \vec{B} = \frac{\vec{J} \times \vec{B}}{en_i}. \quad (2.47)$$

Using the equations 2.17, 2.18 and the vector identity A.8, we obtain:

$$\frac{\partial \vec{B}}{\partial t} = \nabla \times \left[\left(\vec{V} - \frac{1}{en_i \mu_0} \nabla \times \vec{B} \right) \times \vec{B} \right]. \quad (2.48)$$

Therefore, the Hall-equations are:

$$\frac{\partial \rho_m}{\partial t} + \nabla \cdot (\rho_m \vec{v}) = 0, \quad (2.49)$$

$$\rho_m \frac{d\vec{v}}{dt} = -\nabla p + \vec{J} \times \vec{B}, \quad (2.50)$$

$$\frac{\partial p}{\partial t} + \vec{v} \cdot \nabla p + \gamma p \nabla \cdot \vec{v} = 0, \quad (2.51)$$

$$\frac{\partial \vec{B}}{\partial t} = \nabla \times \left[\left(\vec{V} - \frac{1}{en_i \mu_0} \nabla \times \vec{B} \right) \times \vec{B} \right]. \quad (2.52)$$

$$\nabla \cdot \vec{B} = 0. \quad (2.53)$$

Note that due to the assumption of charge neutrality, the number density of ions is equal to the number density of electrons, $n_i = n_e$. Therefore, equation 2.52 can be written in the form [59]:

$$\frac{\partial \vec{B}}{\partial t} = \nabla \times \left[\left(\vec{V} - \frac{1}{en_e \mu_0} \nabla \times \vec{B} \right) \times \vec{B} \right]. \quad (2.54)$$

However, in this section we only will work with the equation 2.52.

We now linearize the equations above, considering harmonic plane wave solutions, as in the case of MHD ideal, and remembering that $\vec{k} = (k_\perp, 0, k_\parallel)$ and $\vec{B}_0 = (0, 0, B_0)$. Therefore, will have the following set of linearized Hall-MHD equations:

$$\omega \hat{\rho}_{m1} = \rho_{m0}(\vec{k} \cdot \hat{v}_1), \quad (2.55)$$

$$\omega \rho_{m0} \hat{v}_1 = \vec{k} \hat{p}_1 + \frac{1}{\mu_0} [(\vec{k} \vec{B}_0 \cdot - \vec{k}_0 \cdot \vec{B}_0) \hat{B}_1], \quad (2.56)$$

$$\omega \hat{p}_1 = \gamma p_0(\vec{k} \cdot \hat{v}_1), \quad (2.57)$$

$$\omega \hat{B}_1 = \frac{i}{en_i \mu_0} [\vec{k} \times [(\vec{k} \vec{B}_0 \cdot - (\vec{k} \cdot \vec{B}_0)) \vec{B}_1]] - (\vec{B}_0 \vec{k} \cdot - (\vec{B}_0 \cdot \vec{k})) \hat{v}_1, \quad (2.58)$$

$$\vec{k} \cdot \hat{B}_1 = 0. \quad (2.59)$$

Now, substituting equation 2.57 in equation 2.56 and taking the inner product with $\vec{k}$, we obtain,

$$(\vec{k} \cdot \hat{v}_1) = \frac{k^2 B_{1z} V_A^2 \omega}{B_0 [\omega^2 - C_S^2 k^2]}. \quad (2.60)$$

Using the expression $i\vec{k} \times \hat{B}_1 = \mu_0 \hat{J}_1$ in equation 2.58 and clearing $\hat{v}_1$ of the equation resulting from the substitution of equation 2.57 in equation 2.56, we obtain the following two equations:

$$\omega \hat{B}_1 = -\frac{1}{en_i} [\hat{J}_1(\vec{k} \cdot \vec{B}_0)] - \vec{B}_0(\vec{k} \cdot \hat{v}_1) + (\vec{B}_0 \cdot \vec{k}) \hat{v}_1, \quad (2.61)$$

$$\hat{v}_1 = \frac{C_S^2}{\omega^2} (\vec{k} \cdot \hat{v}_1) \vec{k} + \frac{V_A^2}{B_0 \omega} (\hat{B}_{1z} \vec{k} - k_z \hat{B}_1). \quad (2.62)$$

Substituting the equation 2.62 in the equation 2.61:

$$\omega \hat{B}_1 = -\frac{1}{en_i} k_z B_0 \hat{J}_1 + (\vec{B}_0 - \frac{C_S^2}{\omega^2} k_z B_0 \vec{k})(\vec{k} \cdot \hat{v}_1) + \frac{k_z V_A^2}{\omega} (\hat{B}_{1z} \vec{k} - k_z \hat{B}_1). \quad (2.63)$$

Now, analyzing the z-component of the last equation and using equation 2.60, we obtain:

$$\omega \hat{B}_{1z} = -\frac{1}{en_i} k_z B_0 \hat{J}_{1z} + k^2 V_A^2 \hat{B}_{1z} \left[\frac{(\omega^2 - k_z^2 C_S^2)}{\omega(\omega^2 - C_S^2 k^2)} \right]. \quad (2.64)$$

Analyzing the z-component of the cross product of $\vec{k}$ on the equation resulting from the substitution of equation 2.57 into equation 2.56 and, on the other hand, the z-component

of equation 2.61 and substituting both results in equation 2.64, after several algebraic manipulations we obtain the dispersion relation of the Hall-MHD as:

$$(\omega^2 - k_z^2 V_A^2)[\omega^4 - \omega^2 k^2 (C_S^2 + V_A^2) + k^2 k_z^2 V_A^2 C_S^2] = \left(\frac{\omega}{\Omega_i}\right)^2 k^2 k_z^2 V_A^4 (\omega^2 - C_S^2 k^2), \quad (2.65)$$

we can identify the factor $(\frac{\omega}{\Omega_i})^2$ as the Hall term or Hall parameter, where $\Omega_i = \frac{eB_0}{m_i}$ is the ion cyclotron frequency.

We can see in the dispersion relation 2.65 that the Hall term couples the shear Alfvén mode to the fast and slow magnetosonic modes. It is very interesting the fact that the Hall term may be viewed as a singular perturbation of the ideal MHD equations, which increases the order of the highest derivative in the system and changes its dispersion equation [60].

It is easy to see that if $\frac{\omega}{\Omega_i} \lll 1 \rightarrow 0$ (low-frequency), the Hall- MHD dispersion relation 2.65 reduces to the ideal MHD dispersion relation 2.39. The Hall-MHD dispersion relation is a higher order dispersion and proportional to k^4 , only in the case that the Hall term and C_S^2 are simultaneously nonzero. We can consider two cases of interest, a cold plasma and a warm plasma.

In the case of cold plasma [55] and [61], we consider the zero pressure, i.e. $C_S^2 = 0$ and the zero plasma beta, i.e. $\beta = \frac{2\mu_0 p}{B^2} = 0$, the Hall- MHD dispersion relation takes the form:

$$(\omega^2 - k_z^2 V_A^2)[\omega^2 - k^2 V_A^2] = \left(\frac{\omega}{\Omega_i}\right)^2 k^2 k_z^2 V_A^4. \quad (2.66)$$

In the limit of low-frequency, the slow magnetoacoustic mode disappears in the equation above and the fast magnetoacoustic mode becomes isotropic, i.e. $\omega = \pm V_A k$, as presented for the case of a low- β plasma ($V_A^2 \gg C_S^2$) in the ideal MHD model. Moreover, considering that $k_z = k_{\parallel} = k \cos \theta$, we can derive the expression of the frequencies of the two modes. For Alfvén waves from 2.66 when the parameter $\frac{k_z V_A}{\Omega_i} \lll 1$, we arrive at the expression $\omega_{\pm} = \frac{k_z^2 V_A^2}{1 + \frac{k_z^2 V_A^2}{\Omega_i^2}}$. From equation 2.66 and after some algebraic manipulations, we arrive at the following expression:

$$\omega_{\pm}^2 = \frac{k_z^2 V_A^2}{2} [(1 + (1 + \alpha^2) \cos^2 \theta) \pm [1 - 2(1 - \alpha^2) \cos^2 \theta + (1 + \alpha^2)^2 \cos^4 \theta]^{\frac{1}{2}}], \quad (2.67)$$

where, $\alpha^2 = \frac{k^2 V_A^2}{\Omega_i^2}$, ω_{-}^2 is the ion cyclotron mode and ω_{+}^2 is the fast magnetoacoustic mode.

Let us analyze the ion cyclotron mode, which is the version of the Alfvén mode to the Hall- MHD in the regime of low-frequency and considering a cold plasma. In order to calculate the ion cyclotron resonance ($k, \alpha \rightarrow \infty$), equation 2.67 can take the form:

$$\frac{\omega_-^2}{\Omega_i^2} = \frac{\alpha^2}{2} [(1 + (1 + \alpha^2)\cos^2\theta) - [1 - 2(1 - \alpha^2)\cos^2\theta + (1 + \alpha^2)^2\cos^4\theta]^{\frac{1}{2}}]. \quad (2.68)$$

Now, we multiply and divide by the conjugate to the equation above and consider the limit $\alpha \rightarrow \infty$; we obtain that $\frac{\omega_-^2}{\Omega_i^2} \rightarrow 1$. Therefore, when $k \rightarrow \infty$ then $\omega_- \rightarrow \Omega_i$ and the group velocity goes to zero, so that in the cyclotron resonance point the wave energy accumulates and the wave fields grow to values that are limited by dissipative or nonlinear mode conversion processes. It can be proved that the ion cyclotron mode is represented by a left-hand circular polarization of the electric field.

If the propagation is parallel, i.e. $\theta = 0^\circ \Rightarrow \vec{k} = k_z \hat{e}_z$, the ion cyclotron mode takes the form:

$$\omega_{\pm} = \frac{k_z V_A}{2} [(4 + \alpha^2)^{\frac{1}{2}} - \alpha]. \quad (2.69)$$

The expression 2.69 is know as the "*slow Alfvén wave*", which has a phase velocity smaller than V_A and experiments an ion cyclotron resonance when $\omega_- \rightarrow \Omega_i$. Hence, we can see that the Hall-term not only increases the wave frequency values comparable to or higher than the ion cyclotron frequency, but also removes the low-frequency degeneracy of the parallel propagating Alfvén wave.

Now, we will analyzed the case of a warm plasma [61], where $C_S^2 \neq 0$. As indicated above, the Hall-term present in equation 2.69 couples the Alfvén dispersion equation to the fast and slow magnetoacoustic dispersion equation and represents three types of nontrivial Hall-MHD waves. Firstly, we can recast the equation 2.65 as:

$$(f^2 - \alpha^2 \cos^2\theta)[f^4 - f^2(\alpha^2 \sigma + \alpha^2) + \alpha^4 \sigma \cos^2\theta] - f^2 \alpha^4 \cos^2\theta (f^2 - \sigma \alpha^2) = 0, \quad (2.70)$$

where $f = \frac{\omega}{\Omega_i}$ and $\sigma = \frac{C_s^2}{V_A^2}$.

In the case when $\theta = 0^\circ$ from equation 2.70 we can identify three type of waves

$$f^2 = \alpha^2 \sigma, \quad (2.71)$$

$$f_-^2 = \frac{2}{[\frac{2}{\alpha^2} + 1] - [\frac{4}{\alpha^2} + 1]^{\frac{1}{2}}}, \quad (2.72)$$

$$f_+^2 = \frac{2}{\left[\frac{2}{\alpha^2} + 1\right] + \left[\frac{4}{\alpha^2} + 1\right]^{\frac{1}{2}}}. \quad (2.73)$$

The expressions 2.71 and 2.72 are the dispersion relations for the slow and fast waves, while the expression 2.73 is called the dispersion relation for the intermediate waves. If $\theta = 90^\circ$, we obtain the following dispersion relations:

$$f^2 = f_+^2 = 0, \quad (2.74)$$

$$f_-^2 = \alpha^2(\sigma + 1). \quad (2.75)$$

When $\theta = 90^\circ$ the slow and intermediate waves are null and only the fast waves is observed. For parallel propagation the intermediate waves are identified as Alfvén waves, are uncoupled with the magnetoacoustic waves and experience ion cyclotron resonance. For oblique angles of propagation the slow magnetoacoustic and the intermediate waves reconnect to form new intermediate wave which does not experience a resonance and they have a phase speed intermediate between the fast and slow speeds at all frequencies.

2.1.3 Alfvén waves in the resistive MHD model

The resistive MHD model is an extension of the ideal MHD model [50]. The basic equations of the resistive MHD model, are given by:

$$\frac{\partial \rho_m}{\partial t} + \nabla \cdot (\rho_m \vec{v}) = 0, \quad (2.76)$$

$$\rho_m \left(\frac{\partial \vec{v}}{\partial t} + \vec{v} \cdot \nabla \vec{v} \right) + \nabla p - \rho_m \vec{g} - \vec{J} \times \vec{B} = 0, \quad (2.77)$$

$$\frac{\partial p}{\partial t} + \vec{v} \cdot \nabla p + \gamma p \nabla \cdot \vec{v} = (\gamma - 1) \eta |\vec{J}|^2, \quad (2.78)$$

$$\frac{\partial \vec{B}}{\partial t} + \nabla \times \vec{E} = 0, \quad (2.79)$$

where

$$\vec{J} = \mu_0^{-1} (\nabla \times \vec{B}), \quad (2.80)$$

$$\vec{E} + \vec{v} \times \vec{B} = \eta \vec{J}, \quad (2.81)$$

and

$$\nabla \cdot \vec{B} = 0. \quad (2.82)$$

Using Faraday's law and Ohm's law, equations 2.79 and 2.81 respectively, we obtain the induction equation (flux equation)

$$\frac{\partial \vec{B}}{\partial t} = \nabla \times (\vec{v} \times \vec{B}) - \nabla \times (\eta \vec{J}). \quad (2.83)$$

We note, that unlike the ideal MHD model, in the resistive MHD model the resistivity enters through the Ohmic dissipation term in the internal energy equation and through the resistive diffusion in the induction equation.

Now, if we linearize the resistive MHD equations, as it was done in the previous cases, assuming small amplitude perturbations about a static equilibrium, $f(\vec{v}, t) = f_0(x) + f_1(x)e^{i(k_y y + k_z z - \omega t)}$, which really is not justified since resistivity causes the magnetic field to decay (*for more details see [62]*), and considering a plasma slab with a constant resistivity η , the set of linearized resistive MHD equations are:

$$\frac{\partial \rho_{m1}}{\partial t} + \nabla \cdot (\rho_{m0} \vec{v}_1) = 0, \quad (2.84)$$

$$\rho_{m0} \left(\frac{\partial \vec{v}_1}{\partial t} + \nabla p_1 - \rho_{m1} \vec{g} + \vec{B}_0 \times (\nabla \times \vec{B}_1) - (\nabla \times \vec{B}_0) \times \vec{B}_1 \right) = 0, \quad (2.85)$$

$$\frac{\partial p_1}{\partial t} + \vec{v}_1 \cdot \nabla p_0 + \gamma p_0 \nabla \cdot \vec{v}_1 = 2(\gamma - 1)\eta \nabla \times \vec{B}_0 \cdot \nabla \times \vec{B}_1, \quad (2.86)$$

$$\frac{\partial \vec{B}_1}{\partial t} = \nabla \times (\vec{v}_1 \times \vec{B}_0) + \eta \nabla^2 \vec{B}_1. \quad (2.87)$$

We can see that the resistive terms mess up the integration of the equations for the values ρ_{m1} , p_1 and $\vec{B}_1$. Let's take the x -direction as one direction of inhomogeneity normal to y -direction and z -direction respectively. We can defined the variables:

$$\begin{aligned} \vec{k}_0 &= (0, k_y, k_z) \quad \therefore \quad \vec{k}_0^2 = k_y^2 + k_z^2, \\ u &\equiv v_{1x}, \\ v &\equiv (\nabla \times \vec{v}_1)_x = -i(k_z v_{1y} - k_y v_{1z}), \\ w &\equiv \nabla \cdot \vec{v}_1 - v'_{1x} = i(k_y v_{1y} + k_z v_{1z}), \\ B_1 &\equiv -iB_{1x}, \\ R &\equiv i(\nabla \times \vec{B}_1)_x = i j_{1x} = k_z B_{1y} - k_y B_{1z}, \end{aligned} \quad (2.88)$$

where $\vec{k}_0$ is the horizontal wave vector, u is the normal velocity, v is the normal vorticity, w is the horizontal part of the compressibility, B_1 is the normal magnetic field perturbation, R is the perturbed normal current and the $(\prime)$ represents the derivative with respect to x . Taking into account the projections of the horizontal wave vector onto the magnetic field, we obtain $G \equiv e_x \cdot (\vec{k}_0 \times \vec{B}_0) = k_y B_{0z} - k_z B_{0y}$ and $F \equiv \vec{k}_0 \cdot \vec{B}_0 = k_y B_{0y} + k_z B_{0z}$, respectively. These quantities depend only on x , since the physical variables in the equilibrium are inhomogeneous in x . Using the previous physical variables, equations 2.84 – 2.87 become:

$$-i\omega\rho_{m1} + (\rho_{m0}u)' + \rho_{m0}w = 0, \quad (2.89)$$

$$-i\rho_{m0}\omega u + (p_1)' + \rho_{m1}\vec{g} - k_0^{-2}(F(B_1)' + GR)' + FB_1 = 0, \quad (2.90)$$

$$-i\rho_{m0}\omega v + G'B_1 + FR = 0, \quad (2.91)$$

$$-i\rho_{m0}\omega w - k_0^2 p_1 + F'B_1 + GR = 0, \quad (2.92)$$

$$-i\omega p_1 + p_0' u + \gamma p_0(u' + w) + 2(\gamma - 1)\eta k_0^{-2}[F'(B_1'' - k_0^2 B_1) + G'R'] = 0, \quad (2.93)$$

$$-i\omega B_1 - Fu - \eta(B_1'' - k_0^2 B_1) = 0, \quad (2.94)$$

$$-i\omega R - (Gu)' + Fv - Gw - \eta(R'' - k_0^2 R) = 0, \quad (2.95)$$

We can see that, in the limit case $\eta \rightarrow 0$ we obtain the ideal MHD equations. Let's turn our attention to the incompressible case, where we take the limits $\gamma \rightarrow \infty$ and $\nabla \cdot \vec{v}_1 \rightarrow 0$ simultaneously, whereupon, the variable w is known in terms of u of the form $w = -u'$ and, therefore, p_1 can be determined. Considering the component of the displacement vector $\vec{\xi} \equiv \frac{i\vec{u}}{\omega}$, we obtain the following sixth order system:

$$\eta[(\rho_{m0}\omega^2\xi')' - k_0^2(\rho_{m0}\omega^2 + \rho_{m0}'g)\xi + F''B_1] + i\omega F(B_1 - F\xi) = 0, \quad (2.96)$$

$$\eta(B_1'' - k_0^2 B_1) + i\omega(B_1 - F\xi) = 0, \quad (2.97)$$

$$\eta(R'' - k_0^2 R) + i\omega(R - G'\xi) - \frac{iF}{\rho_{m0}\omega}(FR - G'B_1) = 0. \quad (2.98)$$

We will now study the case when the equilibrium quantities are completely homogeneous. Therefore, to the incompressible resistive MHD equations, we obtain:

$$\eta\rho_{m0}\omega^2(\xi'' - k_0^2\xi) - i\omega F(B_1 - F\xi) = 0, \quad (2.99)$$

$$\eta(B_1'' - k_0^2B_1) + i\omega(B_1 - F\xi) = 0. \quad (2.100)$$

We note that the equation 2.98 was not considered, this is because the variable R does not appear in the equations 2.96 and 2.97; therefore, we can restrict the analysis to the two first equation for the variables ξ and B_1 . Assuming a harmonic dependence in the x -direction, i.e. $\frac{d}{dx} = ik_x$ and introducing the resistive parameter $\tilde{\eta} \equiv \frac{\eta k^2}{2\omega_A}$, where $k^2 \equiv k_x^2 + k_y^2 + k_z^2$ and ω_A is the known continuum Alfvén frequency of the ideal MHD model, we obtain the dispersion equation

$$\omega^2 + 2i\tilde{\eta}\omega_A\omega - \omega_A^2 = 0, \quad (2.101)$$

with the solution

$$\omega = \omega_A(\pm\sqrt{1 - \tilde{\eta}^2} - i\tilde{\eta}) = 0. \quad (2.102)$$

We can see that to the incompressible resistive MHD model with a homogeneous and incompressible plasma, the frequency depends directly on the resistive parameter, and it is reduced to ideal MHD model when $\tilde{\eta} \rightarrow 0$. The case when the equilibrium quantities are inhomogeneous and the plasma is compressible will be studied, in detail, in the chapter four specifically when we analyze the case of toroidal geometry (toroidal model of Alfvén waves).

Chapter 3

Cylindrical model of Alfvén waves

In this chapter we will derive in detail the equations that will be used for the discussion of Alfvén Wave modes in the cylindrical model [65–67]. For this purpose, we work within the framework of cold-plasma theory in the low frequency regime considering the effects of a finite $\frac{\omega}{\omega_{ci}}$ ratio [68], i.e. ($\omega \leq \omega_{ci} \ll \omega_{ce}$), where kinetic and resistive effects are not considered, but the Hall effect is taken into account. We express the equations describing the Alfvén Wave modes in Gaussian units (centimeter-gram-second system of units (*cgs*)) as are described by Appert *et al.* in [67]. Since it is convenient to derive the plasma equations with the simplest possible structure, we will use local cylindrical coordinates, or the magnetic coordinates, which are written out explicitly in the appendix B, to obtain the dispersion relation of the Alfvén wave.

Subsequently, we will discuss the main aspects of the electromagnetic wave equation, the antenna, and the boundary conditions pertinent to the model (plasma-vacuum, vacuum-antenna-vacuum and vacuum-chamber) and power absorbed by the plasma column. We then present a short discussion of the modes in the continuum spectrum (singular modes) and analyze the theory of the global Alfvén waves (discrete modes) in the cylindrical model. Finally, we present, a brief description of the TCABR and JET tokamaks (story, geometry antennas system, and main parameters).

3.1 Theory of waves in a cold magnetized cylindrical plasma column

We begin by deriving the basic plasma equations in cylindrical geometry. A circular cross-section tokamak with large aspect ratio $\epsilon = \frac{a}{R} \lll 1$, where R and a are the major and minor radii, respectively, can be considered as a straight periodic cylindrical plasma column, with the usual correspondence, $k = n/R$, between the longitudinal (z -direction) wave number k and the toroidal wave number n .

Therefore, in this model we consider a cylindrical plasma column, with radius r_p , subjected to an equilibrium helical magnetic field denoted by $\vec{B}_o(\vec{r}) = B_{o\theta}\hat{e}_\theta + B_{oz}\hat{e}_z$. Other relevant physical quantities are $n_{io}(\vec{r})$, $n_{eo}(\vec{r})$, $\vec{v}_{io}(\vec{r})$ and $\vec{v}_{eo}(\vec{r})$, the ion and electron densities and mean velocities, respectively. All equilibrium quantities are functions of the radial cylindrical coordinate r . We assume the electric field $\vec{E}_o$ to be zero. These quantities have to satisfy the equation of motion for particles that constitute the plasma (ions and electrons):

$$m_\alpha n_\alpha \frac{\partial \vec{v}_\alpha}{\partial t} + m_\alpha n_\alpha (\vec{v}_\alpha \cdot \nabla) \vec{v}_\alpha = -\nabla p_\alpha + q_\alpha n_\alpha \left(\frac{\vec{v}_\alpha \times \vec{B}}{c} + \vec{E} \right), \quad (3.1)$$

where m_α , q_α , n_α , p_α and $\vec{v}_\alpha$ represent the mass, charge, density, pressure and mean velocity of the particles of species α , respectively, and the quasineutrality condition:

$$\sum_i Z_i n_{io} = n_{eo}, \quad (3.2)$$

here, the sum is extended over all ion species i of charge number Z_i .

The equations will be derived in the large aspect ratio tokamak approximation ($B_{o\theta} \ll B_{oz}$, $B_{oz} \approx \text{const}$) and low- β MHD limit ($\nabla p_{eo} \approx \nabla p_{io} \approx 0$). We linearize the equations of motion assuming that all physical quantities can be expressed as $\chi_\alpha(\vec{r}, t) = \chi_{\alpha o}(\vec{r}) + \chi_{\alpha 1}(\vec{r}, t)$, where $\chi_{\alpha o}(\vec{r})$ corresponds to the equilibrium value and $\chi_{\alpha 1}(\vec{r}, t)$ is the perturbation ($|\chi_{\alpha o}(\vec{r})| \gg |\chi_{\alpha 1}(\vec{r}, t)|$).

Let us start with the equation of motion for electrons. Firstly, we assume a equilibrium velocity $\vec{v}_{eo} = V_o \hat{e}_\parallel$, where $|V_o| \propto |\frac{B_{o\theta}}{B_{oz}}|$ and $\hat{e}_\parallel = \frac{\vec{B}_o}{B_o}$. Since we consider small-amplitude perturbations with frequencies $\omega \lesssim \omega_{ci} \ll \omega_{ce}$ in a cold current-carrying plasma, where

ω_{ci} and ω_{ce} are the cyclotron frequency for ions and electrons, respectively, we can assume that the mass of the electrons is negligible $m_i \gg m_e \rightarrow 0$ (infinite mobility along the magnetic field). Taking into account these approximations and considerations, we obtain from the equation of motion:

$$\vec{E}_1 + \frac{1}{c}\vec{v}_{e1} \times \vec{B}_o + \frac{V_o}{c}\hat{e}_{||} \times \vec{B}_1 = 0. \quad (3.3)$$

We can apply the vector operators $\hat{e}_{||} \cdot$ and $\hat{e}_{||} \times$ to equation (3.3). In the first case is easy to see that we obtain $\hat{e}_{||} \cdot \vec{E}_1 = 0$, while in the second case we obtain:

$$\vec{v}_{e1} - v_{e1||}\hat{e}_{||} = -\frac{1}{B_o}[c(\hat{e}_{||} \times \vec{E}_1) - V_o(\vec{B}_1 - B_{1||}\hat{e}_{||})]. \quad (3.4)$$

The first term on the right-hand side is the electric drift force, and the second term is the equilibrium current term. Multiplying equation (3.4) by the factors $-en_{eo}$ and $\frac{4\pi}{\omega}$ we obtain the expression for the perpendicular component of the electron current density

$$\frac{4\pi}{\omega}(j_{e1\perp}\hat{e}_{\perp}) = \frac{4\pi}{\omega}(\vec{j}_{e1} - j_{e1||}\hat{e}_{||}) = \frac{4\pi en_{eo}}{\omega B_o}[c(\hat{e}_{||} \times \vec{E}_1) - V_o(\vec{B}_1 - B_{1||}\hat{e}_{||})]. \quad (3.5)$$

Now, recalling the expressions of the plasma frequency for ions ($\omega_{pi}^2 = \frac{4\pi n_{oi}q_i^2}{m_i}$), cyclotron frequency for ions ($\omega_{ci} = \frac{q_i B_o}{m_i c}$), the parallel component of Ampere's law for low-frequencies, ($j_{e0||} = -n_{eo}eV_o = \frac{c}{4\pi}(\vec{\nabla} \times B_o)_{||}$), and using the quasineutrality condition ($\sum_i \frac{\omega_{pi}^2}{\omega_{ci}} = \frac{4\pi n_{eo}ec}{B_o}$), we can rewrite equation (3.5) as

$$\frac{4\pi}{\omega}(j_{e1\perp}\hat{e}_{\perp}) = \sum_i \frac{\omega_{pi}^2}{\omega \omega_{ci}}(\hat{e}_{||} \times \vec{E}_1) + \frac{c}{\omega} \frac{(\vec{\nabla} \times B_o)_{||}}{B_o} \cdot (\vec{B}_1 - B_{1||}\hat{e}_{||}). \quad (3.6)$$

Now let us turn to the study of the ions. Since $m_i \gg m_e$, we can neglected the flow of ions in equilibrium ($\vec{v}_{io}$) and, assuming perturbed quantities varying as $e^{i(m\theta + kz - \omega t)}$, the equation of motion (3.1) for the ions to first order becomes

$$-i\omega\vec{v}_{i1} = \frac{q_i}{m_i}\vec{E}_1 + \frac{q_i}{m_i c}(\vec{v}_{i1} \times \vec{B}_o). \quad (3.7)$$

Applying the vector operators $\hat{e}_{||} \cdot$ to equation (3.7), we obtain that $\hat{e}_{||} \cdot \vec{v}_{i1} = \hat{e}_{||} \cdot \vec{E}_1 = 0 \Rightarrow v_{i1||} = 0$.

In order to calculate the current density, we apply the vector operator $\vec{B}_o \times$ to the equation of motion for ions

$$-i\omega(\vec{B}_o \times \vec{v}_{i1}) = \frac{q_i B_o}{m_i}(\hat{e}_{||} \times \vec{E}_1) + \frac{q_i B_o^2}{m_i c}[\hat{e}_{||} \times (\vec{v}_{i1} \times \hat{e}_{||})], \quad (3.8)$$

or

$$(\vec{B}_o \times \vec{v}_{i1}) = ic \frac{\omega_{ci}}{\omega}(\hat{e}_{||} \times \vec{E}_1) + i \frac{\omega_{ci}}{\omega} B_o \vec{v}_{i1}. \quad (3.9)$$

Replacing $(\vec{B}_o \times \vec{v}_{i1})$ into equation (3.7) and grouping the terms, we obtain:

$$\vec{v}_{i1} = -\frac{c}{B_o} \frac{1}{(1 - (\frac{\omega}{\omega_{ci}})^2)}(\hat{e}_{||} \times \vec{E}_1) - \frac{ic}{B_o} \frac{\frac{\omega}{\omega_{ci}}}{(1 - (\frac{\omega}{\omega_{ci}})^2)} \vec{E}_1. \quad (3.10)$$

As we did with the equation of motion for electrons (3.6), we can rewrite equation (3.10) as

$$(\frac{4\pi}{\omega}) \vec{j}_{i1} = -\frac{(\frac{\omega_{pi}^2}{\omega \omega_{ci}})}{(1 - (\frac{\omega}{\omega_{ci}})^2)}(\hat{e}_{||} \times \vec{E}_1) - i \frac{(\frac{\omega_{pi}}{\omega_{ci}})^2}{(1 - (\frac{\omega}{\omega_{ci}})^2)} \vec{E}_1. \quad (3.11)$$

Now, having obtained the expressions for the current density of electrons and ions, we can incorporate the current density into the equation for the dielectric tensor

$$\bar{\epsilon} \cdot \vec{E}_1 = \vec{E}_1 + i \frac{4\pi}{\omega}(\vec{j}_{e1} + \sum_i \vec{j}_{i1}), \quad (3.12)$$

and using the quantities S and D defined by Stix [69] we obtain

$$\bar{\epsilon} \cdot \vec{E}_1 = S \vec{E}_1 + iD(\hat{e}_{||} \times \vec{E}_1) + i \frac{c}{\omega} \frac{(\nabla \times B_o)_{||}}{B_o}(\vec{B}_1 - B_{||} \hat{e}_{||}), \quad (3.13)$$

where:

$$S = 1 + \sum_i \frac{(\frac{\omega_{pi}}{\omega_{ci}})^2}{(1 - (\frac{\omega}{\omega_{ci}})^2)} = 1 + \frac{c^2}{V_A^2} \sum_i \frac{f_i}{1 - (\frac{\omega}{\omega_{ci}})^2}, \quad (3.14)$$

$$D = -\sum_i \frac{(\frac{\omega_{pi}}{\omega_{ci}})^2 \frac{\omega}{\omega_{ci}}}{(1 - (\frac{\omega}{\omega_{ci}})^2)} = -\frac{c^2}{V_A^2} \sum_i \frac{f_i \frac{\omega}{\omega_{ci}}}{1 - (\frac{\omega}{\omega_{ci}})^2}. \quad (3.15)$$

In the above equations, we have introduced the mass fraction ($f_i(r) = \frac{n_{io} m_i}{\sum_i n_{io} m_i}$) and the Alfvén velocity ($V_A^2(r) = \frac{B_o^2}{4\pi \sum_i n_{io} m_i}$), both expressions depend only on the radial position. With the purpose of deriving the cold-plasma equations with a simple structure, we will work with magnetic coordinates which are suitable for systems with helical symmetry of the magnetic field (*see appendix B*). The Maxwell's equations can be written, through the dielectric tensor and harmonic disturbances, as

$$\nabla \times \vec{B}_1 = -\frac{i\omega}{c}(\vec{\epsilon} \cdot \vec{E}_1), \quad (3.16)$$

$$\nabla \times \vec{E}_1 = \frac{i\omega}{c}\vec{B}_1. \quad (3.17)$$

Relating the equations (3.16) and (3.17), we obtain the general equation for an electromagnetic wave

$$\nabla \times \nabla \times \vec{E}_1 = \frac{\omega^2}{c^2}(\vec{\epsilon} \cdot \vec{E}_1). \quad (3.18)$$

Now, using magnetic coordinates in both sides of equation (3.18) and recalling that $E_{1\parallel} = 0$ and the equation (3.13), together with the Maxwell's equation (3.17), we can write the nonzero components of $\nabla \times \nabla \times \vec{E}_1$ and $\frac{\omega^2}{c^2}(\vec{\epsilon} \cdot \vec{E}_1)$ to first order in $|\frac{B_{o\theta}}{B_{oz}}|$:

$$(\nabla \times \nabla \times \vec{E}_1)_r = (k_\perp^2 + k_\parallel^2)E_{1r} + \frac{ik_\perp}{r} \frac{\partial}{\partial r}(rE_{1\perp}) - ik_\parallel r \frac{\partial}{\partial r}\left(\frac{1}{r} \frac{B_{o\theta}}{B_{oz}}\right)E_{1\perp}, \quad (3.19)$$

$$(\nabla \times \nabla \times \vec{E}_1)_\perp = k_\parallel^2 E_{1\perp} - \frac{\partial}{\partial r}[-ik_\perp E_{1r} + \frac{1}{r} \frac{\partial}{\partial r}(rE_{1\perp})] + ik_\parallel r \frac{\partial}{\partial r}\left(\frac{1}{r} \frac{B_{o\theta}}{B_{oz}}\right)E_{1r}, \quad (3.20)$$

$$\frac{\omega^2}{c^2}(\vec{\epsilon} \cdot \vec{E}_1)_r = \frac{\omega^2}{c^2}(SE_{1r} - iDE_{1\perp}) - \frac{1}{r} \frac{\partial}{\partial r}\left(r \frac{B_{o\theta}}{B_{oz}}\right)ik_\parallel E_{1\perp}, \quad (3.21)$$

$$\frac{\omega^2}{c^2}(\vec{\epsilon} \cdot \vec{E}_1)_\perp = \frac{\omega^2}{c^2}(SE_{1\perp} - iDE_{1r}) + \frac{1}{r} \frac{\partial}{\partial r}\left(r \frac{B_{o\theta}}{B_{oz}}\right)ik_\parallel E_{1r}. \quad (3.22)$$

Using equation 3.17, we obtain from (3.18 - 3.22):

$$A \frac{1}{r} \frac{\partial}{\partial r}(rE_{1\perp}) = ik_\perp GE_{1\perp} + (A - k_\perp^2)i \frac{\omega}{c} B_{1\parallel}, \quad (3.23)$$

$$A \frac{\partial}{\partial r}\left(\frac{i\omega}{c} B_{1\parallel}\right) = (G^2 - A^2)E_{1\perp} - k_\perp Gi \frac{\omega}{c} B_{1\parallel}, \quad (3.24)$$

where:

$$A = \frac{\omega^2}{c^2}S - k_\parallel^2 = \frac{\omega^2}{c^2} + \frac{\omega^2}{V_A^2} \sum_i \frac{f_i}{1 - \frac{\omega^2}{\omega_{ci}^2}} - k_\parallel^2, \quad (3.25)$$

$$G = -\frac{\omega^2}{c^2}D - \frac{2k_\parallel}{r} \frac{B_{o\theta}}{B_{oz}} = \frac{\omega^2}{V_A^2} \sum_i \frac{f_i \frac{\omega}{\omega_{ci}}}{1 - \frac{\omega^2}{\omega_{ci}^2}} - \frac{2k_\parallel}{r} \frac{B_{o\theta}}{B_{oz}}. \quad (3.26)$$

Equations 3.23 and 3.24 are the so-called Appert equations, which we shall use for the discussion of Alfvén wave excitation [67]. It is important to note that the term $\frac{\omega^2}{c^2}$, in the expression for A , is neglected because $c \gg V_A$. When $A = 0$, we obtain the dispersion

relation for Alfvén waves ($\omega^2 = k_{\parallel}^2 V_A^2 (1 - \frac{\omega^2}{\omega_{ci}^2})$). We note also that $A = 0$ represents a singularity in the system of equations; we shall discuss this later on. When $G = 0$ the equilibrium current term ($\propto V_o$) is neglected.

For the purpose of simplifying the system, we will consider only one ion species, that is, consider $f_i = 1$ in the expressions for A and G in the limit $c \gg V_A$. The singular points of equations 3.23 and 3.24 are given by $A = 0$ and $r = 0$. As mentioned above, the singular point at $A(r) = 0$ gives the dispersion relation of Alfvén waves and defines a resonant surface where the solution of the wave equation is singular. The singular surface at $r = 0$ defines the regularity conditions that the proper eigenfunctions have to satisfy. If we exclude the cases $A(r \rightarrow 0) = 0$ and $G(r \rightarrow 0) = 0$, we can consider $k_{\perp} \sim \frac{m}{r}$ (see appendix B) and $k_{\parallel}$ finite, where m is the poloidal wave number. Then, it follows that, to first order in a series expansion in powers of r , the coefficients in equations 3.23 and 3.24 are given by $A = a_o$ and $G = g_o$. Then, by using the Frobenius method, we have that, as $r \rightarrow 0$ equations 3.23 and 3.24 impose that $rE_{\perp} = \varepsilon r^{\alpha}$ and $(i\frac{\omega}{c})B_{\parallel} = \beta r^{\alpha}$, and

$$(mg_o - \alpha a_o)e_o - m^2 b_o = 0, \quad (3.27)$$

$$(g_o^2 - a_o^2)e_o - (mg_o + \alpha a_o)b_o = 0. \quad (3.28)$$

The homogeneous system has a nontrivial solution, when the determinant vanishes, for e_o and b_o , that is, $\alpha^2 = m^2 \Rightarrow \alpha = \pm m$. We take the regular solution $rE_{\perp} = \varepsilon r^{|m|}$ and $(i\frac{\omega}{c})B_{\parallel} = \beta r^{|m|}$ and obtain the regularity condition

$$\varepsilon(r=0) = \frac{m^2}{mg_o - |m|a_o} \beta(r=0). \quad (3.29)$$

These results will be used when we define the boundary conditions later on.

3.2 Wave equation

Let us consider a plasma column of radius r_p surrounded by an antenna of vanishingly small thickness, at radius r_a , located in the vacuum region, and a perfectly conducting outer shell or a metallic conducting wall at radius r_s (figure 3.1).

Figure 3.1: Plasma-antenna-wall configuration in cylindrical geometry

To specify the Alfvén wave excitation problem we need, apart from the wave equation system in the plasma, the wave equation in the vacuum where the sheet antenna can be treated as a discontinuity of the perturbed magnetic field in the vacuum. To obtain the expression of the wave equation, we consider the following equations

$$\nabla \times \vec{B}_1 = \left(\frac{4\pi}{c}\right) \vec{J}_{ant} \quad (3.30)$$

and

$$\nabla \cdot \vec{B}_1 = 0. \quad (3.31)$$

The antenna current density $\vec{J}_{ant}$ must have the form $\vec{J}_{ant} = \nabla \times \vec{b}$, where $\vec{b}$ is an arbitrary vector (current potential), so that it automatically satisfies $\nabla \cdot \vec{J}_{ant} = 0$ [67]. Hence, the antenna current density is assumed to be the form

$$j_r = -is \frac{km}{r} \Theta(r - r_a) \Gamma_o \exp(i(m\theta + kz - \omega t)), \quad (3.32)$$

$$j_\theta = k\delta(r - r_a) \Gamma_o \exp(i(m\theta + kz - \omega t)), \quad (3.33)$$

and

$$j_z = -i(1 - s) \frac{m}{r} \delta(r - r_a) \Gamma_o \exp(i(m\theta + kz - \omega t)), \quad (3.34)$$

where Γ_o and s ($0 \leq s \leq 1$) are real constants. The value of the constant s will define the type of antenna that we will work with [70]; for $s = 0$ the antenna is a helical antenna

without feeders of radial currents, whereas if $s = 1$ the antenna only has poloidal currents in the sheet and these are fed by radial currents (figure 3.2).

Figure 3.2: (a) Helical antenna and (b) Poloidal antenna with radial feeders [67].

Considering that for region II (figure 3.1) does not exist a current density contribution by the antenna, while in region III we have a current density contribution by the antenna being purely radial, from the equation 3.30 we have:

$$\nabla \times \vec{B}_1 = 0 \quad r_p < r < r_a, \quad (3.35)$$

$$\nabla \times \vec{B}_1 = \left(\frac{4\pi}{c}\right) j_r \vec{e}_r \quad r_a < r < r_s. \quad (3.36)$$

Assuming that the perturbed quantities vary as $e^{i(m\theta + kz - \omega t)}$ and using the equations 3.31, 3.35 and 3.36 in cylindrical coordinates and the radial component of the antenna current density, equation 3.32, we obtain the vacuum wave equation (z-component of the vacuum wave equation):

$$\frac{1}{r} \frac{d}{dr} r \frac{dB_{1z}}{dr} - \left(k^2 + \frac{m^2}{r^2}\right) B_{1z} = 0 \quad r_p < r < r_a, \quad (3.37)$$

$$\frac{1}{r} \frac{d}{dr} r \frac{dB_{1z}}{dr} - \left(k^2 + \frac{m^2}{r^2}\right) B_{1z} = \frac{4\pi}{c} \frac{m^2}{r^2} s k \Theta(r - r_a) \beta_o \exp(i(m\theta + kz - \omega t)) \quad r_a < r < r_s, \quad (3.38)$$

and using the r and θ -components of equations 3.35 and 3.36, with $k = k_z$, we can calculate $B_{1\theta}$ and B_{1r} respectively:

$$\left. \begin{aligned} B_{1\theta} &= \frac{m}{k_z r} B_{1z} \\ B_{1r} &= -\frac{i}{k_z} \frac{dB_{1z}}{dr} \end{aligned} \right\} \quad for \quad r_p < r < r_a, \quad (3.39)$$

$$\left. \begin{aligned} B_{1\theta} &= \frac{m}{k_z r} B_{1z} + \frac{i}{k_z} \frac{4\pi}{c} j_r \\ B_{1r} &= -\frac{i}{k_z} \frac{dB_{1z}}{dr} \end{aligned} \right\} \quad \text{for } r_a < r < r_s. \quad (3.40)$$

Equations 3.37 and 3.38 are known as the homogeneous and inhomogeneous Bessel equation with pure imaginary argument respectively, and their general solutions, as shown in [24, 71–73], are given by:

$$B_{1z}(r) = C_1 I_m(k_z r) + C_2 K_m(k_z r) \quad r_p < r < r_a, \quad (3.41)$$

$$\frac{dB_{1z}(r)}{dr} = C_1 I'_m(k_z r) + C_2 K'_m(k_z r) \quad r_p < r < r_a, \quad (3.42)$$

$$\begin{aligned} B_{1z}(r) &= D_1 I_m(k_z r) + D_2 K_m(k_z r) - \vartheta \left(I_m(k_z r) \int_r^{r_w} dr' \frac{K_m(k_z r')}{r'} - \right. \\ &\quad \left. K_m(k_z r) \int_{r_a}^r dr' \frac{I_m(k_z r')}{r'} \right) \quad r_a < r < r_s, \end{aligned} \quad (3.43)$$

$$\begin{aligned} \frac{dB_{1z}(r)}{dr} &= D_1 I'_m(k_z r) + D_2 K'_m(k_z r) - \vartheta \left(I_m(k_z r) \int_r^{r_w} dr' \frac{K_m(k_z r')}{r'} - \right. \\ &\quad \left. K_m(k_z r) \int_{r_a}^r dr' \frac{I_m(k_z r')}{r'} \right)' \quad r_a < r < r_s, \end{aligned} \quad (3.44)$$

where, I_m and K_m are the modified Bessel function of the first kind and second kind respectively. The integrals in the equations 3.43 and 3.44, are:

$$\begin{aligned} \int dr' \frac{K_m(k_z r')}{r'} &= 2^{-m-2} \pi (k_z r')^{-m} \csc(m\pi) \left(4^m \Gamma\left(-\frac{m}{2}\right) {}_1\tilde{F}_2\left(-\frac{m}{2}; 1-m, 1-\frac{m}{2}; \frac{(k_z r')^2}{4}\right) - \right. \\ &\quad \left. (k_z r')^{2m} \Gamma\left(\frac{m}{2}\right) {}_1\tilde{F}_2\left(\frac{m}{2}; m+1, \frac{m}{2}+1; \frac{(k_z r')^2}{4}\right) \right), \end{aligned} \quad (3.45)$$

$$\int dr' \frac{I_m(k_z r')}{r'} = 2^{-m-1} (k_z r')^m \Gamma\left(\frac{m}{2}\right) {}_1\tilde{F}_2\left(\frac{m}{2}; m+1, \frac{m}{2}+1; \frac{(k_z r')^2}{4}\right). \quad (3.46)$$

Here, the functions Γ and ${}_1\tilde{F}_2$ represent the gamma function and one the generalized hypergeometric function, respectively, and are defined by [74]

$$\Gamma(z) = \int_0^\infty t^{z-1} e^{-t} dt, \quad (3.47)$$

$${}_1\tilde{F}_2 \left(\begin{matrix} \alpha_1 \\ \rho_1 \quad \rho_2 \end{matrix} \middle| z \right) = \sum_{k=0}^{\infty} \frac{(\alpha_1)_k}{(\rho_1)_k (\rho_2)_k} \frac{z^k}{k!} \quad (|z| < \infty), \quad (3.48)$$

where $(\alpha_k) = \Gamma(\alpha + k)/\Gamma(\alpha)$ is the Pochhammer symbol.

3.3 Boundary conditions and power emitted by the antenna

The proper solutions of the plasma-vacuum wave equations have to satisfy boundary conditions at the interfaces between different regions. Given an arbitrary value for $\beta(r = 0)$, in the equation 3.29, we can calculate, by integration of the system of equations 3.23 and 3.24, the values of $B_{1\parallel}$ and $E_{1\perp}$ inside the plasma. Therefore, we can also know the fields $B_{1\theta}$, B_{1z} , $B_{1\perp}$, $E_{1\theta}$ and E_{1z} in the plasma column.

At the plasma-vacuum interface ($r = r_p$), we require the fields be continuous. Using the expressions for $k_{\parallel}$ and $\hat{e}_{\parallel}$ shown in appendix B, we have

$$B_{1\parallel}^I = B_{1\parallel}^{II} = \vec{B}_1^{II} \cdot \frac{\vec{B}_o}{|\vec{B}_o|} = \frac{k_{\parallel}}{k_z} B_{1z}^{II}, \quad (3.49)$$

while using the r-component of equations 3.17 and 3.39, we obtain

$$E_{1\perp}^I = \frac{i\omega}{ck_z k_{\parallel}} \frac{dB_{1z}^{II}}{dr}. \quad (3.50)$$

At the antenna, $r = r_a$, the surface current imposes that [75]:

$$\hat{e}_r \times [\vec{B}_1^{III} - \vec{B}_1^{II}] = \frac{4\pi}{c} \vec{J}_{ant}, \quad (3.51)$$

$$\hat{e}_r \cdot [\vec{B}_1^{III} - \vec{B}_1^{II}] = 0, \quad (3.52)$$

using the relation between B_{1r} and $\frac{dB_{1z}}{dr}$ in the wave equation, together with the above two equations, we obtain three boundary conditions:

$$B_{1z}^{II} - B_{1z}^{III} = \frac{4\pi}{c} J_{\theta}, \quad (3.53)$$

$$B_{1\theta}^{III} - B_{1\theta}^{II} = \frac{4\pi}{c} J_z, \quad (3.54)$$

$$\frac{dB_{1z}^{II}}{dr} - \frac{dB_{1z}^{III}}{dr} = 0. \quad (3.55)$$

Another important equation, which must be satisfied by the components of the current in the antenna, is $\nabla \cdot \vec{J} = 0$ [73].

On the conducting shell with infinite conductivity, $r = r_s$, it is imposed that the magnetic field normal to the wall B_{1r}^{III} must be zero

$$\frac{dB_{1z}^{III}}{dr} = 0, \quad (3.56)$$

while, B_{1z}^{III} is an arbitrary constant on the wall. We note that the conditions 3.53 - 3.56 allow the determination of the arbitrary constant β in 3.29

Knowing the fields in the three regions shown in figure 3.1, we can calculate the total complex power delivered by the antenna inside the vacuum domain V [76]:

$$P_{ant} = \frac{1}{2} \int_V \vec{J} \cdot \vec{E}^* dV. \quad (3.57)$$

The total complex power delivered by the antenna is transmitted through the plasma-vacuum region, and can be expressed as:

$$P_{plas} = \frac{1}{2} \int_{\partial\Omega} E_{\perp}^* B_{\parallel} d\sigma. \quad (3.58)$$

3.4 Continuum and global Alfvén waves

As we discussed above, in the ideal MHD limit with cylindrical symmetry, the eigenmode equations 3.23 and 3.24, for low frequency (frequencies below the ion cyclotron frequency), MHD waves in a plasma, described within the fluid model, presents a singularity at the Alfvén frequency $\omega_A = k_{\parallel} V_A$, here $k_{\parallel}$ is the wave vector parallel to the magnetic field, and $V_A = \frac{B}{(\mu_0 m_i n)^{\frac{1}{2}}}$ is the Alfvén velocity [53]. Because the plasma density n is usually maximum at the plasma axis and minimum at the plasma edge, with a continuous variation, the condition $A = 0$ determines a continuum frequencies with singular modes strongly damped, [77–80], given by

$$\min[\omega_A^2(r)] \leq \omega^2 \leq \max[\omega_A^2(r)], \quad (3.59)$$

where, when finite ω/ω_{ci} effects are taken into consideration, a resonance surface appears when the dispersion relation (Alfvén wave resonance) is given by

$$\omega_A(r) = \left| \frac{k_{\parallel}(r) V_A(r)}{[1 + (\frac{k_{\parallel}(r) V_A(r)}{\omega_{ci}})^2]^{1/2}} \right|. \quad (3.60)$$

Here, since the frequency is a function of the radius, the excited waves form a continuous spectrum from a minimum value that can be on or off axis to a maximum value at the plasma edge. The parallel wave vector is given by

$$k_{||}(r) = \left(\frac{n}{R}\right) \left[\frac{m}{qn} + 1 \right] \frac{B_z}{B_{total}}, \quad (3.61)$$

where n is the toroidal mode number, (Rk_z) , and m is the poloidal mode number, (rk_θ) , and the profile safety factor $q(r)$ is given by a function

$$q(r) = \frac{rB_{tor}}{RB_{pol}}. \quad (3.62)$$

This function depends on the radial coordinate and the proper value at the edge of the plasma column.

The ion gyrofrequency ω_{ci} is given by the expression [81]:

$$\omega_{ci} = 9.58 \times 10^3 Z \mu^{-1} B_{tor} rad/sec, \quad (3.63)$$

where Z is charge state and equals 1 for hydrogen and 2 for deuterium, $\mu = m_i/m_p$ is the effective ion mass expressed in units of the proton mass. For our calculations we will take the values of $\mu > 1$ for the TCABR tokamak, i.e. operates with hydrogen, and $\mu > 2$ to JET tokamak, i.e. operates with deuterium.

The expression for the Alfvén velocity is [81]:

$$V_A = 2.18 \times 10^{11} \mu^{-1/2} n_i^{-1/2} B_{tor} cm/sec. \quad (3.64)$$

We note that the parallel wave vector depends on the values m , n , R and q , representing the azimuthal or poloidal wave number, the toroidal wave number, the major radius and the safety factor, respectively, whose values will be discussed later.

Experimental and theoretical results obtained on the base of the MHD approach to Alfvén waves, developed by the theory group of Lausanne, Switzerland, especially the work [66], show evidence of resonance peaks at frequencies just below the lower edge of the Alfvén continuum, due to the plasma equilibrium current gradient and which can be related to the excitation of new class of weakly damped modes of the Alfvén wave, the so-called global modes or global Alfvén waves (GAWs). Numerical and theoretical studies using kinetic description of the Alfvén waves modes, i.e. when nonideal effects such as finite Larmor radius and electron Landau damping are considered, were also performed showing the existence of the GAWs called the kinetic Alfvén wave (KAW) [48, 82].

In analytical studies of the (GAWs) using the WKB approximation [59, 66, 79], it was concluded that the edge of the continuum is an accumulation point of a discrete spectrum and the existence of GAWs with frequency values ω below the lower edge of the continuum is related to the behavior of the solution of the MHD eigenvalue equation 3.23 and 3.24 around the minimum value of the frequency in the Alfvén continuum, i.e. $\omega^2 = \min[\omega_A^2(r)]$.

In cylindrical plasma columns, the GAWs excited below the continuum are the only possibility for solutions of the wave equations with proper eigenfunctions. The GAW has a global wave structure which extends over most of the plasma radius, and is only slightly damped and thus can be easily destabilized by alpha particles. This destabilization of the GAWs are strongly related to the intensity of radial field profiles inside the plasma column and to the radial displacement of the modes at the plasma surface [66]. However, the GAWs modes can be readily stabilized when toroidicity effects are taken into account [18]. On the other hand, as we will see in the chapter 5, the periodicity in toroidal geometry introduces gaps in the Alfvén continuum, similarly to the band structure introduced by periodicity in solids [83]. Inside these gaps it is possible to excite proper global modes, which are called Toroidal Alfvén Eigenmodes (TAEs) [84]. Therefore, the study of (GAWs) in cylindrical geometry is relevant as preamble for the investigation of TAEs.

Chapter 4

Excitation of Alfvén waves by an external antenna system

The continuous nature of the excitable spectrum yields the well-known property of resonance absorption in which the strength of the coupling to the wave is independent of both the nature and the strength of the subsequent damping mechanisms. It is precisely this property that allows the antenna-plasma coupling, measured by the antenna loading, to be calculated accurately in the MHD limit [85]. Because of this, one method used to excite the resonance is to drive the wave field of the Alfvén waves from outside the plasma column, which requires external antennas parallel to the static magnetic field. The main idea is to excite a compressional wave of specified toroidal and poloidal wavelengths, often referred to as the driven surface wave, which will then couple to the Alfvén wave resonance inside the plasma column.

Although efficient antenna-plasma coupling was investigated, an unexpected problem of uncontrolled density rise, observed in high-power RF experiments, was not solved [86]. We remark that the excitement produced by an antenna depends, primarily, on the form of temporal variation of the excitation, the geometry of the antenna, and the physical environment in which the antenna is inserted. Furthermore, by determining the width of absorbed spectrum around a resonance, it is possible to determine its damping coefficient.

An antenna system that excites a large number of harmonics with different m , n numbers usually delivers RF power simultaneously both in the central and peripheral parts

of the plasma column. That is why an antenna system that launches waves with double helicity, $\pm m, \pm n$, is incapable of avoiding the RF power deposition close to plasma surface. Experimental [87] and numerical [82] results concerning the antenna loading for Alfvén wave heating of tokamak plasmas show evidence of resonance peaks at frequencies just below the lower edge of the Alfvén continuum, i.e. GAWs, which are global eigenmodes of the Alfvén waves. The GAWs are low-frequency waves and its separation from and beneath the lower edge is a function of the density profile, the q-profile, m and n , and the value of ω/ω_{ci} [66,88]. The use of GAWs as a plasma diagnostic is very useful and, because of this, the analysis of global Alfvén waves is important. On the other hand, TAEs can also be excited by an external antenna system and the determination of the width of the resonance as the antenna frequency is swept allows an estimative of the damping rate. This scheme has been successfully carried out in JET [89,90].

In order to continue our study of GAWs and subsequently of TAEs, now we shall discuss briefly the main characteristics of the TCABR and JET tokamaks. We will focus on the antenna systems for both.

4.0.1 TCABR tokamak

The TCABR tokamak, which is in operation at the Institute of Physics of the University of São Paulo, was transferred, at the middle of the 1990's, from the Centre de Recherches en Physique des Plasmas (CRPP), Lausanne where it was called TCA (Tokamak Chauffage Alfvén) due to Alfvén wave heating [70,91,92] being its main scientific objective (see figure 4.1). Its Alfvén excitation and control data acquisition systems were substantially modified, and it started operation in 1999, being renamed TCABR, for "*Tokamak Chauffage Alfvén Brésilien*".

TCABR is a small circular cross-section tokamak, which has advantages because it can be used for staff training and it is simpler to make new tests or install new equipments, than larger tokamaks. TCABR has many plasma diagnostic systems, in particular, electron cyclotron emission and Thompson scattering for electron temperature measurements. The density is measured by an interferometer, which gives the line integral along three lines of sight, and by the Thompson scattering system, which can give the local

value of the density and electron temperature at center of the plasma column, but only in one instant of the discharge. Other diagnostic systems are: emission measurements of soft X-ray, optical measurements of spectral lines, Mirnov coils, electrostatic probes and magnetic probes to measure the field excited by the antenna system.

Figure 4.1: Medium-sized tokamak TCABR, for confinement of high temperature plasmas.

The experiments on Alfvén wave heating, Alfvén wave excitation, and current drive, initiated at CRPP, have been continued in TCABR, with new advanced RF system [25, 27, 93]. To that end, the actual antenna system used in the TCABR tokamak consists of two similar units, separated toroidally by 180 degrees. Each unit has one pair of top and bottom modules, which are composed by two poloidal quarter turns each one, as shown in figures 4.2 and 4.3.

Figure 4.2: (a) Scheme of the one poloidal quarter turn of the TCABR antenna. (b) Photography of one antenna module in the test bench.

Figure 4.3: Poloidal cross-section showing the location of the two poloidal quarter turns.

The antenna system is poloidal with radial feeders ($s = 1$). Each pair is separated 20 degrees in the toroidal direction. The positioning of one antenna sector in the vacuum chamber is shown in figure 4.4.

Figure 4.4: Schematic drawing of an antenna poloidal sector; top view.

The polished stainless steel vacuum vessel has a rectangular cross section, with additional space at the top and bottom to accommodate the antenna loops. However, this rectangular cross section can be modelled as having a circular cross section without affecting substantially the numerical results [27].

In the TCABR tokamak only GAWs will be analyzed. For this purpose, since the range of wave numbers of interest for TCABR, in the experiments, is $-3 \leq m \leq 3$; $-3 \leq n \leq 3$, the antenna modules can be fed with proper phasing to excite waves with toroidal and poloidal mode numbers $n = \pm 1, \pm 2, \pm 3$ and $m = \pm 1, \pm 2, \pm 3$. The parameters to simulate the TCABR tokamak were chosen for RF excitation modeling, considering the experimental parameters of Paulo Puglia doctoral thesis, to be submitted [94]: $R = 61$ cm (radius major), $r_p = 18$ cm (plasma radius), $r_a = 19.9$ cm (antenna radius), $r_s = 27.7$ cm (wall radius). The experiments were carried at fixed value of the toroidal magnetic field, $B_{tor} = 1.07$ T.

Taking into account a detailed analysis of the density profile previously carried out for TCABR discharges, we take $n(x) = n_o(1 - x^2)^{0.8}$, where $x = r/r_p$, and n_o is the density at the center of the plasma column. The safety factor profile dependence on the radial coordinate is taken in the form $q(x) = q_a / ((q_a/q_0) - A(x^2 - x^4) + (1 - (q_a/q_0))x^6)$, where the

constant A vary according to the value of plasma current and ensures the concavity the safety factor profile, q_0 is the value the safety factor at the center of the plasma column, assumed a fixed value equal to 1, and hydrogen the filling gas.

4.0.2 JET tokamak

In 1978, the European Community (Euratom, along with Sweden and Switzerland) launched the Joint European Torus (JET) project in the United Kingdom. The JET is the largest tokamak operating in the world today [95]. A similar tokamak, JT-60, operates at the Naka Fusion Institute of Japan Atomic Energy Agency in Japan [96], but only JET has the facilities to use D-T fuel. The JET produced its first plasma in 1983, and became the first experiment to produce controlled fusion power in November 1991. Up to 16 MW of fusion power for one second and 5 MW sustained average power have been achieved in D-T plasmas using the device. JET has been very successful in operating remote handling techniques in a radioactive environment to modify the interior of the device and has shown that the remote handling maintenance of fusion devices is realistic.

The JET has tested several antenna systems for ion cyclotron resonance heating - ICRH. In 2000, a specific Enhancement Project was started at JET in order to test a prototype for ITER, the ITER-like Antenna. However, the antennae developed for ICRH are not suitable to excite TAEs, which are of much lower frequency than the ion-cyclotron waves. In fact, the first experiments to excite these modes in JET employed external saddle coils that were used for control of MHD modes [37]. Although these coils allowed a preliminary investigation of TAEs in JET, the excited spectra were too broad for obtaining detailed informations about an specific mode. Therefore, a new antenna system was designed by the "*Centre de Recherches en Physique des Plasmas*", from Lausanne, and installed in JET during the 2004-2005 shutdown [97]. It consists of two modules, separated toroidally, each module with four excitation coils with eighteen loops extended along the toroidal and poloidal directions, as indicated in figures 4.5, 4.6, and 4.7.

Figure 4.5: (a) Module formed by 4 antennas, each consisting of 18 coils [86]. (b) Real image of one assembly of 4 antennas system as installed on the wall of the JET vessel [39].

The excitation coils are installed inside the vacuum vessel, on the low field side wall below the $z = 0$ midplane of JET. They are divided into two groups of four modules located at toroidally opposite positions. Figure 4.5 shows a view of the designed antenna layout and one group of four antennas as installed in the vessel.

In the numerical model, each coil is represented as a single loop located, at the "antenna surface" $r = r_a$, of dimensions l_y (poloidal direction) and l_z (toroidal direction), as shown schematically in figure 4.6. The direction of current flow can be chosen independently in each loop. Further specification of the antenna system can be found in [86, 98].

Figure 4.6: Rectangular conductor with current flow.

The full antenna arrangement is then adapted to a cylindrical plasma column, as indicated figure 4.7.

Figure 4.7: Position of the antenna modules in the cylindrical model.

For analysis of GAWs, we consider a density profile $n(x) = 1.93 + 0.291x^2 - 16.2x^3 + 34.7x^4 - 20.8x^5$, where $x = r/r_p$, and $n_{eo} = 1.93 \times 10^{19} \text{ m}^{-3}$ is the density of particles in the center of the plasma column. The dependence of the safety factor on the radial coordinates is taken of the form $q(x) = 1.0 + 5.59x^2 - 14.03x^3 + 12.22x^4$, where the safety factor value at the edge of the plasma column is $q_a = 4.78$ and the safety factor value in the center of the plasma column is $q_o = 1$. The density and safety factor profiles were taken from [99] by interpolating the respective profiles used in the JET discharge #77788 at the time $t_0 = 4.985$ seconds, as it is shown in [86]

In a first investigation, the computations were carried out only for the range of interest for JET, i.e. an antenna structure phased to excite waves with range of toroidal and poloidal mode numbers ($-9 \leq m \leq 9, -3 \leq n \leq 3$). The parameters used to simulate the JET tokamak were chosen for RF excitation modeling: $R = 296 \text{ cm}$ (radius major), $r_p = 125 \text{ cm}$ (plasma radius), $r_a = 130 \text{ cm}$ (antenna radius), $r_s = 135 \text{ cm}$ (wall radius). The discharge parameters are $B_{tor} = 3.45 \text{ T}$ (toroidal magnetic field), the safety factor value at the boundary to the cylindrical approximation is $q_a = 4.78$, where the plasma current in the JET is $I_p = 1.9 \text{ MA}$ [100] and deuterium as the filling gas.

For analysis of TAEs, we will work with the HELENA and CASTOR codes. The

CASTOR code was modified for the new external JET antenna. The code uses the reconstruction of equilibrium profiles of the JET discharges given by HELENA code, i.e. plasma shape, pressure, current density and safety factor profiles, to calculate the radial profiles of the linear perturbations related to the resonance frequency of the antenna. For this purpose, CASTOR used the actual geometry of JET wall and the geometry of new JET antenna; more details will be presented in Chapters 6 and 7.

As already mentioned, the new antenna system used in JET has been recently upgraded to allow a reasonably pure spectrum of excited modes. The antenna system represents an inductive load, which is fed by a coaxial line around 100 m long, and no matching circuit can be installed close to the antenna to follow the varying plasma load. Due to these stringent conditions, commercial available sweeping RF generators, normally designed for 50 Ohm resistive loads, are not appropriate. A new RF amplifier that can work properly in these conditions has been designed by the Plasma Physics Laboratory of University of São Paulo, as part of an international collaboration involving the Plasma Fusion Center, of the Massachusetts Institute of Technology, and the Centre de Recherches en Physique des Plasmas, of École Polytechnique Fédérale de Lausanne. The amplifier was built in collaboration with POLITRON, a Brazilian industry specialized in RF equipment, and its first unit has been successfully tested in JET last June of 2014.

The analysis of TAEs will be focused on procuring the best phases of the currents in the antenna. This will give an idea of the phases in which the new RF amplifier should work to drive a specific toroidal mode.

Chapter 5

Global Alfvén waves results

In this chapter we describe the computational model and the main results of numerical simulations for excitation of global Alfvén waves (GAWs) in two systems, i.e. TCABR and JET tokamaks. Firstly we present the general computational model, then discuss the computational antenna model and, finally, we analyze the main parameters numerically for the case of the TCABR tokamak and its antenna system modules to subsequently analyze the JET tokamak using the new geometry of the antennas loops, described in [39, 86, 98].

The main aim was the development of a numerical model of RF power deposition into the plasma column of TCABR and the JET tokamaks, to test the performance of the their antenna system modules, by means of GAWs excitation. We also discuss the existence of global modes outside the continuum for different mode numbers m and n and different frequencies and densities values for both tokamak systems and analyze the profile of the excited magnetic fields. Finally, we present and analyze the numerical results obtained for global Alfvén waves (GAWs) in both tokamaks.

5.1 Computational model

Since we have a modular and independently driven antenna structure, we can separately fix the phases of all antenna groups. Decomposing the resulting antenna structure yields its Fourier components, whose strengths are defined by the phasings and amplitudes of the antenna currents, and the shape of the antennas themselves, principally their width

and length. The computational model starts with a Fourier representation of the currents in the antenna [25], representing the antenna structure as a set of k poloidal elements "straps", with known positions (θ_k, z_k) , traversed by currents with different phases, as show in the scheme of the figure 5.1.

Figure 5.1: Scheme of one strap antenna current Fourier decomposition.

The current density of the k -th element is expanded as a sum of poloidal and toroidal harmonics, through a developoment in helical Fourier series.

$$j_k(\theta_k, z_k) = \sum_{m,n} j_{m,n}^k \exp i(m\theta + \frac{n}{R}z). \quad (5.1)$$

The amplitudes of the harmonics $j_{m,n}^k$ are given by [25]:

$$j_{m,n}^k = \frac{j_{ok}dL}{\pi^2 r_a R} \left(\frac{\sin \left(\frac{mL}{r_a} \right) \sin \left(\frac{nd}{R} \right)}{\left(\frac{mL}{r_a} \right) \left(\frac{nd}{R} \right)} \right) \exp -i(m\theta_k + \frac{n}{R}z_k). \quad (5.2)$$

where j_{ok} is the surface current density of the k -th element and $2d$ is the width of the element.

Therefore, the component of the total current density on the surface of the antenna ($r = r_a$) is obtained by summing the contributions of all the k -th elements,

$$J_{m,n} = \sum_k j_{m,n}^k = \frac{dL}{\pi^2 r_a R} \left(\frac{\sin\left(\frac{mL}{r_a}\right) \sin\left(\frac{nd}{R}\right)}{\left(\frac{mL}{r_a}\right) \left(\frac{nd}{R}\right)} \right) \sum_k j_{ok} \exp -i(m\theta_k + \frac{n}{R}z_k + \psi_k), \quad (5.3)$$

where ψ_k is the current phase of the k -th element.

For the calculations, we consider a cylindrical plasma with radius r_p in MHD equilibrium, with density profile $n(r) = n_o t(r)$, where $t(r)$ is a function dependent on the radial coordinate, and n_o is the density of particles at the center of the plasma column. As it was said above, we consider the safety factor $q(x) = q_a f(r)$ dependent on the radial coordinates, where q_a is the value at the edge of the plasma column and is given by the expression [1]:

$$q_a = \frac{r_p B_{tor}}{R B_{pol}} = \frac{2\pi r_p^2 B_{tor}}{\mu_0 R I_p}, \quad (5.4)$$

where $B_{pol} = \frac{\mu_0 I_p}{2\pi r_p}$ is the poloidal magnetic field in the boundary and the plasma current (circular plasma). We recall that the stability of plasma requires that the minimum value of the factor at the edge is $q_a^{min} > 2 - 3$ and the maximum plasma current in a tokamak is determined by

$$I_{max} = \frac{2\pi r_p^2 B_{tor}}{\mu_0 R q(a)_{min}}. \quad (5.5)$$

The electromagnetic fields in the plasma obey the equations presented in section 3.1 of this thesis, while in the region between the plasma and the antenna, as in the region between the antenna and the wall, will satisfy the Helmholtz equation for the magnetic field (as was shown in section 3.2). By using the density profiles and the safety factor, we solve the system of equations numerically, obtaining general solutions with arbitrary coefficients for the fields in the three regions considered of the system (plasma, vacuum-antenna and vacuum-wall). These constants are fixed by boundary conditions at the plasma-vacuum interface and the chamber wall, and by jump conditions at the antenna surface [75].

To calculate the profiles of the components B_r and B_z of the magnetic field for the externally excited Alfvén waves, we assume in the cylindrical model that the plasma column of radius r_p is surrounded by vacuum and by an ideally conducting shell with

radius r_s . Furthermore we assume a sheath antenna with radius r_a , situated in the vacuum region, i.e. $r_p < r_a < r_s$.

In summary, the numerical procedure is to obtain the amplitudes of the electromagnetic fields generated by each harmonic of the total current individually, to then add the magnitudes of all Fourier components of the field in the entire space inside the cylindrical chamber. Knowing each spectral component excited in plasma, we can calculate the total power supplied by the antenna on the boundary of the plasma in the process of excitation of the modes m and n . Therefore, a complex impedance for the plasma may be defined as the ratio between the total power supplied by the antenna in $(r = r_a)$ and a single coil current,

$$Z_p = \frac{2\bar{P}_{tot}}{I_{loop}^2} = \frac{2}{(2j_{ok}d)^2} \sum_{m,n} \bar{P}_{m,n}, \quad (5.6)$$

where the average power associated with each harmonic excited in the plasma, is given by

$$\bar{P}_{m,n} = -\frac{\pi r_a R c}{2} (E_{m,n} B_{m,n}^*)|_{r=r_a}. \quad (5.7)$$

5.2 Global Alfvén waves results in the TCABR

In this section we describe the main results of numerical simulations of excitation of GAWs using the theory described by Appert *et al.* in [67] and shown in chapter 3. For the numerical analysis of GAWs, we have started using an old numerical program created with the main goal of designing an RF system for Alfvén waves heating and current drive in TCABR tokamak [25, 40]. Improvements were made in the numerical program, in particular the modification of the geometry of the antenna array (present TCABR antenna), modified expressions of plasma-vacuum conditions, computational implementation of the effective mass, mode numbers, and field components profiles (magnetic and electric field) calculation.

Like its predecessor, the numerical calculations were performed with MATLAB; however in the new program the computation is semi-analytical and not completely numerical, what brought advantages in calculation time. The main aim was the development of a

numerical model of RF power deposition into the plasma column of TCABR tokamak, to test the performance of the antenna system modules. We discuss the existence of the GAWs outside the continuum for different mode numbers m and n and different frequencies, effective mass and densities values to the system and analyze the profile of the magnetic fields excitations.

In the experiments carried out by Puglia [94], only a single poloidal quarter module was employed to excite the waves. The excited wave fields were measured by two magnetic probes inside the vacuum vessel, located -45° , in the poloidal direction, and 90° in the toroidal direction, with respect to the exciting antenna sector, as indicated in Fig. 5.2.

Figure 5.2: Scheme of system for excitation and detection of Alfvén waves in TCABR [94].

With respect to equation 5.3, a k -th element of the antenna has parameters $2L = 99$ cm (antenna coil poloidal length), $2d = 4.4$ cm (antenna coil toroidal length - wire diameter). The same current value was considered for all k -th element, that is, $I_{ant} = 1.0$ A. The current phase in the antenna is taken of the form $\psi = (\frac{m_0 y}{r_a} + \frac{n_0 z}{R})$, exciting modes m_0 and n_0 of arbitrary choice.

Using the cylindrical approximation, the safety factor values at the boundary, for each discharge is calculated with equation 5.5. In figure 5.3, we show three different safety factor profiles, each one related to a specific value of plasma current.

Figure 5.3: Safety factor profiles. The coefficient multiplying x^2 and x^4 ensures the concavity the safety factor profile.

For the present analysis, we used the data obtained in the discharges # 28038 and # 28289 of the TCABR tokamak [94]. The experimental plasma parameters are obtained as function of time during the discharges. They are line density, soft x rays, bolometer, ECE, plasma current, loop voltage, position, magnetic oscillations, the phase difference and power spectrum of the signals measured by the probes magnetic, as function of the evolution of the line density for one fixed frequency. For our simulations, the most important data that we extract from the experimental results are the frequency, line density, and plasma current.

We show in table 5.1 the values of these parameters for two discharges in which GAWs were excited.

Discharge Number	Frequency	Plasma Current	Central Density
28038	2.86 MHz	83 kA	$2.74 \times 10^{19} m^{-3}$
		86 kA	$2.29 \times 10^{19} m^{-3}$
28289	3.11 MHz	88 kA	$1.82 \times 10^{19} m^{-3}$

Table 5.1: Table of experimental parameters for two discharges with excitation of GAWs in TCABR [94].

As shown in table 5.1, the values of the parameters of interest that were obtained experimentally for the each discharge in which GAWs were excited are the frequency generated by the antenna, the plasma current, and the line density [94]. In the experimental scheme, a fixed value of the frequency generated by the antenna is considered, as well as a parabolic density profile, i.e. $n(x) = n_o(1-x^2)^{0.8}$. From the point of view of our numerical scheme, for each discharge with a fixed value of the frequency, the plasma current and line density are the parameters of interest, and these three parameters are considered as input values in the numerical code. In the case of the discharge # 28038, two values of plasma current and central density are observed.

We note that the respective central density is calculated by multiplying the factor 1.4 to the line density used in each discharge, i.e. $1.957 \times 10^{19} m^{-3}$ and $1.635 \times 10^{19} m^{-3}$ for the discharge # 28038 and $n_{eo} = 1.3 \times 10^{19} m^{-3}$ for the discharge # 28289. The factor 1.4 is directly linked to the value of the exponent 0.8 in the parabolic density profile and is calculated from the line integral for such profile.

5.2.1 Numerical procedure to analyze the results for GAWs

As it was mentioned, the Alfvén wave resonance is given by equation 3.60, where the Alfvén wave resonance inside the plasma column is determined by the frequency of the

wave excited by the antenna modules, while, to obtain global modes, the frequency of the generator should be $f_{ant} \leq \frac{\min(\omega_A)}{2\pi}$.

Knowing the three experimental parameters of table 5.1, where the antenna frequency was fixe and the resonance was achieved due to density variation during the discharge, our main objective is to calculate the profiles of the excited wave magnetic fields. Therefore, the calculation of the effective mass M_i and the modes numbers poloidal m and toroidal n for which GAWs are experimentally obtained in TCABR, and which are the unknown parameters in the experiment, are important. In order to analyze the numerical results, we assume that the frequency values in table 5.1 represent the frequencies of excited GAWs. Therefore, it is required that these frequencies be outside the Alfvén continuum.

The frequency variation, i.e. the difference between the minimum frequencies of the continuum and the frequency generated by the TCABR antenna $\Delta f = f_{min} - f_{ant}$, for the three values of the plasma current, and for different values of effective mass and mode numbers m and n , is calculated. The range of values of the effective mass M_i is between 1.0 – 1.6. The choice of the value range of the effective mass is because they are the experimentally expected values [94].

The values of the effective mass M_i and of the modes m and n , related to the GAWs and to the values described in table 5.1, will be numerically calculated, in order to calculate the profiles of the waves magnetic fields exciteb at the antenna frequency.

Firstly, we analyze the discharge # 28038 with plasma current $I_p = 83$ kA. For this purpose the dependence on n of Δf for fixed m is shown in figures 5.4-5.6. We note that negative values of Δf represent the Alfvén continuum, i.e. $f_{min} < f_{ant}$, and the special case when $\Delta f \ll 1$ the antenna frequency is precisely the minimum of the continuum. Each of the twelve lines represents a value of the specific mass effective spaced from each other by 0.05 within the range $[1 - 1.6]$.

We are interested in the values of n for which the value of Δf is acceptably small, i.e. $0.01 \text{ MHz} < \Delta f < 0.2 \text{ MHz}$, which ensures that the analysis being conducted just below the lower edge of the Alfvén continuum region corresponds to the local Alfvén frequency provided by antenna.

Figure 5.4: $\Delta f \times n$ for fixed $m = 1$, for multiple values of the effective mass, referring to discharge # 28038 with $I_p = 83$ kA.

Figure 5.5: $\Delta f \times n$ for fixed $m = 2$, for multiple values of the effective mass, referring to discharge # 28038 with $I_p = 83$ kA.

Figure 5.6: $\Delta f \times n$ for fixed $m = 3$, for multiple values of the effective mass, referring to discharge # 28038 with $I_p = 83$ kA.

From figures 5.4-5.6 above, for values of m equal to 1, 2, and 3, it is observed that our essential condition, $0.01 \text{ MHz} < \Delta f < 0.2 \text{ MHz}$, is fulfilled only for values of n equal to 2, 1, and 1 respectively, for a given range of effective mass values. We note that the values of mode numbers $m = n = 0$ are not taken into account, since these values give indeterminate values for expressions 3.29 and 3.61; this fact not will occur in the case of toroidal geometry, as we will see in detail in chapter six.

The next step of our analysis is to calculate the effective mass values that represented the excited GAWs. For this purpose, knowing the values of three pairs of mode numbers $(m, n) = (1, 2), (2, 1), (3, 1)$, we can calculate the interval of effective mass values for which the essential condition, $0.01 \text{ MHz} < \Delta f < 0.2 \text{ MHz}$, is fulfilled. Therefore, we can shorten our initial range of values for the effective mass, which will be favorable to decrease the calculation time of the exact effective mass value.

The results obtained are shown in the figure 5.7, where the curves shown the dependence on the effective mass of Δf for fixed m and n .

Figure 5.7: $\Delta f \times$ effective mass for fixed modes numbers, and for discharge # 28038 with $I_p = 83$ kA.

From figure 5.7 above, we can get an idea of the range of effective mass values where is the exact effective mass value that represented the possible GAWs (inside of the shaded area), i.e. $(1, 2) \rightarrow 1.2 < M_i \leq 1.35$, $(2, 1) \rightarrow 0.9 < M_i \leq 1.05$, and $(3, 1) \rightarrow 1.4 < M_i \leq 1.6$, together with the frequency, plasma current, central density and modes numbers m and n values which are known.

Now, the results for the effective impedance for the GAWs excited in discharge # 28038, for the effective masses in the allowed ranges show in figure 5.7, are shown in figure 5.8. We can see that the exact values for the effective mass are represented by high intensity peaks of the real part of the impedance (active) value. These values are approximately 1.35, 1.05, and 1.61 for the pairs of modes numbers $(m, n) = (1, 2)$, $(2, 1)$, and $(3, 1)$ respectively.

Finally, in figures 5.9 and 5.10 are shown the structures of the profiles of corresponding magnetic field components $|B_r|$ and $|B_z|$, for GAWs, inside and outside of the plasma column. These structures correspond to the three pairs of modes numbers and effective mass obtained, which corresponds to the density, frequency, listed in table 5.1.

Figure 5.8: Possible GAWs represented by impedance peaks for three pairs of mode numbers, for discharge # 28038 with $I_p = 83$ kA. The ranges of variation of the effective mass correspond to the ones of figure 5.7

Figure 5.9: Radial profiles of magnetic field component $|B_r|$ for GAWs, discharge # 28038 with $I_p = 83$ kA, for three pairs of mode numbers.

Figure 5.10: Profile of magnetic field component $|B_z|$ for GAWs through the total radius, discharge # 28038 with $I_p = 83$ kA.

We note that the radial profiles for $|B_r|$, shown in figure 5.9, obey the analytical dependence $B_r \sim r^{m-1}$ close to the plasma center.

A similar numerical analysis was performed for the case in which the plasma current is $I_p = 86$ kA with the central density $n_{eo} = 2.29 \times 10^{19} \text{ m}^{-3}$, and for the same fixed frequency value generated by the antenna, i.e $f_{req} = 2.86$ MHz.

The results of the profiles of the magnetic field components $|B_r|$ and $|B_z|$ are presented in figures 5.11 and 5.12. We note that there were found three pairs of modes $(m, n) = (1, 2), (2, 1)$, and $(3, 1)$, as in the previous case, and with effective mass values equal to 1.58, 1.25, and 1.9, respectively. The radial profiles of the GAWs have a distribution similar to the previous case, with same fields strengths to cases when $(m, n) = (2, 1)$, and $(3, 1)$. However, the fields strengths are smaller when $(m, n) = (3, 1)$.

Figure 5.11: Radial profiles of magnetic field component $|B_r|$ for GAWs for, discharge # 28038 with $I_p = 86$ kA, and three pairs of mode numbers.

Figure 5.12: Profile of magnetic field component $|B_z|$ for GAWs through the total radius, discharge # 28038 with $I_p = 86$ kA.

Finally, a similar numerical analysis was performed for discharge # 28289 (see table 5.1) and there were found two pairs of modes $m = 1, n = 2$ and $m = 2, n = 1$ with effective mass values equal to 1.36 and 1.21, respectively. The results of the profiles of magnetic field components $|B_r|$ and $|B_z|$ inside and outside of the plasma column, i.e. through the total radius, for each pair of modes (m, n) are presented in the figures 5.13 and 5.14.

In conclusion, we used the experimental values of the frequency, plasma current, and central plasma density to calculate numerically the approximate modes numbers, effective mass and the respective profiles of magnetic field components. Using these results, we can have an overall picture on the excitation of the GAWs inside of plasma column. We show in table 5.2 with the results obtained for each of the discharges analyzed.

Figure 5.13: Radial field profiles of global modes for $m = 1$ and $n = 2$, for discharge # 28289, with $I_p = 88$ kA and $Mi \approx 1.36$.

Figure 5.14: Radial field profiles of global modes for $m = 2$ and $n = 1$, for discharge # 28289, with $I_p = 88$ kA and $Mi \approx 1.21$.

Discharge Number	Frequency	Plasma Current	Central Density	Modes Numbers	Effective Mass
28038	2.86 MHz	83 kA	$2.74 \times 10^{19} m^{-3}$	$m = 2 \quad n = 1$	1.05
				$m = 1 \quad n = 2$	1.35
				$m = 3 \quad n = 1$	1.61
		86 kA	$2.29 \times 10^{19} m^{-3}$	$m = 2 \quad n = 1$	1.25
				$m = 1 \quad n = 2$	1.58
				$m = 3 \quad n = 1$	1.9
28289	3.11 MHz	88 kA	$1.82 \times 10^{19} m^{-3}$	$m = 1 \quad n = 2$	1.36
				$m = 2 \quad n = 1$	1.21

Table 5.2: Table of results obtained from numerical simulation of discharges in TCABR with excitation of GAWs.

5.2.1.1 Global Alfvén waves results in the JET

In order to simulate the excitation of GAWs in the JET tokamak for the JET discharge #77788 at the time 4.985 seconds, we specify the following antenna parameters $l_y = 21$ cm (antenna coil poloidal length), $l_z = 23$ cm (antenna coil toroidal length), $2d = 0.4$ cm (wire diameter), $R = 296$ cm (radius major), $r_p = 125$ cm (plasma radius), $r_a = 130$ cm (antenna radius), $r_s = 135$ cm (wall radius). Using the cylindrical approximation, different current values were considered for all 8 rectangular loops (all Clockwise), the current value of each single rectangular loop in the two antenna modules are 1 A. The phases for one module are 0° and for the other module are 180° , (see figures 4.6 and 4.7).

The poloidal direction of the current is contained in the value of the current phase ψ_k ($\uparrow$ ($\psi_k = 0$) and $\downarrow$ ($\psi_k = \pi$)). We are not considering the effect of the radial feeders of the antenna. In this case, equations 3.53 and 3.54 are equivalent and it is not necessary to take into account the contribution of the toroidal component of the antenna current.

As discussed above, the global modes appear next to the minimum value of the continuous Alfvén waves spectrum, where the Alfvén resonance is given by the equation 3.60. This resonance is determined only by the frequency of the antennas modules (frequency generator $f_{ant} = \frac{\omega_{ant}}{2\pi}$). Therefore, to obtain resonance (continuous Alfvén waves spectrum), the generator frequency should be $f_{ant} = \frac{\omega_A}{2\pi}$, while, to obtain global modes it should be $f_{ant} \leq \frac{\min(\omega_A)}{2\pi}$.

Thus, the results are shown for the case where a global mode is observed in the region outside the continuum. From the calculate of the frequency variation, it follows that the global modes can be found for lower frequency next to $\min(\omega_A)$ for any pair of values m and n and one effective mass value respectively.

Different pairs of values m and n with three effective mass values 2.0, 2.5 and 3.0 were investigated. In the figures 5.15, 5.16 and 5.17 are shown the possible frequency values for which the real part of the impedance (active) presents a maximum, with respect to a pair of values m and n , represented by high intensity peaks.

The calculations were made with reference to the 8 coil current of 1 A each. We recall that the active impedance represents dissipative mechanisms (heating) in the plasma boundary, while the imaginary part of the impedance (reactive impedance) corresponds

to oscillating RF fields.

The numerical procedure described above was repeated for various values of m and n in the JET tokamak experimental conditions. The results allow to obtain, in a first step, the main modes where global modes appear in the plasma considering $1.93 \times 10^{19} \text{ m}^{-3}$ as the value of the central density and taking frequency and effective mass as variable parameters.

Figure 5.15: Possible global modes, for $m = 1$ and $n = 1$, represented by impedance peaks, for certain frequency and effective mass values, for JET.

Figure 5.16: Possible global modes, for $m = 1$ and $n = 2$, represented by impedance peaks, for certain frequency and effective mass values, for JET.

Figure 5.17: Possible global modes, for $m = 1$ and $n = 3$, represented by impedance peaks, for certain frequency and effective mass values, for JET.

Figure 5.18: Possible global modes, for $m = 2$ and $n = 1$, represented by impedance peaks, for certain frequency and effective mass values, for JET.

Here, we will consider the case for which $m = 2$ and $n = 1$. The perturbed radial field profiles are calculated for zero poloidal and toroidal positions, with respect to the antenna system. We can see, from figure 5.18, that there is only one possible global

mode, represented by the peaks for each value effective mass. The corresponding radial field profiles are shown in figures 5.19 and 5.20.

Figure 5.19: $|B_r|$ field structure of possible global mode in JET for $m = 2$ and $n = 1$.

Figure 5.20: $|B_z|$ field structure of possible global mode in JET for $m = 2$ and $n = 1$.

We can calculate the field structures for the case in which the place of measurement of the field structures is $\pi/2$, i.e. 90° degrees, toroidal, and 0° degrees, poloidal. The results are shown in, figures 5.21 and 5.22,

Figure 5.21: $|B_r|$ field structure of possible global mode in JET for $m = 1$ and $n = 2$.

Figure 5.22: $|B_z|$ field structure of possible global mode in JET for $m = 1$ and $n = 2$.

Also, we calculated the field structures for the case $m = 1$ and $n = 3$ for the case in which the place of measurement of the field structures is $\pi/2$, i.e. 90° degrees, toroidal, and 0° degrees, poloidal. The results are shown in, figures 5.23 and 5.24,

Figure 5.23: $|B_r|$ field structure of possible global mode in JET for $m = 1$ and $n = 3$.

Figure 5.24: $|B_z|$ field structure of possible global mode in JET for $m = 1$ and $n = 3$.

In conclusion, we used the experimental values to calculate numerically the approximate modes numbers, effective mass and the respective profiles of magnetic field components. For the case $m = 1$ and $n = 3$ we can see that the results are very different to the experimental results in [86], LEMan code 0.2 MHz, CASTOR code without antenna

0.197 MHz, experimental 0.193 MHz and our cylindrical code 0.225 MHz with effective mass 3.0. We show in table 5.3 with the results obtained for each of the discharges analyzed.

Discharge Number	Modes Numbers	Frequency (MHz)	Effective Mass
77788 (4.9 s)	$m = 1 \quad n = 1$	0.072, 0.09	3.0
		0.084, 0.104	2.5
		0.101, 0.128	2.0
	$m = 1 \quad n = 2$	0.151, 0.108	3.0
		0.175, 0.193	2.5
		0.212, 0.238	2.0
	$m = 1 \quad n = 3$	0.225, 0.240	3.0
		0.260, 0.278	2.5
		0.318, 0.339	2.0
	$m = 2 \quad n = 1$	0.073	3.0
		0.077	2.5
		0.081	2.0

Table 5.3: Table of results obtained from numerical simulation of discharges in JET with excitation of GAWs.

In this chapter, we have shown that an external antenna structure can excite global modes that are located near the extremum of the Alfvén continuum (GAWs). However as noted above, for more realistic analysis for JET tokamak it is necessary to consider its full toroidal geometry, where toroidal Alfvén eigenmodes (TAEs) can be excited. This is the subject of the next chapter.

Chapter 6

Toroidal model of Alfvén eigenmodes

As we discussed in the first chapter, the toroidal Alfvén eigenmodes (TAEs) may be excited by alpha particles in magnetically confined fusion reactors, tapping part of the energy from these fast particles available for collisional energy transfer to the electrons, therefore making it more difficult to achieve the conditions for full plasma ignition.

The alpha particle population can change the stability properties of plasma. The confinement of alpha particles in a tokamak reactor is a crucial issue for achieving ignition. In the case of JET, a significant alpha pressure is achieved, making the study of alpha particle driven instabilities quite important. In JET, the alpha particle birth velocity is close to the Alfvén velocity; therefore, the instabilities are linked with the Alfvén waves. In a reactor dominated by high-energy fusion products the TAEs will interact with these energetic ions via particle-wave resonances.

As already seen, in cylindrical geometry the Alfvén waves can be singular and form a continuous spectrum of waves, each one localized on a single magnetic flux surface. The Alfvén waves have very large gradients on the resonant layer, i.e. when the Alfvén frequency matches the perturbation frequency at the resonant layer. These large gradients cause mode conversion leading to continuum damping. In cylindrical geometry this continuum damping is very large; therefore, the Alfvén eigenmodes can not be excited by resonant energetic particles and the poloidal Fourier harmonics are eigenfunctions of the system.

On the other hand, in toroidal geometry, i.e. in an axisymmetric toroidal plasma,

the poloidal symmetry is broken and gaps appear inside the Alfvén continuum. Inside these gaps the Alfvén resonance condition is not satisfied for some specific frequencies. Global eigenmodes excited inside these gaps may have no continuum damping and are easily destabilized by resonant energetic ions. In toroidal geometry the different Fourier cylindrical harmonics are coupled, generating the gap. Inside them, waves propagating in different directions can couple to form an standing wave with fractional poloidal mode numbers. These modes are labelled toroidicity induced Alfvén eigenmodes (TAEs).

With the purpose of studying the TAEs, we used the toroidal resistive magnetohydrodynamics code CASTOR (Complex Alfvén Spectrum of TORoidal plasmas) [101–104]. As already discussed, the TAEs can be excited by means of an external antenna [90], where the waves are not driven unstable, but oscillating with the frequency of antenna. Therefore, for modelling the excitation of TAEs by the new antenna systems of the JET tokamak, the CASTOR code was extended to include the antenna in the vacuum surrounding the plasma [105].

6.1 TAEs analysis of resistive MHD equations in toroidal geometry using CASTOR

CASTOR is a Fortran 77 code and was developed by W. Kerner and J. P. Goedbloed [102]. The CASTOR code solves numerically the resistive MHD eigenvalue problem expressed in a general toroidal geometry, where, due to this symmetry, the dependence on the toroidal angle can be described with one toroidal mode number, i.e. $u(R, Z, \phi) = u(R, Z)e^{in\phi}$, and therefore the eigenfunctions are essentially two dimensional.

The code considers the resistive MHD equations linearized around a static axisymmetric equilibrium and solves them in their weak form by applying the finite element method, which provides a flexible and highly accurate numerical approximation and leads to a large scale complex eigenvalue problem [102] and [106]. The equilibrium information needed in CASTOR is calculated using the equilibrium code HELENA [42], [43], and [107], about which we will comment later.

We remark that the following description of the CASTOR code is taken directly from

references [101–104], with equations reproduced here for sake of 'completeness. But none of this development is original work carried out in the thesis.

6.1.1 Linear resistive MHD eigenvalue problem and CASTOR code

The resistive magnetohydrodynamic equations is one of the simplest self consistent models for the description of large scale motions of a hot plasma. In this model the plasma is described as a conducting fluid embedded in a magnetic field. As noted in chapter 2, the relevant variables for the description of the plasma behavior are the density, the pressure, the fluid velocity, the current density, and the electric and magnetic fields. The time evolution of the system is determined through equations 2.76 - 2.82.

We can highlight again that, in the electromagnetic equations, the displacement current has been dropped, whereby are eliminated the electromagnetic waves from the system, and the space charge effects and ohmic dissipation are neglected in the momentum equation and in the energy equation, respectively. On the other hand, the effect of the term $\eta \vec{J}$ in the Ohm law allows for a finite electric field parallel to the magnetic field. This implies that the magnetic flux is not conserved and the magnetic field lines are allowed to break.

The resistive equations 2.76 - 2.82 can be made dimensionless by normalizing the space coordinate, the magnetic field, the density, and the velocity as follows

$$R = \frac{R}{R_M}, \quad \vec{B} = \frac{\vec{B}}{B_M}, \quad \rho = \frac{\rho_m}{\rho_M}, \quad \vec{v} = \frac{\vec{v}}{V_A} \quad \text{with} \quad V_A^2 = \frac{B_M^2}{\mu_0 \rho_M}. \quad (6.1)$$

Here R_M , ρ_M , and B_M are the major radius, the density, and the toroidal field at the position of the magnetic axis respectively, and the velocity is normalized to the velocity of the Alfvén wave on the magnetic axis. Also we have the normalization of other important quantities as

$$\begin{aligned} \vec{E} &= \frac{\vec{E}}{V_A B_M}, & \eta &= \frac{\eta}{\mu_0 R_M V_A}, & p &= \frac{\mu_0 p}{B_M^2}, \\ \vec{J} &= \frac{\mu_0 R_M \vec{v}}{B_M} & t &= \frac{t}{\tau_A}, & \text{with} & \tau_A = \frac{R_M}{V_A}. \end{aligned} \quad (6.2)$$

From the resulting system of equations, the pressure can be replaced by the temperature by using the ideal gas law $p = \Re \rho_m T$ and we can eliminate the electric field and the current density, so then we are left with four evolution equations and one condition on the magnetic field, therefore, dropping the tildes of the normalized quantities we obtain

$$\frac{\partial \rho_m}{\partial t} + \nabla \cdot (\rho_m \vec{v}) = 0, \quad (6.3)$$

$$\rho_m \frac{d\vec{v}}{dt} + \nabla p - (\nabla \times \vec{B}) \times \vec{B} = 0, \quad (6.4)$$

$$\frac{\partial \vec{B}}{\partial t} + \nabla \times (\eta \nabla \times \vec{B}) - \nabla \times (\vec{v} \times \vec{B}) = 0, \quad (6.5)$$

$$\rho_m \frac{\partial T}{\partial t} + \rho_m \vec{v} \cdot \nabla T + (\gamma - 1) \rho_m T \nabla \cdot \vec{v} = 0, \quad (6.6)$$

$$\nabla \cdot \vec{B} = 0. \quad (6.7)$$

A better way to express the system of equations 6.3 - 6.7 is to use the vector potential $\vec{B} = \nabla \times \vec{A}$ instead of $\vec{B}$ itself, with the purpose of dropping condition 6.7, which is not very suitable for numerical calculation of the time behavior of a resistive plasma. This set of equations describes the full non linear time evolution of a resistive plasma. The equations describing the linear stability are obtained by expanding all quantities around the equilibrium in the form

$$\chi(\vec{r}, t) = \chi_0(\vec{r}) + e^{\lambda t} \chi(\vec{r}). \quad (6.8)$$

Here λ is the eigenvalue and can, in general, be complex. The imaginary part of λ corresponds to oscillatory behaviour, while a negative real part yields damping and a positive real part yields an exponentially growing instability. Therefore, the resistive MHD eigenvalue problem in dimensionless units can be written in the following form [41]

$$\begin{aligned} \lambda \rho_{1m} &= -\nabla \cdot (\rho_{0m} \vec{v}_1), \\ \lambda \rho_{0m} \vec{v}_1 &= -\nabla(\rho_{0m} T_1 + \rho_{1m} T_0) + (\nabla \times \vec{B}_0) \times (\nabla \times \vec{A}_1) - \vec{B}_0 \times (\nabla \times \nabla \times \vec{A}_1), \\ \lambda \rho_{0m} T_1 &= -\rho_{0m} \vec{v}_1 \cdot \nabla T_0 - (\gamma - 1) p_0 \nabla \cdot \vec{v}_1 + 2\eta(\gamma - 1)(\nabla \times \vec{B}_0) \cdot (\nabla \times \nabla \times \vec{A}_1), \\ \lambda \vec{A}_1 &= -\vec{B}_0 \times \vec{v}_1 - \eta(\nabla \times \nabla \times \vec{A}_1). \end{aligned} \quad (6.9)$$

We note that the last equation of the system 6.9, i.e. the induction equation, was written using the relations $\vec{B} = \nabla \times \vec{A}$, allowing a formulation well suited for the numerical approximation of the entire spectrum.

In the CASTOR code, the linearized resistive MHD equations 6.9, i.e. the eigenvalue problem, are numerically solved using the Galerkin method [106], [108] and [109]. In this method, the above system of equations 6.9 can be written in the matrix form

$$\mathbf{L}\mathbf{U} = \lambda\mathbf{R}\mathbf{U}, \quad (6.10)$$

where $\mathbf{L}$ and $\mathbf{R}$ are differential operators and $\mathbf{U}$ is the state vector defined by

$$\mathbf{U}^T \equiv (\rho_1, v_{1s}, v_{1\theta}, v_{1\phi}, T_1, A_{1s}, A_{1\theta}, A_{1\phi}), \quad (6.11)$$

where the elements of $\mathbf{U}$ are expressed in the (s, θ, ϕ) coordinate system, where s is the radial coordinate (*see appendix B for more details*).

Here, the test functions, in the Galerkin method in the weak form, are chosen to be equal to the discretization functions of the state vector $\mathbf{U}$. The weak form of 6.10 is constructed by multiplying the set of equations with an arbitrary test function $\mathbf{V}$ and integrating over the domain of interest, i.e. the plasma volume

$$\int \mathbf{V}\mathbf{L}\mathbf{U}dV = \int \mathbf{V}\mathbf{R}\mathbf{U}dV, \quad (6.12)$$

therefore, $\mathbf{U}$ is a solution of 6.10 in the weak sense if the equation 6.12 is satisfied for an arbitrary $\mathbf{V}$ satisfying the appropriate boundary conditions.

The state vector $\mathbf{U}$ used in the numerical solution is expressed as

$$\bar{\mathbf{U}}^T \equiv (\bar{\rho}, \bar{v}_1, \bar{v}_2, \bar{v}_3, \bar{T}, \bar{A}_1, \bar{A}_2, \bar{A}_3), \quad (6.13)$$

where the following representation for the velocity was chosen [110]

$$\vec{v}_1 = R^2 \bar{v}_1 \nabla \theta \times \nabla \phi - i R^2 \bar{v}_2 \nabla \phi \times \nabla s - i \frac{R^2}{f} \bar{v}_3 \vec{B}, \quad (6.14)$$

where $f = \nabla \psi / \nabla s$.

The relations between the components in 6.11 and 6.14 are given in terms of the contravariant components $v^s = \vec{v}_1 \cdot \nabla s$, $v^\theta = \vec{v}_1 \cdot \nabla \theta$, and $v^\phi = \vec{v}_1 \cdot \nabla \phi$ [111]

$$\bar{v}_1 = \frac{fq}{F}v^s, \quad \bar{v}_2 = \frac{if}{F}(qv^\theta - v^\phi), \quad \bar{v}_3 = \frac{if}{F}v^\phi, \quad (6.15)$$

where $F = RB_\phi$.

Now, for the representation of the perturbed vector potential, a covariant representation is chosen

$$\vec{A} = -i\bar{A}_1\vec{a}^1 + \bar{A}_2\vec{a}^2 + \bar{A}_3\vec{a}^3, \quad (6.16)$$

where $\bar{A}_1 = iA_s$, $\bar{A}_2 = A_\theta$, and $\bar{A}_3 = A_\phi$.

Finally, the perturbed density and temperature are multiplied by s

$$\bar{\rho} = s\rho_1, \quad \bar{T} = sT_1. \quad (6.17)$$

The eight variables of the state vector U are functions of both the s and the θ coordinates. The components of the state vector are discretized by means of a combination of cubic Hermite and quadratic finite elements for the radial s -direction and a truncated series of Fourier modes for the poloidal direction. Due to the considered axisymmetric equilibrium, the dependence on the toroidal angle can be described by a single Fourier mode. This yields

$$\bar{U}^k(s, \theta, \phi, t) = \sum_{m=M_1}^{M_2} \sum_{j=1}^N (a_{mj1}^k h_{j1}^k(s) + a_{mj2}^k h_{j2}^k(s)) e^{im\theta} e^{in\phi} e^{\lambda t}, \quad (6.18)$$

where k labels the eight components of $\bar{U}$, m labels the Fourier harmonics in the poloidal direction and j labels radial grid points.

We notice that two finite elements $h_{j1}^k(s)$ and $h_{j2}^k(s)$, are used in each radial, while for $\bar{v}_1$, $\bar{A}_2$ and $\bar{A}_3$ cubic Hermite finite elements are used and, for $\bar{\rho}$, $\bar{v}_2$, $\bar{v}_3$, $\bar{T}$, and $\bar{A}_1$, are approximated by quadratic finite elements. In the Galerkin procedure the discretization 6.18 is used in the system 6.10 and the weak form of this system is obtained by multiplying it with each of the finite elements and integrating over the plasma volume, for a detailed study it is recommended reading [106] and [112].

The application of the Galerkin procedure then yields an algebraic system of the form

$$\mathbf{A} \cdot \mathbf{U} = \lambda \mathbf{B} \cdot \mathbf{U}, \quad (6.19)$$

where A is a non-Hermitian matrix and B a positive definite matrix. Both $\mathbf{A}$ and $\mathbf{B}$ are tridiagonal block matrices with sub-blocks of dimension $16M \times 16M$ (see [104] where the matrix elements of A and B are given explicitly).

An important point is the fact that the algebraic system 6.19 is part of the original version of CASTOR code, i.e. without an external antenna. A way to include the effect of the antenna on the system is to include a driving term in the system due to the external antenna, changing the eigenvalue problem into a driven response problem [113]. The asymptotic solution is characterized by the same temporal dependence of the driver and the time dependence of the plasma is given by the frequency of the driver, i.e. $\lambda = i\omega_d$. This yields the following forced oscillation problem involving the same matrices $\mathbf{A}$ and $\mathbf{B}$

$$(\mathbf{A} - i\omega_d \mathbf{B}) \cdot \mathbf{U} = \mathbf{f}_d, \quad (6.20)$$

where ω_d is the driving frequency and $\mathbf{f}_d$ is the driving term and is obtained from the solution of the vacuum equation including the antenna.

The solution $\mathbf{U}$ is now the stationary state solution in which all quantities oscillate with the driver frequency. From the numerical point of view the driven problem 6.20 is simpler than the corresponding spectral problem 6.19 since it does not require the computation of the full spectrum.

As in the case of cylindrical geometry, the study of the boundary conditions at the plasma-vacuum, vacuum-antenna-vacuum, and vacuum-wall interface to resistive MHD in toroidal geometry is very important, since the solutions in neighboring regions are connected by these boundary conditions. We will follow the scheme and notation used in [105] for the study of the boundary conditions, where it is considered a resistive plasma with zero equilibrium pressure and vanishing current density at the plasma boundary, i.e. the pressure balance condition $p_1 = 0$ is satisfied for the equilibrium considered.

In the plasma-vacuum interface, the linearized boundary conditions are

$$\vec{b} \cdot \vec{n} = \hat{b} \cdot \vec{n}, \quad \vec{b} \times \vec{n} = \hat{b} \times \vec{n}, \quad (6.21)$$

where $\vec{b}$ is the plasma magnetic field perturbation, $\hat{b}$ is the perturbed magnetic field in the vacuum, and $\vec{n}$ is normal to the plasma boundary.

We can see that, in the weak form of the eight resistive MHD equations used in CASTOR, two surface integrals appear as a result of a partial integration of the momentum and induction equation. Defining $\vec{v}^*$ and $\vec{A}^*$ as the adjoint test functions and using continuity of the equilibrium magnetic field $\vec{B}_0$ together with the vacuum response α , i.e. $\vec{B}_0 \cdot \hat{b} = \alpha(\hat{b} \cdot \vec{n}_0) = \alpha(\vec{b} \cdot \vec{n}_0)$, the two surface integrals are

$$\begin{aligned} W_S^I &= - \int \int_S \alpha(\vec{v}^* \cdot \vec{n}_0)(\vec{b} \cdot \vec{n}_0) dS, \\ W_S^R &= \int \int_S \eta(\vec{A}^* \times \vec{b}) \cdot \vec{n}_0 dS. \end{aligned} \quad (6.22)$$

Now, the relation between the normal and tangential components of the perturbed magnetic field in the vacuum at the plasma boundary describes the influence of the vacuum region between the plasma and the ideally conducting wall. For the case when there is no antenna present in the vacuum, this relation can be expressed as

$$(\hat{b} \times \vec{n})_m = \sum_{\bar{m}} \alpha_{m\bar{m}} (\hat{b} \cdot \vec{n})_{\bar{m}}. \quad (6.23)$$

The vacuum response matrix $\alpha_{m\bar{m}}$ is obtained from the vacuum solutions with the boundary condition $(\hat{b} \cdot \vec{n})_{\bar{m}} = \delta_{m\bar{m}}$ at the plasma boundary and $\hat{b} \cdot \vec{n} = 0$ at the ideally conducting wall. The row m of the matrix α contains the Fourier series of $\hat{b} \times \vec{n}$ due to the unit perturbation in the m th harmonic of $\hat{b} \cdot \vec{n}$.

For the case when we have an antenna present, the current in the antenna yields an additional contribution to the tangential magnetic field at the plasma boundary, which is independent of the normal magnetic field perturbation of the plasma, analogously as discussed in chapter 3 for the GAWs. The surface current in the antenna causes a jump in the tangential magnetic field at the antenna. The response of the tangential field to the normal field perturbation is given by

$$(\hat{b} \times \vec{n})_m = \sum_{\bar{m}} \alpha_{m\bar{m}} (\hat{b} \cdot \vec{n})_{\bar{m}} + \beta_m^{ant}, \quad (6.24)$$

where β_m^{ant} is the driven vacuum solution with unperturbed boundary and results from the vacuum solution with the boundary conditions $\hat{b} \cdot \vec{n} = 0$ at both the plasma and the ideally conducting wall.

The vacuum response matrix α is independent of the presence of the antenna. By this construction, where the antenna solution obeys the condition $\hat{b} \cdot \vec{n} = 0$ at the plasma

boundary, the complete vacuum solution consists of two independent ones, which can be seen as the homogeneous and inhomogeneous solutions of the vacuum equations.

In CASTOR code, the boundary conditions above are implemented together the vacuum solution; therefore, it is important to discuss the numerical solution of the vacuum equations. Firstly, the perturbed magnetic field in the vacuum, i.e. between the plasma boundary and an ideally conducting wall, regardless of the antenna that sits between them, is described by the equations

$$\nabla \cdot \hat{b} = 0, \quad \nabla \times \hat{b} = 0. \quad (6.25)$$

The zero curl and divergence of $\hat{b}$ suggests the introduction of a magnetic scalar potential $\hat{b} = \nabla \Phi$ reducing the equations 6.25 to a single Laplace equation $\nabla \cdot \nabla \Phi = 0$. Continuing with the methodology used in [105], the Laplace equation has to be solved with respect to two sets of boundary conditions, for the response matrix α . Considering no antenna surface, i.e. no condition, the boundary conditions are

$$\begin{aligned} (\vec{b} \cdot \vec{n})_m &= \delta_{\bar{m}m}, & \text{on the plasma boundary,} \\ \vec{b} \cdot \vec{n} &= 0, & \text{on the ideally conducting wall,} \end{aligned} \quad (6.26)$$

while, for the antenna induced response β , the boundary conditions are

$$\begin{aligned} (\vec{b} \cdot \vec{n})_m &= 0, & \text{on the plasma boundary,} \\ \vec{b} \cdot \vec{n} &= 0, & \text{on the ideally conducting wall,} \\ [\vec{b} \times \vec{n}] &= \vec{j}, & \text{at the antenna surface.} \end{aligned} \quad (6.27)$$

The coordinate system to be used in the vacuum must have three surfaces as coordinate surfaces. These three surfaces can be arbitrarily prescribed as $r_i = r_i(\theta)$ with $i = p, a$, and w , i.e. plasma boundary, the antenna, and the wall respectively. In the vacuum region the poloidal angle can be chosen to be the polar angle θ . However, on the plasma boundary it has to match with the straight field line coordinate $\chi_i = \theta_i(r = r_p)$ [62].

The radial coordinate in the vacuum region s can be constructed using a quadratic interpolation of the three fixed radial points

$$s = s_a \left(\frac{r - r_p}{r_a - r_p} \right) \left(\frac{r - r_w}{r_a - r_w} \right) + \left(\frac{r - r_p}{r_w - r_p} \right) \left(\frac{r - r_a}{r_w - r_a} \right). \quad (6.28)$$

We recall that (r, θ) are the polar coordinates system centered on the geometric center of the plasma, $\chi = \chi_p$ is the poloidal angle at the plasma boundary and it depends on the coordinate θ . Here, s_a is the position of the antenna surface in the (s, χ) coordinate system, $s = 0$ on the plasma boundary, and $s = 1$ on the wall.

For the numerical solution of the Laplace equation, the standard weak form of the finite element method is used again

$$W_V = \int \int \int \Phi^* \nabla^2 \Phi dV = - \int \int \int \nabla \Phi^* \nabla \Phi dV + \int \int \Phi^* (\vec{b} \cdot \vec{n}) dS, \quad (6.29)$$

where the surface integral is over both the plasma boundary and the wall.

The boundary term containing the term $(\vec{b} \cdot \vec{n})$ is perfectly suited to implement the boundary conditions of the vacuum problem as natural boundary conditions at the plasma and the wall, where the term arising from the wall vanishes and the term from the plasma boundary 6.26, i.e. $(\vec{b} \cdot \vec{n})_m = \delta_{\bar{m}m}$, creates the right-hand side of the system of equations resulting from the weak form. On the other hand, for the conditions 6.27, the boundary terms vanish and the conditions at the wall and at the plasma boundary are again naturally satisfied. Finally, in CASTOR code including the antenna, the jump in the magnetic potential at the antenna, i.e. the jump of Φ and $\partial\Phi/\partial s$ due to the nonorthogonal coordinate system, is an essential condition, and it is implemented by the introduction of a cubic finite element at the antenna surface, which has a jump at $s = s_a$.

6.2 The equilibrium in CASTOR code

As already said, the required information about the equilibrium is passed to CASTOR code through the equilibrium mapping file produced by the equilibrium code HELENA [107]. In this section we will describe briefly the method used for the numerical solution of the equilibrium equations for the purpose of calculating the equilibrium quantities needed in the code CASTOR.

The HELENA code is a Fortran 77 program that solves the MHD equilibrium equation of a toroidal axisymmetric plasma with the use of isoparametric bicubic Hermite finite elements and yields accurate solutions. The procedure is based on adjusting the positions of the elements, such that, in the final solution, the element boundaries coincide with flux

surfaces greatly facilitating the calculation of the flux surface quantities needed for the stability calculations.

6.2.1 The Grad-Shafranov equation

The equations describing the static equilibrium of an ideal plasma are given by force balance, Ampère's law, and the condition of vanishing divergence of the magnetic field

$$\vec{J} \times \vec{B} = \nabla p, \quad \mu_0 \vec{J} = \nabla \times \vec{B}, \quad \nabla \cdot \vec{B} = 0. \quad (6.30)$$

Firstly, in figure 6.1 it is shown the representation of the tokamak geometry with cylindrical coordinates (R, ϕ, Z) . Here, R is the distance from the axis of symmetry, Z is the vertical coordinate, R_e and R_i are the two values of the major radius where the last closed magnetic surface crosses the equatorial plane, where $R_i < R_e$, $a = (R_e - R_i)/2$ and $R_0 = (R_e + R_i)/2$.

Figure 6.1: Schematic representation of the tokamak geometry.

In toroidal geometry with axisymmetry, the zero divergence of $\vec{B}$ allows for the introduction of a scalar field $\psi(R, Z)$ such that the magnetic field can be represented by

$$\vec{B} = \nabla\psi \times \nabla\phi + F\nabla\phi, \quad (6.31)$$

where $F = F(\psi)$ is an arbitrary function representing the poloidal current profile [102], ψ represents the poloidal magnetic flux, and the poloidal magnetic field is obtained from the relation $B_p = \nabla\psi/R$. We notice that the field lines lie on surfaces of constant ψ , i.e. $\vec{B} \cdot \nabla\psi = 0$. The current density can then be written as

$$\vec{J} = -\Delta^*\psi\nabla\phi + \nabla F \times \nabla\phi, \quad (6.32)$$

where the operator ∇^* is given by [107]

$$\Delta^* \equiv R^2 \nabla \cdot \frac{1}{R^2} \nabla. \quad (6.33)$$

The first equation of 6.30, i.e. the MHD equilibrium force balance, is described by the Grad-Shafranov equation for the poloidal flux $\psi(R, Z)$ [62]

$$\Delta^*\psi \equiv R \frac{\partial}{\partial R} \left(\frac{1}{R} \frac{\partial\psi}{\partial R} \right) + \frac{\partial^2\psi}{\partial Z^2} = \mu_0 R J_\phi, \quad (6.34)$$

where J_ϕ is the toroidal current density. Due to the toroidal symmetry, the right-hand side of 6.34 can be written in terms of two flux functions, i.e. the pressure P and the diamagnetic profile F . From force balance it follows that both $P(\psi)$ and $F(\psi) = RB_\phi$ are functions of ψ only, i.e. $\nabla p \times \nabla\psi = 0$ and $\nabla F \times \nabla\psi = 0$. Therefore

$$\mu_0 R J_\phi = -\mu_0 R^2 \frac{dP(\psi)}{d\psi} - \frac{1}{2} \frac{dF^2(\psi)}{d\psi}. \quad (6.35)$$

The formulation of the equilibrium problem of finding $\psi(R, Z)$ in terms of physical quantities contains two trivial scaling parameters, the vacuum magnetic field B_0 at the geometric center of the plasma and the scale length of the problem which is the minor radius of the plasma boundary a . These two parameters only provide the dimensions of the physical quantities and do not enter the problem otherwise. Similarly, the total poloidal flux $2\pi\psi_1$ only enters as a scaling parameter normalizing the J_ϕ and B_ϕ profiles. Normalizing the two profiles P and F using the parameter $\alpha = a^2 B_0 / \psi_1$ and rescaling the physical parameters the Grad-Shafranov equation becomes [107]

$$\Delta^* \bar{\psi} = \frac{\partial^2 \bar{\psi}}{\partial x^2} + \frac{\partial^2 \bar{\psi}}{\partial y^2} - \frac{\epsilon}{1 + \epsilon x} \frac{\partial \bar{\psi}}{\partial x} = -\frac{(1 + \epsilon x)^2}{\epsilon} \bar{P}'(\bar{\psi}) - \frac{1}{\epsilon} \bar{F}(\bar{\psi}) \bar{F}'(\bar{\psi}), \quad (6.36)$$

where $\bar{\psi} \equiv \psi/\psi_1$ is the normalized flux, which plays the role of a radial coordinate, $\epsilon = a/R_0$ is the inverse aspect ratio, and the normalized coordinates $x = (R - R_0)/a$ and $y = Z/a$ are used in the poloidal plane.

The solution $\bar{\psi}(x, y)$ of the above equation is a smooth continuous function of x and y so that the solution consists of a set of nested closed flux surface around the magnetic axis where $B_p = 0$. In order to separate the shape of the two input profiles $\bar{P}(\bar{\psi})$ and $\bar{F}(\bar{\psi})\bar{F}'(\bar{\psi})$ from the amplitude, two unit profiles are defined, which are normalized to one at the magnetic axis ($\bar{\psi} = 0$) [114] and [115]

$$\begin{aligned} \frac{1}{2} AB \Pi(\bar{\psi}) &= -\bar{P}'(\bar{\psi}), \\ A \Gamma(\bar{\psi}) &= -\frac{1}{\epsilon} (\bar{P}'(\bar{\psi}) + \bar{F}(\bar{\psi}) \bar{F}'(\bar{\psi})), \end{aligned} \quad (6.37)$$

with $\Pi(0) = \Gamma(0) = 1$. The quantities A and B determine the amplitudes of the two input profiles. However, only B is an input quantity for HELENA code and the value of A is determined by the condition $\bar{\psi}$ on the plasma boundary. Therefore, in terms of $\Pi(\bar{\psi})$ and $\Gamma(\bar{\psi})$ the Grad-Shafranov equation is written as follows

$$\Delta^* \bar{\psi} = A [\Pi(\bar{\psi}) + Bx(1 + \frac{\epsilon x}{2}) \Gamma(\bar{\psi})]. \quad (6.38)$$

The boundary condition to be imposed on the solution of equation 6.34 depends on the type of application. An important point is that the distance and the magnetic field are normalized differently in the HELENA and CASTOR codes. The distance and the magnetic field are rescaled in HELENA when the mapping file for CASTOR code is produced. The equilibrium quantities needed as input for the toroidal resistive eigenvalue code CASTOR are primarily the coefficients g^{ij} of the straight field line coordinate system (s, θ, ϕ) , see appendix B. In HELENA code, cubic Hermite elements are used for the discretization of the computational plane and for the solution ψ , and yields a very accurate representation of ψ and $\nabla \psi$ with a continuous representation of the fields lines [43]. The Grad-Shafranov equation is solved using the Galerkin method in the weak form, using the discretization of x , y and ψ ; this leads to a system of linear equations for each step of the non-linear iteration [104]. Because the plasma behaviour is quite anisotropic with respect

to the directions parallel and perpendicular to equilibrium magnetic field, it is essential to consider the poloidal flux as a radial coordinate. This coordinate is called flux coordinate system (ψ, θ, ϕ) and it is characterised by the Jacobian $J^{-1} = \nabla\psi \times \nabla\theta \cdot \nabla\phi$. On the other hand, HELENA code also expresses the poloidal cross section in equilibrium by a straight field line coordinate system (ψ, χ, ϕ) , which is characterised by a constant ratio $B_0^\phi/B_0^\chi = q(\psi)$, here q denotes the safety factor.

Chapter 7

Excitation of Toroidal Alfvén Eigenmodes in JET

7.1 Introduction

In this chapter we investigate the excitation of toroidal Alfvén eigenmodes (TAEs) in JET, using the CASTOR code. The main objective of this study is to determine the effectiveness of the new antenna system installed in JET to drive modes with a somewhat cleaner spectrum than that obtained in previous experiments, with just one amplifier driving all the modules of the antenna [39]. Specifically, in the new excitation system, designed by the Plasma Physics Laboratory of the University of São Paulo, each module of the antenna will be excited by an independent amplifier. The driving signals for the eight amplifiers will be provided by a master driver unit that can vary the amplitude and the phase of the driving signal for each amplifier, in order to preferentially excite a particular mode, that is, a mode with a specific toroidal mode number n . The master driver unit will be programmable so that it will specify the amplitudes and phases for the amplifiers from a feedback signal from the antenna. Therefore, if a particular mode is excited, the master driver can program the driving signals for the amplifiers in order to track it during the entire RF pulse.

However, as already described in chapter 4, the new antenna system of JET has only two antennae, separated 180° in the toroidal direction, each one with four modules [117].

Then, one important question to be asked is how effective will be the variation of amplitude and phase of the feed current for each module to select a reasonable "*pure*" mode. In this chapter we address this question through numerical calculations of the actual fields excited in the plasma, using the CASTOR code. Actually, in his doctoral thesis, Panis also used the same code to calculate the mode structure of the modes and compared the results with experimental ones from JET [86]. However, he did not use the version of the code that allows modeling of the excitation by external antennae [105], possibly due to the difficult to properly implement the new antenna configuration of JET.

Therefore, the first task to achieve our objective was to include in the antenna version of CASTOR the new antenna structure. This was successfully done after direct consultation with Dr. Duarte Borba and Dr. Guido Huysmans, who developed the antenna version of CASTOR. The results of the revised version of the code were benchmarked by comparison with the experimental results from discharge #77788 of JET, which is well documented in the literature [86], [105], and [97], as described in the sequel.

As already mentioned, in toroidal geometry the poloidal mode number m is not a proper quantum number and the coupling between cylindrical modes with different m numbers introduces gaps in the Alfvén continuum of cylindrical geometry [23]. The gap is mainly caused by counter-propagating modes, so that, in cylindrical geometry, the parallel mode number for the poloidal mode number m beats with that for $m + 1$; specifically the gap occurs at a magnetic surface $s = s_0$ where the Alfvén frequencies to m and $m + 1$ are equals and

$$k_{\parallel m}(s_0) = -k_{\parallel m+1}(s_0), \quad (7.1)$$

which is related, in the cylindrical approximation, with the position where the safety factor is

$$q(s_0) = \frac{m + \frac{1}{2}}{n}. \quad (7.2)$$

Knowing the profile of the safety factor, $q(s)$, this expression allows to determine the pairs (m, n) of the cylindrical mode numbers where the condition given by equation 7.1 is satisfied and, from these values, we can estimate the range of frequencies for which TAEs can be excited, according to the expression given by the cylindrical approximation,

$$\frac{\omega}{V_a(s)/R} = \frac{1}{2q(s)}. \quad (7.3)$$

The range is therefore determined by the minimum and maximum values of q .

For a given frequency, the mode structure is calculated using the current antenna system of JET, for each frequency of the chosen range. For this purpose, it was necessary to introduce some changes in the previous extended version of CASTOR that allow external excitation [105] and [118]. The precise positions and dimensions of all modules of the antenna, figure 7.1, were used to calculate all coefficients of the helical Fourier components of the antenna currents, as described in chapter 5.

Figure 7.1: Position of the antennas on the toroidal model. Here R_0 is the major radius.

Nevertheless, in CASTOR the phasings of the currents feeding each module can be specified only as 0 or π radians. This allows only a gross separation between even modes, with all modules with zero phase, and odd modes, with the first four modules with zero phase and the remaining ones with π phase, for example; more cases are presented in appendix D. Therefore, the testing of the fine tuning of the antenna system, with proper phases of the currents feeding the different modules, to excite a better spectrum of modes centered on a desired value of n , is not directly possible to carry out with CASTOR. This problem was overcome by adopting the procedure described in the sequel.

1. Determination of the equilibrium quantities

The equilibrium quantities are calculated with the HELENA code [107]. All the required inputs for this code, aspect ratio, shape of the plasma column, pressure and poloidal

current profiles in terms of the flux function, etc, can be arbitrarily specified, or, as will be the case for the results presented in this chapter, obtained from the equilibrium reconstruction of actual tokamaks discharges. The HELENA code provides all the required inputs for CASTOR, as the computational grid, metric parameters for the vector operators, etc.

2. Determination of the resonances

Once determined the equilibrium quantities and defined the frequency range of interest, the resonance frequencies, for a given value of n , are determined by running CASTOR with all antenna modules, with the only provision of choosing all phases the same (zero) for even modes, and opposite phases for odd modes, as already explained. The resonance frequencies are manifested as peak in the absorbed power, as exemplified in figure 7.2. Naturally, we first performed a gross frequency scan followed by finer ones near the resonances.

Figure 7.2: Example of resonance frequencies indicated by peaks in the absorbed power. The power absorbed, in arbitrary units, by the plasma as a function of the normalized antenna frequency.

As explained in chapter 6, CASTOR utilizes a Fourier representation in the poloidal direction and cubic Hermite finite elements in the radial direction. The maximum number of poloidal harmonics is chosen by the user. However, since normally the minimum value

of q is around one, it follows from the approximate cylindrical expression, Eq. 7.2, that values of $|m|$ of the order of n have to be taken into account in the poloidal representation. Actually, to guarantee a proper representation, the minimum value of m in the poloidal representation has to be at least of the order of $2n$, approximately. With this caveat, the profiles of the excited fields in a poloidal cross section of the plasma column can be determined in this step.

3. Calculation of the mode profiles

The impossibility of specifying arbitrary phases of the feeding currents in CASTOR is overcome by exploring the helical Fourier representation of the antenna elements. The positions of these elements are schematically represented in figure 7.3, where z corresponds to the toroidal direction and y to the poloidal direction, $0 \leq z \leq 2\pi R$ and $0 \leq y \leq 2\pi a$.

Figure 7.3: The scheme of the positioning of the JET antennas.

Although the actual antennas are slightly below the equatorial plane in JET, we neglect this weak effect in the current modelling, although it could be easily included. Taking into account the helical Fourier representation of the antenna, it follows that the field components, calculated for fixed mode numbers m and n and for an antenna module centered at coordinates (y_i, z_i) , $i = 1, 2, \dots, 8$, are simply related to those of a module centered at $y = 0$, $z = 0$ by the phase coefficient $k_i = e^{-i(\frac{m}{a}y_i + \frac{n}{R}z_i)}$. Using this fact, after choosing a resonant frequency, we calculate all the field variables in the plasma for just one reference module. Representing any field variable (we usually consider the radial component of the perturbed velocity) calculated for this module by $\tilde{V}_{ref}$, we have that same quantity for any other module is given by

$$\tilde{V}_i = \tilde{V}_{ref} \times e^{i(\frac{m}{a}y_{ref} + \frac{n}{R}z_{ref})} \times e^{-i(\frac{m}{a}y_i + \frac{n}{R}z_i)}. \quad (7.4)$$

Since one module can excite a large spectrum of n modes, for each frequency we calculate the perturbed fields corresponding to all values of n that are of interest ($1 \leq n \leq 17$ in the calculations presented in this chapter). For each value of n , we store a matrix with the values of the perturbed field for all radial positions of the grid and for all values of the poloidal components used to represent the field ($|m| \leq 23$). With this data, we can reconstruct the quantities for any other module using Eq. 7.4 and including the specific values of the amplitude and phase of the current feeding that module.

4. Optimization of the spectrum

Naturally, to optimize the spectrum for a given toroidal mode number n_0 , the phase of the current feeding a module located at z_i has to be multiplied by the phase factor $e^{-i\frac{n_0}{R}z_i}$. Therefore the sum $\sum_{i=1}^8 \tilde{V}_i$ for this value of n is maximized. However, the other components of the spectrum excited by the same module will be multiplied by $e^{-i\frac{n-n_0}{R}z_i}$ and will interfere not in phase with the components due to the other modules. Therefore, the perturbed field distribution in a given poloidal plane will continue having components for $n \neq n_0$ and will not correspond to a single eigenfunction for $n = n_0$.

In the results presented in the sequel, we compare the radial profiles of the radial component of the perturbed velocity before and after optimization for a given toroidal mode number n_0 . As expected, the amplitude of the perturbations increase for this value. However, it not always decreases for satellite values of n , in particular, in the case of values $n_0 \sim 10$, for which neighboring modes have very close resonance frequencies.

7.1.1 Results of the simulation of TAEs in JET

In this section we present the results of simulations performed for the new antenna system of JET. For benching marking the results, we simulate the discharge #77788, for which detailed experimental data are available [97].

This discharge was one of an experimental campaign to measure the damping rate of TAEs excited already with the new antenna system of JET, but with all modules driven by only one RF amplifier, i.e., without the possibility of fine tuning the phases of the currents feeding the individual modules. In this discharge an almost continuous $n = 3$ mode was observed, but also $n = 7, 9$ modes and no even n modes.

The equilibrium quantities provided by the HELENA code for the discharge #77788, at $t = 10$ s, are shown in figures 7.4 and 7.5. In figure 7.4 the magnetic flux surfaces are pictured in terms of straight-field-lines coordinates (a) and in terms of flux and poloidal angle variables (b). The corresponding profile for the safety factor q is shown in figure 7.5, with the value 0.861 at the magnetic axis. The maximum plasma current in this discharge was $I_p = 2$ MA and the toroidal magnetic field $B_T = 2.7$ T.

Figure 7.4: Equilibrium solution provided by HELENA for JET discharge #77788 at $t = 10$ s, R , ϕ , Z denote cylindrical coordinates. Flux line contours shown in straight-field-line coordinates (a) and flux coordinates (ψ, χ) (b).

Figure 7.5: The safety factor profile reconstructed by HELENA for JET discharge #77788 at $t = 10$ s. Plasma current $I_p = 2$ MA; toroidal magnetic field $B_T = 2.7$ T.

Finally the density profile used in the simulations, which can be somewhat arbitrarily specified in CASTOR, is shown in figure 7.6. In CASTOR the density profile is introduced normalized, i.e. n_e/n_{e0} , like all inputs [103]. We note that density profile is very similar to the density profile used in [86], thereby justifying the reason for this choice. The central electron density is $n_{e0} \approx 2.3 \times 10^{19} \text{ m}^{-3}$ which is similar to experimental value in [86].

Figure 7.6: Density profile used in CASTOR to simulate JET discharge #77788 at $t = 10$ s. Here $n_{e0} \approx 2.3 \times 10^{19} \text{ m}^{-3}$.

7.1.1.1 Analysis of $n = 3$ TAEs

In the case of $n = 3$ modes, the range of frequencies where the resonance can be located is estimated by the TAE gaps modes in the continuous spectrum of local Alfvén waves, using the expression 7.3, as it is shown in the figure 7.7.

Figure 7.7: The frequency spectrum of the $n = 3$ modes as function of the the variable s that labels the flux surfaces. The the red lines represent the TAE region and the green line represent the normalized frequency of resonance.

The TAE gap closest to the plasma center is the $(m, m + 1) = (3, 4)$ gap, at the flux surface $q = 1.167$. The toroidicity induced gaps, in the range of frequencies between the red spaced lines, represent the TAE region where the antenna frequency is scanned in the search for eigenmodes. For these calculations, we employed poloidal Fourier representation with maximum poloidal number $|m| = 23$.

The absorbed power is shown as a function of the normalized mode frequency $x = \omega R/V_A$. We observe three well defined peaks at $x = 0.39, 0.43$, and 0.47 . The experimental value for the frequency, using only four modules of the antenna system, is $f = 186$ kHz, at $t = 9.3$ s. Other experimental values for the frequency are $f = 179$ kHz, at $t = 13.8$ s, and $f = 174$ kHz, at $t = 14.9$ s. Considering the value of the major radius of JET, $R = 2.96$ m, and the central density $n_{e0} \approx 2.4 \times 10^{19} \text{ m}^{-3}$, the frequency 186 kHz corresponds to $x = \omega R/V_A = 0.41$, very close to the value $x = \omega R/V_A = 0.43$ of the maximum peak in figure 7.8. Actually the difference between the two values correspond to relative error in the central density $\delta n/n_{e0} \approx 0.08$, well within the experimental error in the density measurement.

Figure 7.8: The power absorbed by the plasma as a function of the antenna frequency.

In the figure 7.9 we show the comparison between the total spectrum of the eight antennas and the spectrum due only to $n = 3$, it for unoptimized phases. We observe that the $n = 3$ component of the spectrum represents the major contribution to the total spectrum.

Figure 7.9: Values of the radial velocity field excited by all eight antennas for unoptimized phases. For $n = 3$ (blue asterisk), and for all modes (red solid).

In the figure 7.10 we show the comparison between the spectrum with unoptimized and optimized phases for the toroidal resonant mode $n_0 = 3$. The total perturbed radial velocity due to the eight antennas with unoptimized phases is shown in (a) and with phases optimized in (b).

Figure 7.10: Real (blue asterisk), imaginary (green dotted) and absolute (red solid) values of the radial velocity field for $n = 3$ mode, which is excited by all eight antennas. (a) unoptimized phases, (b) phases optimized using the factor $e^{-i \frac{n_0}{R} z_i}$ for $n_0 = 3$.

We see that for $n = 3$, the π phasing between the toroidally opposite modules of the antenna already provides a quite good optimization. Indeed, the detailed phase optimization increases the absolute value of the perturbed radial velocity only by a small factor of 1.06. The optimized phases of the eight antennas are shown in the table 7.2 at the end of this section.

However, since the optimization was for the $n_0 = 3$ mode, it is important to verify how the other components of the spectrum behave. First we note that, as expected, the even components are not much affected, as shown for $n = 4$ in figure 7.11.

Figure 7.11: Real (blue asterisk), imaginary (green dotted) and absolute (red solid) values of the total radial velocity field for the $n = 4$ component of the spectrum, which is excited by all eight antennas. (a) unoptimized phases, (b) phases optimized for $n_0 = 3$.

However, for the odd components of the spectrum, the $n_0 = 3$ phase optimization does not lead to a reduction of their amplitude; in fact it may even lead to an increase. This is shown in figure 7.12 for the $n = 5$ component, where the increase factor is 1.15 approximately and the absolute value of the perturbed radial velocity is more intense in the region near to the edge of the plasma column, and in figures D.1 and D.2 of appendix D, for the $n = 1$ and $n = 7$ components, respectively.

This is because, the neighboring modules do not allow good mode discrimination, for low values of n odd. We note that the vacuum wavelength for these modes is larger than 10^3 m, while the distance between the antenna modules are of the order of 30 cm. However for $n = 1$, as show in the figure D.1, we observe a slightly decrease after the optimization process.

Figure 7.12: Real (blue asterisk), imaginary (green dotted) and absolute (red solid) values of the radial velocity field for the $n = 5$ component, excited by all eight antennas. (a) unoptimized phases, (b) phases optimized for $n_0 = 3$.

7.1.1.2 Analysis of high- n TAEs

One of the main objectives of the new antenna system is to facilitate the excitation of improved spectrum of large n modes. Then, to check the efficiency of the system, we will study the toroidal modes within the range $n = 7$ to $n = 13$. The normalized resonant frequencies $\omega R/V_A$ obtained with CASTOR for each value of n in this range are shown in table 7.1.

In this section, we present the results for the three main resonant modes, i.e. $n = 9, 10$, and 11 . The spectrum of the odd resonant modes $n = 9, 11$, by unoptimized phases, are obtained using the phases $[0^\circ, 0^\circ, 0^\circ, 0^\circ, 180^\circ, 180^\circ, 180^\circ, 180^\circ]$ and of the even mode $n = 10$ by using the same phase in all modules $[0^\circ]$. We compare the radial profiles of the radial perturbed velocity of the main mode and of all the other components of the spectrum as the optimization for a particular value of n is carried out.

Toroidal Mode	Normalized Resonance Frequency	Toroidal Mode	Normalized Resonance Frequency
7	0.38	12	0.43
8	0.51	13	0.55
9	0.49	14	0.45
10	0.53	15	0.52
11	0.48		

Table 7.1: Table of results obtained from CASTOR to the normalized resonance frequency.

In the figures 7.13, 7.14 and 7.15 we show the comparison between the total spectrum of the eight antennas and the spectrum due only to $n = 9$, $n = 10$ and $n = 11$, for unoptimized phases, respectively. We observe that, for the $n = 9$, $n = 10$ and 11 modes, the spectrum is dominated by their contribution, that is, summing the contributions of all n mode numbers, the resulting perturbations is still determined mainly by the $n = 9$ and 11 components of the spectrum.

Figure 7.13: Values of the radial velocity field excited by all eight antennas for unoptimized phases. For $n = 9$ (blue asterisk), and for all modes (red solid).

Figure 7.14: Values of the radial velocity field excited by all eight antennas for unoptimized phases. For $n = 10$ (blue asterisk), and for all modes (red solid).

Figure 7.15: Values of the radial velocity field excited by all eight antennas for unoptimized phases. For $n = 11$ (blue asterisk), and for all modes (red solid).

In figures 7.16 to 7.18 we show the comparison between the spectrum with unoptimized and optimized phases for the toroidal resonant modes $n_0 = 9, 10$, and 11. We note that the efficiency of the optimization process is reasonable, since the intensity of each resonant mode is increased by the optimal phasing. For the $n_0 = 9$ mode, for example, the increase in the absolute value is by a factor of 1.84 approximately. This factor is 2.19 and 2.7 when $n_0 = 10$ and 11, respectively. For the three modes, the absolute value of the perturbed radial velocity, is more intense in the middle region between the center and the edge of the plasma column.

In the table 7.2 it is presented the optimized phases values, for the eight modules, for each resonant mode. The same characteristic observed for $n_0 = 3$ is present for the high- n values, that is, all components with $n > n_0$ increase in intensity by a factor larger than that for the resonant mode n_0 , as shown in sections D.0.2 to D.0.4 in appendix D. However, the components $n < n_0$ increase in intensity by a factor smaller than that for the resonant mode n_0 . This characteristic depends on the parity of n_0 , i.e. if it is even or odd mode.

Figure 7.16: Real (blue asterisk), imaginary (green dotted) and absolute (red solid) values of the radial velocity field for resonant mode $n = 9$, which is excited by all eight antennas. (a) unoptimized phases, (b) phases optimized for $n_0 = 9$.

Figure 7.17: Real (blue asterisk), imaginary (green dotted) and absolute (red solid) values of the radial velocity field for resonant mode $n = 10$, which is excited by all eight antennas. (a) unoptimized phases, (b) phases optimized for $n_0 = 10$.

Figure 7.18: Real (blue asterisk), imaginary (green dotted) and absolute (red solid) values of the radial velocity field for resonant mode $n = 11$, which is excited by all eight antennas. (a) unoptimized phases, (b) phases optimized for $n_0 = 11$.

Toroidal resonant mode	Optimized phases values
3	[26.31°, 8.77°, -8.77°, -26.31°, -153.70°, -171.23°, -188.77°, -206.30°]
9	[78.92°, 26.31°, -26.31°, -78.92°, -101.08°, -153.69°, -206.31°, -258.92°]
10	[87.69°, 29.23°, -29.23°, -87.69°, -272.31°, -330.77°, -29.23°, -87.69°]
11	[96.45°, 32.15°, -32.15°, -96.45°, -83.55°, -147.85°, -212.15°, -276.45°]

Table 7.2: Table of results obtained from CASTOR to the normalized resonance frequency.

We also carried out an analysis of the spectrum changes for variations of the optimal phase. We vary the optimal phases by the following amounts $\Delta = \pm 0.5^\circ, \pm 5^\circ, \pm 45^\circ, \pm 90^\circ, \pm 135^\circ, \pm 175^\circ$.

In all cases, we find variation in the intensity of the components, for all the phase variations $\pm\Delta$, when the variation is done simultaneously for all eight modules. In the case when the phase variations is done only for one module, or some specific module, and with different phase variations between them, we observe that the intensity of the components with parity equal to that of the resonant mode n_0 , including the proper resonant mode, are reduced, and a large increase in the intensity of the spectrum components with parity different to that the resonant mode, but without exceeding the intensity of the resonant mode.

In figures 7.19 to 7.21 we show the radial velocity fiel excited by all eight antennas after the optimized process for the toroidal modes $n = 9$, $n = 10$ and $n = 11$.

Figure 7.19: Values of the radial velocity field excited by all eight antennas for optimized phases. For $n = 9$ (blue asterisk), and for all modes (red solid).

Figure 7.20: Values of the radial velocity field excited by all eight antennas for optimized phases. For $n = 10$ (blue asterisk), and for all modes (red solid).

Figure 7.21: Values of the radial velocity field excited by all eight antennas for optimized phases. For $n = 11$ (blue asterisk), and for all modes (red solid).

It is important to verify how the optimization process affects the total spectrum in the toroidal direction. In figures 7.22 to 7.24 we show the comparison, for a toroidal section, between the total spectrum, expressed by the module of the perturbed radial velocity, to (a) unoptimized and (b) optimized phasing, around the toroidal direction, for the modes $n_0 = 9, 10$, and 11 . We can see that after of the optimization process the highest intensities are dislocated on the edge of the plasma column, therefore, away from the center of the plasma column.

Figure 7.22: Module of the perturbed radial velocity in a toroidal section for resonant mode $n = 9$, which is excited by all eight antennas.(a) unoptimized phases, (b) phases optimized for $n_0 = 9$.

Figure 7.23: Module of the perturbed radial velocity in a toroidal section for resonant mode $n = 10$, which is excited by all eight antennas.(a) unoptimized phases, (b) phases optimized for $n_0 = 10$.

Figure 7.24: Module of the perturbed radial velocity in a toroidal section for mode resonant $n = 11$, which is excited by all eight antennas. (a) unoptimized phases, (b) phases optimized for $n_0 = 11$.

7.1.2 Results of the simulation of TAEs in JET considering different antenna distribution

We can see that the optimization does not isolate successfully only the central toroidal mode. The satellite modes are also better excited about the optimization process and their intensities are increased even in the biggest factors that the proper optimize mode, although it does not exceed the intensity of this. One possible cause could be due to the symmetry and the proximity of the coils that make up the new JET antenna, which are not suitable for excitation of a satisfactorily pure spectrum. So it was also investigated the excitement given more antenna modules and their redefinition of locations around the plasma column.

In figure 7.25 we show a proposal for a configuration of the JET antenna by increasing the numbers of modules and redefining their positions around the plasma column. We propose the use of 4 modules separated 90° with each module consisting of 8 square coils.

Figure 7.25: Proposal for the position of the antennas on the toroidal model.

In figure 7.26 is shown the spectrum created by the proposal configuration of the JET antenna in the vacuum, relating the absolute value of the total current density of the antenna for each toroidal mode with a particular combination of phase between the eight modules. For the spectrum in the vacuum we note that the optimization process isolates successful forms only the central toroidal mode and the evidence the central toroidal mode is best achieved.

Figure 7.26: Spectrum created by eight modules of the new JET antenna (a) with unoptimized phases exciting odd toroidal modes with phases 0° to 4 coils of each module and 180° for the other 4 coils of each module. (b) optimizing $n_0 = 9$.

The results considering the response of the plasma for the case $n_0 = 9$ is show in figure 7.27. The comparison between the radial profile of the radial perturbation velocity field excited by the 32 coils for unoptimized phases and optimized phases to $n_0 = 9$ shows that when increase the numbers of modules, as well, the numbers of coils in each module and redefine the positions around the plasma column inside of the vessel, the goal to put into evidence the central toroidal mode is best achieved. Other configurations were also studied, for instance 4 modules with 4 coils each and separated 90° and 8 modules with 4 coils each and separated 45° , and all gave similar and good results.

Figure 7.27: Values of the radial velocity field excited by all 32 antennas. For $n = 9$ (blue asterisk), and for all modes (red solid). (a) with unoptimized phases exciting odd toroidal modes with phases 0° to 4 coils of each module and 180° for the other 4 coils of each module. (b) optimizing $n_0 = 9$.

Chapter 8

Conclusions and outlook

8.1 Summary

The main objective of this work was to study perturbations of plasma through the excitation of TAEs using the new JET external antenna. For this purpose, we studied the Alfvén waves from the point of view of the MHD theory for different regimes. Firstly was studied the theory MHD in cylindrical geometry, in which we see the emergence of GAWs outside the continuum of Alfvén waves and close to its minimum. Essentially, an old program to analyze GAWs was modified and adapted to the configuration of TCABR, considering its external antenna geometry. Unfortunately the results could not be validated with experimental results but we are confident that the program is useful and give optimal results when required. The program also was adapted for JET and its new antenna, which was also studied, but the results are only speculative and were performed only as a preliminary test that played the role of an introduction to the study of TAEs.

Subsequently, were studied two numerical codes, i.e., HELENA and CASTOR. The HELENA code solves the MHD equilibrium equation of a toroidal axisymmetric plasma, generates an equilibrium mapping file that gives the required input information for CASTOR. CASTOR solves the linear, resistive MHD eigenvalue problem in a general toroidal geometry, where the equilibria are assumed to be axisymmetric. We implemented the new JET antenna geometry, respecting its design parameters, and maior radius, minor radius, geometry of the JET vessel, etc. We study the JET discharge #77788 at the time

10 seconds.

8.2 Conclusions

Our objective with the CASTOR code was to study the high- n toroidal modes generated by the new JET antenna. Our specific objective was to perform a process of optimization the antenna phases, since it is very useful to know which phases the RF amplifier must work to excite a determined toroidal mode. Our results shown, that using the process of optimization, we can excite any toroidal mode with the RF amplified using the optimal phases values for each antenna. The radial velocity perturbation, which is related with the plasma perturbation, is amplified and detected in a better way, unlike the standard numerical calculations with CASTOR, which are limited to only $0, \pi$ phasing for each antenna module. Therefore using the RF amplifier and optimized phase, which are calculated by CASTOR, we can excite the plasma and know the toroidal mode linked to the excitation. From the results, we can also observe that, although we want to excite a given toroidal mode by optimization process, other toroidal components will also be excited, However the intensity of theses toroidal components never exceed the intensity of the main mode.

We can conclude that the geometry of the new JET antenna it is not well suited for exciting a rasonable pure toroidal eigenmode. For this, it would be necessary to have more antenna modules and their redefinition of locations around the plasma column. The results considering proposal for a configuration of the JET antenna show that when increase the numbers of modules, as well, the numbers of coils in each module and redefine the positions around the plasma column inside of the vessel, the goal to put into evidence the central toroidal mode is best achieved.

On the other hand, it is very important to have access to codes as HELENA and CASTOR, since from them we can create new subroutines and make changes to improve the codes, such that they adapt to new emerging problems in the future.

8.3 Outlook

Finally, a future development of this work would be to use more sophisticated numerical codes than the HELENA-CASTOR pair. The leading candidates are the pair FINESSE-PHOENIX equilibrium-stability codes [119] and [120], which are installed at the Plasma Physics Laboratory of the University of São Paulo.

The FINESSE code (finite element solver for stationary equilibria) computes axisymmetric magnetohydrodynamic equilibria in poloidal elliptic flow regimes. The PHOENIX code is based on the original algorithmic widely used and rigorously tested in the CASTOR code, and calculate the MHD spectral code for rotating plasmas.

Actually the pair FINESSE-PHOENIX with the effects of flow incorporated has been put in the ITER repository for anybody interested to work on MHD problems of interest for ITER. After of the antenna implementation in the PHOENIX code and understanding how to excite the plasma with an antenna considering plasma flows, we can also address problems like feed-back stabilization of modes, TAEs or ELMs (edge-localized modes) for example.

Bibliography

- [1] J. Wesson, *Tokamaks*, Clarendon press, Oxford, (1987).
- [2] T. K. Fowler, *The Fusion Quest*, Jonns Hopkins University, Baltimore, MD, (1997).
- [3] E. Teller, *Fusion*, Ed., Vol. I, Parts A, B, Academic, New York, (1981).
- [4] F. L. Ribe, Rev. Mod. Phys. 47, 7 (1975).
- [5] J.P. Freidberg, *Plasma physics and fusion energy*, Cambridge University Press, (2007).
- [6] J. D. Lawson, *Some Criteria for a Power Producing Thermonuclear Reactor*, Proceedings of the Physical Society B, Volume 70, p. 6 (1957).
- [7] N. A. Krall and A. W. Trivelpiece, *Principles of Plasma Physics*, McGraw-Hill, New York, (1973).
- [8] D. C. Montgomery and D. A. Tidman, *Plasma kinetic Theory*, McGraw-Hill, New York, (1964).
- [9] V. D. Shafranov, *Review of Plasma Physics*, Vol. II, pp. 103, Consultants Bureau, New York, (1966).
- [10] B. B. Kadomtsev, *Review of Plasma Physics*, Vol. II, pp. 153, Consultants Bureau, New York, (1966).
- [11] I. E. Tamm, *Plasma Physics and the Problem of Controlled Thermonuclear Reactions*, Vol. I, pp. 1, Pergamon Press, Oxford, (1961).

- [12] A. D. Sakharov. *Plasma Physics and the Problem of Controlled Thermonuclear Reactions*, Vol. I, pp. 21, Pergamon Press, Oxford, (1961).
- [13] I. E. Tamm, *Plasma Physics and the Problem of Controlled Thermonuclear Reactions*, Vol. I, pp. 35, Pergamon Press, Oxford, (1961).
- [14] <http://www.efda.org/>.
- [15] F. Troyon et al., Nucl. Fusion 23, 1475 (1983).
- [16] F. Troyon et al., Plasma Physics and Controlled Fusion 26, 209 (1984).
- [17] Y. M. Li, S. M. Mahajan, and D. W. Ross, Phys. Fluids 30, 1466 (1987).
- [18] G. Y. Fu, Ph.D. thesis, The University of Texas at Austin, 1988.
- [19] G. Y. Fu, J. W. Van Dam, M. N. Rosenbluth, D. W. Ross, Y. Z. Zhang, H. L. Berk, S. M. Mahajan, C. Z. Cheng, R. L. Miller, X. H. Wang, A. Bhattacharjee, M. E. Mauel, and B. Breizman, in Plasma Physics and Controlled Nuclear Fusion Research 1988, Proceedings of the 12th International Conference, Nice, France (IAEA, Vienna, in press).
- [20] C. Z. Cheng, G. Y. Fu, and J. W. Van Dam, in Theory of Fusion Plasmas 1988, edited by J. Vaclavik, F. Troyon, and E. Sindoni (Societa Italiana di Fisica/Editrice Compositori, Bologna, 1989), p. 259.
- [21] G. Y. Fu and J. W. Van Dam, Phys. Fluids B 1, 1949 (1989).
- [22] Ya.I. Kolesnichenko, Nucl. Fusion 20 727 (1980).
- [23] S. D. Pinches, *Nonlinear interaction of fast particles with Alfvén waves in tokamaks*, Ph.D. thesis, University of Nottingham, 1996, <http://www.rzg.mpg.de/sip/thesis/node1.html>.
- [24] L. F. Ruchko, M. C. R. Andrade and R. M. O. Galvão, Nucl. Fusion 36 (1996) 503.
- [25] L. F. Ruchko, E. Ozono, R. M. O. Galvão, I.C. Nascimento, F.T. Degasperis and E. Lerche, Fusion Engineering and Design 43 (1998) 15-28.

- [26] R. M. O. Galvão, A. G. Elfimov, G. Amarante-Segundo, V. S. Tsypin, L. F. Ruchko, I. C. Nascimento and M. Tendler, *Plasma Phys. Control. Fusion* 41 (1999).
- [27] L. F. Ruchko, et al., *Brazilian Journal of Physics*, vol 32, n0.1, (2002).
- [28] A. G. Elfimov, R. M. O. Galvão, S. A. Galkin, A. A. Ivanov and S. Yu. Medveded, *Brazilian Journal of Physics*, vol. 32, no. 1, (2002).
- [29] R. M. O. Galvão, et al., *Problems of Atomic Science and Technology. No 4. Series: Plasma Physics (7)*. P. 18-23, 2002.
- [30] A. G. Elfimov, E. A. Lerche, R. M. O. Galvão, L. F. Ruchko, A. M. M. Fonseca, R. P. da Silva, and V. Bellintani, *Brazilian Journal of Physics*, vol. 34, no. 4B, December, 2004.
- [31] L. F. Ruchko, et al., *Brazilian Journal of Physics*, vol. 34, no. 4B, December, 2004.
- [32] G. Elfimov, et al., *Nucl. Fusion* 46 (2006).
- [33] L. F. Ruchko, et al., *Review of Scientific Instruments* 82, 023504 (2011).
- [34] R. B. Michie, *Alfvén Wave Experiments on the Pretext Tokamak*, Ph.D. thesis, University of Texas at Austin, (1983).
- [35] A. Fasoli, et al., *Nucl. Fusion* 35, 1485, (1995).
- [36] A. Fasoli, et al., *Phys. Rev. Lett.* 75, 645, (1995).
- [37] A. Fasoli, et al., *Phys. Rev. Lett.* 76, 1067, (1996).
- [38] A. Fasoli, et al., *Plasma Phys. Control. Fusion* 39, B287, (1997).
- [39] A. Fasoli, et al., *Plasma Physics and Controlled Fusion* 52, 075015, (2010).
- [40] E. A. Lerche, *Desenvolvimento e caracterização dos sistemas de alimentação e diagnóstico para excitação de ondas de Alfvén no tokamak TCABR*, University of São Paulo, Physics Institute, Brazil, (1998).

- [41] G. T. A. Huysmans, J. P. Goedbloed and W. Kerner, *Physics of Fluids B: Plasma Physics*, 5, 1545, (1993).
- [42] G. T. A. Huysmans, J. P. Goedbloed and W. Kerner, in *Proc. Second international Conference on Computational Physics*, Amsterdam, 10-14 September 1990, ed. A. Tenner (Singapore, World Scientific, 1991), 371-376.
- [43] G. T. A. Huysmans, J. P. Goedbloed, and W. Kerner, *Proc. CP90 Conf. on Comp. Phys. Proc.*, World Scientific Publ. Co., 1991, p. 371, *Isoparametric Bicubic Hermite Elements for Solution of the Grad-Shafranov Equation*.
- [44] H. Alfvén, *Existence of electromagnetic-hydrodynamic waves*, *Nature*, Vol. 150, pp. 405, (1942).
- [45] D. Melrose, *Instabilities in space and laboratory plasma*, Cambridge University Press, Cambridge, (1986).
- [46] W. Grossmann and J. Tataronis, *Z. Phys.* 261, 217 (1973).
- [47] A. Hasegawa and L. Chen, *Phys. Rev. Lett.* 32, 454 (1974).
- [48] L. Chen and A. Hasegawa, *Phys. Fluids* 17, 1399 (1974).
- [49] D. R. Nicholson, *Introduction to plasma theory*, John Wiley & Sons, (1983).
- [50] J. P. Goedbloed, *Lecture notes on ideal magnetohydrodynamics*, Lectures at Universidade Estadual de Campinas, Brazil, 1978, Report Instituto de Física (1979); Rijnhuizen Report (1983) 83-145.
- [51] S. I. Braginskii, *Transport processes in a plasma*, *Rev. Plasma Phys.* 1, 205-311, (1965).
- [52] J. P. Freidberg, *Ideal magnetohydrodynamics*, Plenum press, New York and London, (1987).
- [53] N. F. Cramer, *The physics of Alfvén waves*, Wiley-VCH, Berlin, (2001).

- [54] J. F. Denisse and J. L. Delcroix, *Plasma waves*, Interscience Publishers, New York, (1963).
- [55] D. G. Swanson, *Plasma waves*, Academic Press, INC., San Diego CA, (1989).
- [56] S. Ohsaki¹ and S. M. Mahajan, Phys. Plasmas 11, 898 (2004).
- [57] E. Hameiri, A. Ishizawa and A. Ishida, Phys. Plasmas 12, 072109 (2005).
- [58] M. J. Lighthill, Phil. Trans. R. Soc. Lond. A, vol. 252, no. 1014, 397-430, (1960).
- [59] R. Cross, *An introduction to Alfvén waves*, The Adam Hilger Series on Plasma Physics, Philadelphia, (1988).
- [60] Z. Yoshida, S. M. Mahajan and S. Ohsaki, Phys. Plasmas 11, 3660 (2004).
- [61] J. A. Bittencourt, *Fundamentals of plasma physics*, Springer, New York, (2004).
- [62] J. P. Goedbloed, R. Keppens and S. Poedts, *Advanced magnetohydrodynamics with applications to laboratory and astrophysical plasmas*, Cambridge university press, Cambridge, (2010).
- [63] V. L. Ginzburg, *Propagation of Electromagnetic Waves in Plasma*, Gordon and Breach, New York, (1961).
- [64] K. Appert, *Theorie des plasma chauds*, École Polytechnique Fédérale de Lausanne, Lausanne, (2004).
- [65] K. Appert, R. Gruber and J. Vaclavik, Phys. Fluids 17 (1974) 1471.
- [66] K. Appert, R. Gruber, F. Gruber and J. Vaclavik, Plasma Phys. 24 (1982) 1147.
- [67] K. Appert, J. Vaclavik and L. Villard, *Introduction to the theory of Alfvén wave heating*, CRPP Report, LRP 238/84 (1984).
- [68] K. Appert and J. Vaclavik, Plasma Phys. 25 (1983) 551.
- [69] T. H. Stix, *The theory of plasma waves*, McGraw-Hill, New York, (1962).

- [70] B. Balet, K. Appert and J. Vaclavik, *Plasma Phys.* 24 (1982) 1005.
- [71] M. Abramowitz and I. A. Stegun, *Handbook of mathematical functions: With formulars, graphs, and mathematical tables*, Dover, New York, (1965).
- [72] B. G. Korenev, *Bessel functions and their applications*, Taylor & Francis, London and New York, (2002).
- [73] D. W. Ross, Yanming LI, S. M. Mahajan and R.B. Michie, *Nucl. Fusion* 26 (1986) 139.
- [74] Y. L. Luke, *Mathematical functions and their approximations*, Academic Press, 22 New York, (1975).
- [75] W. K. H. Panofsky and M. Phillips, *Classical Electricity and Magnetism*, 2nd ed., Addison-Wesley, Reading, MA, (1962).
- [76] L. Villard, K. Appert, R. Gruber and J. Vaclavik, *Phys. Computer Physics, Reports* 4, (1986) 95-135.
- [77] E. M. Barston, K. Appert, *Ann. Phys.* 29, 282 (1964).
- [78] Z. Sedacek, *J. Plasma Phys.* 5, 239 (1971).
- [79] H. Goedbloed and S. Poedts, *Principles of magnetohydrodynamics with applications to laboratory and astrophysical plasmas*, Cambridge university press, Cambridge, (2004).
- [80] A. Hasegawa and C. Uberoi, *The Alfvén wave*, Technical Information Center, United States Departament of energy, Washington, DC (1982).
- [81] J. D. Huba, *NRL Plasma Formulary*, Naval Research Laboratory, (2007).
- [82] D. W. Ross, G. L. Chen and S. M. Mahajan, *Phys. Fluids* 25 (1982) 652.
- [83] W. W. Heidbrink, *Physics of Plasma* 15, 055501 (2008).
- [84] C. Z. Cheng and M. S. Chance, *Phys. Fluids* 29 (1986) 3695.

- [85] G. A. Collins, F. Hofmann, B. Joye, R. Keller, A. Lietti, J. B. Lister, and A. Pochelon, *Phys. Fluids* 29 (7), (1986).
- [86] T. Panis, *Direct measurements of the damping of Alfvén eigenmodes for an assessment of their stability limits in Tokamak plasmas*, École Polytechnique Fédérale de Lausanne, (2010).
- [87] A. De Chambrier, et al., Center de Recherches en Physique des Plasmas, Lausanne, Report LRP 195/81, (1982).
- [88] S. M. Mahajan, D. W. Ross and G. L. Chen, *Phys. Fluids* 26, 2195 (1983).
- [89] P. H. Rebut and the JET Team, Plasma Physics and Controlled Nuclear Fusion Research 1984, Proceedings of the 10th International Conference London (International Atomic Energy Agency, Vienna, 1985), Vol. 1, p. 11.
- [90] W. Kerner, D. Borba, A. Fasoli, C. Gormenzano, G. Huysmans, F. Porcelli, S. Sharapov, and D. Start, Proceedings of the 21th EPS Conference on Controlled Fusion and Plasma Physics, Montpellier, 1994, edited by E. Joffrin P. Platz and P. E. Stott (The European Physical Society, Petit-Lancy, Switzerland, 1994), Vol. 18b, Part II, p.612.
- [91] W. Grossman and J. Tataronis, *Z. Phys.* 261, 217, (1973).
- [92] A. De Chambrier, et al., *Plasma Phys.*, 24 893, (1982).
- [93] E.M.Ozono, *Desenvolvimento do sistema de excitação de ondas de Alfvén no TCABR*, PhD thesis, IFUSP, 2000.
- [94] P. G. P. P. Puglia, et al., *Physics of Plasmas* 21, 122509 (2014).
- [95] www.euro-fusion.org/jet/.
- [96] www-jt60.naka.jaea.go.jp/english/index-e.html.
- [97] D. Testa, et al., *Nucl. Fusion* 50 084010 (2010).
- [98] P. H. Titus, et al., *Fusion Science and Technology* 47, 931, 2005.

- [99] C. Amado, Private Communication.
- [100] M. Kubič, *Review of plasma parameters of the JET tokamak in various regimes of its operation*, Czech Technical University Faculty of Nuclear Sciences and Physical Engineering Department of Physics, (2007).
- [101] A. W. Kerner, S. Poedts, J. P. Goedbloed, G. T. A. Huysmans, B. Keegan and E. Schwarz, 18th EPS Conference on Controlled Fusion and Plasma Physics, Berlin, 1991, edited by P. Bachmann and D. C. Robinson (The European Physical Society, Petit-Lancy, Switzerland, 1991), Vol. 15, Part IV, p.89.
- [102] A. W. Kerner, J. P. Goedbloed, G. T. A. Huysmans, S. Poedts and E. Schwarz, J. Comp. Physics 142 (1998), 271-303.
- [103] S. Poedts, H. A. Holties, J. P. Goedbloed, G. T. A. Huysmans, and A. W. Kerner, *CASTOR Installation and User Guide*, Rijnhuizen Report 96-229, January 1996.
- [104] G. T. A. Huysmans, Ph.D. thesis, Vrije Universiteit Amsterdam, 1991, *External resistive modes in tokamaks*.
- [105] G. T. A. Huysmans, W. Kerner, D. Borba, H. A. Holties, and J. P. Goedbloed, Phys. Plasma 2 (5), pp. 1605-1613, (1995).
- [106] G. Strang, and G. J. Fix, *An analysis of the finite element method*, 1973, Prentice Hall, Englewood, N. J..
- [107] S. Poedts, H. A. Holties, J. P. Goedbloed, G. T. A. Huysmans, and A. W. Kerner, *HELENA Installation and User Guide*, Rijnhuizen Report 96-229, January 1996.
- [108] H. R. Schwarz, *Finite Element Methods*, Academic press, London, 1988.
- [109] J. N. Reddy, *An Introduction to the Finite Element Method*, McGraw-Hill series in mechanical Engineering, 2nd. ed., New York, 1993.
- [110] R. Gruber, F. Troyon, D. Berger, L. C. Bernard, S. Rousset, R. Schreiber, W. Kerner, W. Schneider, and K. V. Roberts, *ERATO stability code*, Comput. Phys. Commun., 21, 323-371, (1981).

- [111] W. D. D’haeseleer, W. N. G. Hitchon, J. D. Callen, and J. L. Shohet, *Flux Coordinates and Magnetic Field Structure: A Guide to a Fundamental Tool of Plasma Theory*, Copyrighted by Springer-Verlag, Berlin Heidelberg, 1991.
- [112] W. Kerner, *Large-scale complex eigenvalue problems*, J. Comp. Phys., 85, (1989).
- [113] J. P. Goedbloed, H. A. Holties, S. Poedts, G. T. A. Huysmans and W. Kerner, Plasma Phys. Control. Fusion, 35, B277-B292, (1993).
- [114] J. P. Goedbloed, *Conformal mapping methods in two-dimensional magnetohydrodynamics*, Comp. Phys. Comm., 24, 311-321 (1981).
- [115] G. T. A. Huysmans, R. M. O. Galvão, and J. P. Goedbloed, Rijnhuizen Report 90-194, 1990, *Documentation of the high beta stability codes HBT and HBTAS at JET*.
- [116] S. A. Galkin, A. A. Ivanov, S. Yu. Medveded and A. G. Elfimov, Computer Physics Communication 143 (2002), 29-47.
- [117] D. Testa, et al., <http://infoscience.epfl.ch/record/143354/>, (2004).
- [118] G. T. A. Huysmans, H. A. Holties, and J. P. Goedbloed, *Analysis of global Alfvén modes by the extension of CASTOR with an external antenna*, Rijnhuizen Report 93-219, December (1993).
- [119] A. J. A. C. Beliën, M. A. Botchev, J. P. Goedbloed, B. van der Holst and R. Keppens, J. Comp. Physics 182 (2002), 91-117.
- [120] J. W. S. Blokland, B. van der Holst, R. Keppens and J. P. Goedbloed, J. Comp. Physics 226 (2007), 509-533.
- [121] F. F. Chen, *Introduction to plasma physics and controlled fusion*, 2nd ed., Springer, (2006).
- [122] H. G. Booker, *Cold plasma waves*, Martinus Nijhoff Publishers, (1984).
- [123] T. G. Cowling, *Magnetohydrodynamics*, Interscience Publishers, INC., New York (1957).

- [124] L. Spitzer, *Física de los gases totalmente ionizados*, Editorial Alhambra, S. A., (1969).
- [125] G. Schmidt, *Physics of high temperature plasma*, 2nd ed., Academic Press, (1979).
- [126] C. L. Longmire, *Elementary plasma physics*, Interscience, New York (1963).
- [127] Reviews of Plasma Physics. vol 2 ed by M.A. Leontovich (Consultants Bureau, New York 1966).
- [128] K. Miyamoto, *Plasma Physics for Nuclear Fusion*, The MIT Press, Cambridge, Mass. (1989).
- [129] S. Jardin, *Computational Methods in Plasma Physics*, CRC Press, (2010).

Appendix A

Vectorial identities

$$\vec{a} \cdot (\vec{b} \times \vec{c}) = \vec{c} \cdot (\vec{a} \times \vec{b}) = \vec{b} \cdot (\vec{c} \times \vec{a}), \quad (\text{A.1})$$

$$\vec{a} \times (\vec{b} \times \vec{c}) = \vec{a} \cdot \vec{c} \vec{b} - \vec{a} \cdot \vec{b} \vec{c}, \quad (\vec{a} \times \vec{b}) \times \vec{c} = \vec{a} \cdot \vec{c} \vec{b} - \vec{b} \cdot \vec{c} \vec{a}, \quad (\text{A.2})$$

$$\nabla \times \nabla \Phi = 0, \quad (\text{A.3})$$

$$\nabla \cdot (\nabla \times \vec{a}) = 0, \quad (\text{A.4})$$

$$\nabla \times (\nabla \times \vec{a}) = \nabla \nabla \cdot \vec{a} - \nabla^2 \vec{a}, \quad (\text{A.5})$$

$$\nabla \cdot (\Phi \vec{a}) = \vec{a} \cdot \nabla \Phi + \Phi \nabla \cdot \vec{a}, \quad (\text{A.6})$$

$$\nabla \times (\Phi \vec{a}) = \nabla \Phi \times \vec{a} + \Phi \nabla \times \vec{a}, \quad (\text{A.7})$$

$$\vec{a} \times (\nabla \times \vec{b}) = (\nabla \cdot \vec{b}) \vec{a} - \vec{a} \cdot \nabla \vec{b}, \quad (\text{A.8})$$

$$(\vec{a} \times \nabla) \times \vec{b} = (\nabla \cdot \vec{b}) \vec{a} - \vec{a} \nabla \cdot \vec{b}, \quad (\text{A.9})$$

$$\begin{aligned} \nabla(\vec{a} \cdot \vec{b}) &= (\nabla \vec{a}) \cdot \vec{b} + (\nabla \vec{a}) \cdot \vec{a} \\ &= \vec{a} \cdot \nabla \vec{b} + \vec{b} \cdot \nabla \vec{a} + \vec{a} \times (\nabla \times \vec{b}) + \vec{b} \times (\nabla \times \vec{a}), \end{aligned} \quad (\text{A.10})$$

$$\nabla \cdot (\vec{a} \vec{b}) = \vec{a} \cdot \nabla \vec{b} + \vec{b} \cdot \nabla \vec{a}, \quad (\text{A.11})$$

$$\nabla \cdot (\vec{a} \times \vec{b}) = \vec{b} \cdot \nabla \times \vec{a} - \vec{a} \cdot \nabla \times \vec{b}, \quad (\text{A.12})$$

$$\nabla \times (\vec{a} \times \vec{b}) = \nabla \cdot (\vec{b} \vec{a} - \vec{a} \vec{b}) = \vec{a} \nabla \cdot \vec{b} + \vec{b} \cdot \nabla \vec{a} - \vec{b} \nabla \cdot \vec{a} - \vec{a} \cdot \nabla \vec{b}, \quad (\text{A.13})$$

Appendix B

Magnetic coordinates and the (s, θ, ϕ) coordinate system

The behavior of the MHD equations in the direction normal to the flux surfaces is very different from the in plane direction. The ideal MHD equations exhibit a singularity in the direction perpendicular to the flux surfaces. In resistive MHD these singularities are resolved but the modes still show large gradients near an ideal singular surface. So, for an accurate representation of the mode structure in our system, it is essential to use a coordinate system which are suitable to represent our problem.

In this appendix, we will see briefly, the magnetic coordinates in the case of cylindrical geometry, which are suitable for systems with symmetry of helical magnetic field, and the (s, θ, ϕ) coordinate system in the case of toroidal geometry, which use the function of the flux as a radial coordinate.

B.1 The magnetic coordinates

Firstly, we shall write the Maxwell equations in the orthogonal right-handed curvilinear coordinate system

$$\hat{e}_r, \quad \hat{e}_\perp = \hat{e}_\parallel \times \hat{e}_r, \quad \hat{e}_\parallel = \frac{\vec{B}_0}{B_0}. \quad (\text{B.1})$$

Any vector in this system has the representation

$$\vec{A} = A_r \hat{e}_r + A_\perp \hat{e}_\perp + A_\parallel \hat{e}_\parallel = \sum_\mu A_\mu \hat{e}_\mu. \quad (\text{B.2})$$

For Maxwell's equations we will need

$$\nabla \times \vec{A} = \sum_\mu (A_\mu \nabla \times \hat{e}_\mu - \hat{e}_\mu \times \nabla A_\mu). \quad (\text{B.3})$$

Since the equilibrium is specified in cylindrical coordinates, $(\hat{e}_r, \hat{e}_\theta, \hat{e}_z)$, we need the transformation formulae between the latter and the magnetic coordinates (B.1). Projection of $\hat{e}_\theta$ and $\hat{e}_z$ onto the system (B.1) yields to first order in $|\frac{B_{0\theta}}{B_0}|$

$$\hat{e}_\theta = \hat{e}_\perp + \frac{B_{0\theta}}{B_0} \hat{e}_\parallel, \quad (\text{B.4})$$

$$\hat{e}_z = -\frac{B_{0\theta}}{B_0} \hat{e}_\perp + \hat{e}_\parallel. \quad (\text{B.5})$$

Likewise, projection of $\hat{e}_\perp$ and $\hat{e}_\parallel$ onto the cylindrical system produces

$$\hat{e}_\perp = \hat{e}_\theta - \frac{B_{0\theta}}{B_0} \hat{e}_z, \quad (\text{B.6})$$

$$\hat{e}_\parallel = \frac{B_{0\theta}}{B_0} \hat{e}_\theta + \hat{e}_z. \quad (\text{B.7})$$

Next we need the $\nabla \times$ of the basis vectors, (B.1). A simple way is to go via

$$\nabla \times \hat{e}_r = 0, \quad \nabla \times \hat{e}_\theta = \frac{\hat{e}_z}{r}, \quad \nabla \times \hat{e}_z = 0. \quad (\text{B.8})$$

To first order in $|\frac{B_{0\theta}}{B_0}|$ we find from (B.7) and (B.8) using (B.3)

$$\nabla \times \hat{e}_\perp = \nabla \times \hat{e}_\theta + \hat{e}_z \times \nabla \frac{B_{0\theta}}{B_0} = r \left(\frac{d}{dr} \left(\frac{1}{r} \frac{B_{0\theta}}{B_0} \right) \right) \hat{e}_\perp + \frac{1}{r} \hat{e}_\parallel, \quad (\text{B.9})$$

$$\nabla \times \hat{e}_\parallel = \frac{B_{0\theta}}{B_0} \nabla \times \hat{e}_\theta - \hat{e}_\theta \times \nabla \frac{B_{0\theta}}{B_0} = \frac{1}{r} \left(\frac{d}{dr} \left(r \frac{B_{0\theta}}{B_0} \right) \right) \hat{e}_\parallel. \quad (\text{B.10})$$

The gradient ∇ acting on the perturbed quantities is $(\frac{d}{dr}, i\frac{m}{r}, ik_z)$ in cylindrical coordinates and $(\frac{d}{dr}, ik_\perp, ik_\parallel)$ in magnetic coordinates, if can define

$$k_\perp = \frac{m}{r} - k_z \frac{B_{0\theta}}{B_0}, \quad k_\parallel = \frac{B_{0\theta}}{B_0} \frac{m}{r} + k_z. \quad (\text{B.11})$$

We can now obtain $\nabla \times \vec{A}$ in magnetic coordinates by using the equations (B.3), (B.4), (B.5), (B.9), (B.10), and (B.11). In components we have with correct up to first order in $|\frac{B_{0\theta}}{B_0}|$

$$(\nabla \times \vec{A})_r = ik_{\perp} A_{\parallel} - ik_{\parallel} A_{\perp}, \quad (\text{B.12})$$

$$(\nabla \times \vec{A})_{\perp} = ik_{\parallel} A_r - \frac{d}{dr}(A_{\parallel}) + r \frac{d}{dr} \left(\frac{1}{r} \frac{B_{0\theta}}{B_0} \right) A_{\perp}, \quad (\text{B.13})$$

$$(\nabla \times \vec{A})_{\parallel} = \frac{1}{r} \frac{d}{dr}(r A_{\perp}) - ik_{\perp} A_r + \frac{1}{r} \frac{d}{dr} \left(r \frac{B_{0\theta}}{B_0} \right) A_{\parallel}. \quad (\text{B.14})$$

B.2 The (s, θ, ϕ) coordinate system

With the purpose of have the function of the flux as a radial coordinate, we take the two angular coordinates such that the magnetic field lines appears straight. With this choice we still have the freedom to choose one of the angular coordinate, therefore if one of the angles is taken to be the usual toroidal angle ϕ of the (R, Z, ϕ) cylindrical coordinate system, then the poloidal coordinate of the straight field line system, θ , must be determined such that the field lines are straight in the (θ, ϕ) plane, whereby

$$\frac{d\phi}{d\theta} = q(\psi), \quad (\text{B.15})$$

where q denotes the safety factor and has dependence on ψ which denotes the poloidal flux.

The covariant and contravariant coordinate system are defined by

$$\begin{aligned} \vec{a}^1 &= \nabla s & \vec{a}_1 &= \mathbf{J} \nabla \theta \times \nabla \phi, \\ \vec{a}^2 &= \nabla \theta & \vec{a}_2 &= \mathbf{J} \nabla \phi \times \nabla s, \\ \vec{a}^3 &= \nabla \phi & \vec{a}_3 &= \mathbf{J} \nabla s \times \nabla \theta, \end{aligned} \quad (\text{B.16})$$

where the radial coordinate s is given by $\nabla \psi = f(s) \nabla s$, J is the Jacobian of the (s, θ, ϕ) coordinate system. The metric coefficients g^{ij} and g_{ij} are given by

$$\begin{aligned} g^{11} &= |\nabla s|^2 & g_{11} &= \frac{J^2}{R^2} |\nabla \theta|^2, \\ g^{12} &= \nabla s \cdot \nabla \theta & g_{12} &= -\frac{J^2}{R^2} \nabla s \cdot \nabla \theta, \\ g^{22} &= |\nabla \theta|^2 & g_{22} &= \frac{J^2}{R^2} |\nabla s|^2, \\ g^{33} &= |\nabla \phi|^2 = \frac{1}{R^2} & g_{33} &= R^2. \end{aligned} \quad (\text{B.17})$$

In this coordinates system, a field line can be represented by

$$\frac{dl_\phi}{dl_p} \equiv \frac{\sqrt{g_{33}}d\phi}{\sqrt{g_{22}}d\theta} = \frac{B_\phi}{B_p}, \quad (\text{B.18})$$

where B_ϕ and B_p are the physical components in the toroidal and poloidal direction.

Using B.15, we obtain an expression of the poloidal arclength in terms of the angle θ

$$dl_p = \frac{B_p}{B_\phi} R q d\theta, \quad \text{or} \quad \theta = \int \frac{F}{qR|\nabla\psi|} dl_p, \quad \text{where} \quad F = RB_\phi, \quad (\text{B.19})$$

and an expression for the Jacobian

$$J = \frac{fqR^2}{F}. \quad (\text{B.20})$$

Appendix C

New JET antenna spectrum

In this appendix, we present the spectrum created by the new JET antenna in the vacuum, relating the absolute value of the total current density of the antenna for each toroidal mode with a particular combination of phase between the eight modules.

Figure C.1: Spectrum created by eight modules of the new JET antenna (a) with phases $[0^\circ, 0^\circ, 0^\circ, 0^\circ, 0^\circ, 0^\circ, 0^\circ, 0^\circ]$ (b) with phases $[180^\circ, 180^\circ, 180^\circ, 180^\circ, 180^\circ, 180^\circ, 180^\circ, 180^\circ]$.

Figure C.2: Spectrum created by eight modules of the new JET antenna (a) with phases $[0^\circ, 0^\circ, 0^\circ, 0^\circ, 180^\circ, 180^\circ, 180^\circ, 180^\circ]$ (b) with phases $[180^\circ, 0^\circ, 180^\circ, 0^\circ, 180^\circ, 0^\circ, 180^\circ, 0^\circ]$.

Figure C.3: Spectrum created by eight modules of the new JET antenna (a) with phases $[180^\circ, 180^\circ, 0^\circ, 0^\circ, 0^\circ, 0^\circ, 180^\circ, 180^\circ]$ (b) with phases $[0^\circ, 180^\circ, 180^\circ, 0^\circ, 0^\circ, 180^\circ, 180^\circ, 0^\circ]$.

If we used the factor $e^{-i\frac{n_0}{R}z_i}$ as the current phase where n_0 is the toroidal mode that want excite, the spectrum the new JET antenna will be altered, optimizing with respect to the required mode.

Figure C.4: Spectrum with $e^{-i\frac{n_0}{R}z_i}$ phasing (a) optimizing $n_0 = 3$ (b) optimizing $n_0 = 8$.

Figure C.5: Spectrum with $e^{-i\frac{n_0}{R}z_i}$ phasing (a) optimizing $n_0 = 10$ (b) optimizing $n_0 = 15$.

Appendix D

Figures of TAEs results

D.0.1 Resonant mode $n_0 = 3$

Figure D.1: Radial profile created by eight modules of the new JET antenna for mode $n = 1$. (a) unoptimized phases, (b) phases optimized for $n_0 = 3$. We see that the intensity decreases slightly by a factor 0.98.

Figure D.2: Radial profile created by eight modules of the new JET antenna for mode $n = 7$. (a) unoptimized phases, (b) phases optimized for $n_0 = 3$. We see that the intensity increases by a factor 1.27.

D.0.2 Resonant mode $n_0 = 9$

Figure D.3: Radial profile created by eight modules of the new JET antenna for mode $n = 5$. (a) unoptimized phases, (b) phases optimized for $n_0 = 9$. We see that the intensity increases slightly by a factor 1.06.

Figure D.4: Radial profile created by eight modules of the new JET antenna for mode $n = 7$. (a) unoptimized phases, (b) phases optimized for $n_0 = 9$. We see that the intensity increases by a factor 1.38.

Figure D.5: Radial profile created by eight modules of the new JET antenna for mode $n = 11$. (a) unoptimized phases, (b) phases optimized for $n_0 = 9$. We see that the intensity increases by a factor 2.65.

Figure D.6: Radial profile created by eight modules of the new JET antenna for mode $n = 13$. (a) unoptimized phases, (b) phases optimized for $n_0 = 9$. We see that the intensity increases by a factor 4.71.

D.0.3 Resonant mode $n_0 = 10$

Figure D.7: Radial profile created by eight modules of the new JET antenna for mode $n = 6$. (a) unoptimized phases, (b) phases optimized for $n_0 = 10$. We see that the intensity increases by a factor 1.15.

Figure D.8: Radial profile created by eight modules of the new JET antenna for mode $n = 8$. (a) unoptimized phases, (b) phases optimized for $n_0 = 10$. We see that the intensity increases by a factor 1.55.

Figure D.9: Radial profile created by eight modules of the new JET antenna for mode $n = 12$. (a) unoptimized phases, (b) phases optimized for $n_0 = 10$. We see that the intensity increases by a factor 3.5.

Figure D.10: Radial profile created by eight modules of the new JET antenna for mode $n = 14$. (a) unoptimized phases, (b) phases optimized for $n_0 = 10$. We see that the intensity increases by a factor 8.38.

D.0.4 Resonant mode $n_0 = 11$

Figure D.11: Radial profile created by eight modules of the new JET antenna for mode $n = 7$. (a) unoptimized phases, (b) phases optimized for $n_0 = 11$. We see that the intensity increases by a factor 1.27.

Figure D.12: Radial profile created by eight modules of the new JET antenna for mode $n = 9$. (a) unoptimized phases, (b) phases optimized for $n_0 = 11$. We see that the intensity increases by a factor 1.79.

Figure D.13: Radial profile created by eight modules of the new JET antenna for mode $n = 13$. (a) unoptimized phases, (b) phases optimized for $n_0 = 11$. We see that the intensity increases by a factor 5.1.

Figure D.14: Radial profile created by eight modules of the new JET antenna for mode $n = 15$. (a) unoptimized phases, (b) phases optimized for $n_0 = 11$. We see that the intensity increases by a factor 30.9.